

A Database Publication

# ATARI USER

Vol. 1 No. 2

June 1985

£1

**Electronic  
Mail —  
we keep  
you posted**

**FROG  
JUMP**

Full listing of  
the classic game

**XE** In-depth appraisal of  
Atari's latest machine

## Atari Insights

Write your  
own programs

Getting to grips  
with binary

Synchronise  
your sound





# COME ATARI USER MAGAZINE.

ATARI USER, STOP HERE.)

A choice of a 1050 Disk Drive or a 1010 Cassette Programmer Recorder and additional software.

No one else could offer you all this power at these prices.

And, as everything comes together, you can make the most of the unbeatable ATARI 800XL straight away.

Without doubt, ATARI Personal Computer Packs are the easiest way to get into computers.

The only difficulty is deciding which one. Now read on.



Part C: 800XL,  
1040 Cassette Programmer Recorder,  
Tutorial by Programming Plus Pack,  
Demonstration Software £129.99 (Normal cost £164.95)

ONAL COMPUTER PACKS



Vol. 1 No. 2 June 1985

Managing Editor: **Derek Macklin**  
Features Editor: **Chris McKnight**

Editorial Team:  
**Mike Bibby**  
**Alan McLeish**  
**Kevin Edwards**  
**Pete Bibby**

Production Editor: **Peter Glover**  
Layout Design: **Heather Sheldrick**  
News Editor: **Mike Conway**

Advertising Manager: **John Ridding**  
Advertising Sales: **John Snowden**  
Editor in Chief: **Peter Brumfield**

Editorial: 041-458 0835  
Administration: 041-458 0383  
Advertising: 041-458 0500  
Subscriptions: 041-480 0173  
Telex: 687854 BHAH11G  
Postal Mailing: 614555283

Published by:  
**Databases Publications Ltd,**  
Europe House, 68 Charter Road,  
Harold Grove, Stockport SK7 5NY.

Subscription rates for  
12 issues, post free:

£12 - UK  
£15 - Eire (Selling only)  
£20 - Rest of world (surface)  
£30 - Rest of world (airmail)

**AT&T** Membership  
Bureau of Circulation

"Atari User" assumes program listings and articles for publication. Material should be typed or computer-printed, and preferably double-spaced. Program listings should be accompanied by cassette tape or disc. Please include a stamped, self-addressed envelope, otherwise the return of material cannot be guaranteed. Contributions accepted for publication by Databases Publications Ltd will be on an all-rights basis.

© 1985 Databases Publications Ltd. No material may be reproduced in whole or in part without written permission. While every care is taken, the publishers cannot be held legally responsible for any errors in articles, lists or other information.

"Atari User" is an independent publication and Atari Corp. USA Ltd are not responsible for any of the articles in this issue or for any of the opinions expressed.

Stock trade distribution:  
European Sales and Distribution (UK) Ltd, 11 Belfrage Road, Crawley, West Sussex RH11 6AA. Tel. 0293 27050.

## News

Keep up to date with all the latest news... and who's this reading Atari User?

7

## Beginners

This month Mike Bibby gets you started in writing your own programs. You'll soon be saying "programming is easy".

10

## Analysis

With the Atari 1300X now in the shops, we bring you an analysis of this new machine and present the first program showing how to use the extra memory to good effect.

14

## Software

If it's chess, adventures or arcade games you're thinking of buying, read our reviews first.

20

## Submarine

Play this educational game and see if you can sink the enemy within six moves.

40

## Bit Wise

Do your sums in binary notation with the aid of our regular series on the way the Atari works.

42

## Sounds

It's music, music, music with Pete Bibby's creative use of the SOUND command.



## Random Numbers

If it's a random byte you're in need of, read Kevin Edwards' article - he'll show you how to get one.



Guide the frog across the road and over the river to home in this arcade classic.

## Graphics

Dave Russell continues his series with an introduction to Graphics Modes 1 and 2.

56

## Adventuring

Brillig rehearses the arguments for graphic adventures and we give you a brain-bending puzzle to solve before next month.

50

## Mailbag

Your chance to air your views, ask questions, provide answers, and generally contribute.

59

## Microscope

Take a closer look at this etch-a-sketch program then use it to draw some exciting designs.

52

## Order Form

Take out a subscription for Atari User - at a special introductory offer. Or buy this month's disc of listings.

61

# comms



Some of the most exciting developments in microcomputing are taking place in the field of communications. In this special 12-page section we bring you the low-down on linking your Atari to the outside world.

- Peter Atkinson confesses that he's hooked on hacking.
- Bulletin Boards explained by Peter Tootill, with all the latest Atari-based bulletin board

numbers for you to phone.

- Basilidon, gateway to the world via the ITEC's bulletin board.
- MicroLink, the exciting new micro communications system tailored to your needs. Full details of the service and the facilities it offers can be found in the centre pages.
- Why use serial transmission? Robin Hudson explains.

# ATARI

EUROPE'S LEADING  
'ATARI'  
MAIL ORDER  
SPECIALISTS

**SOFTWARE EXPRESS INTERNATIONAL**

WATCH-OUT FOR FURTHER THRILLING ADVENTURES OF  
CAPTAIN SOFTWARE IN THIS MAGAZINE SOON

1900

SOFTWARE EXPRESS INTERNATIONAL



SEND SAE FOR OUR PRICE LIST.  
31 STONEYHURST ROAD  
EDMINGTON, BIRMINGHAM B24 8HA

**HOTLINE**  
**(021) 384 5080**

# STs on way to whack the Macs

**ANNOUNCED** a major hiccup, the first 520ST machines will be arriving in the UK within days of this issue of *Atari User* hitting the newsstands, and will go on sale shortly afterwards.

And with this initial shipment Atari boss Jack Tramiel will have kept his promise to the UK.

That was that the British would be given the opportunity to buy the 520ST before anyone else in the world.

He gave this undertaking to Atari User when the new machine was unveiled for the International Press Corps at the recent Hannover Fair.

"We want the British to have their first", the Atari boss said. "You see you (the British) are the most computer literate people in the world and, as such, you will have a true appreciation of the ST".

Coming a price tag of £699, the new machine comes with a 500k 3½" floppy disk drive.

It is being seen as a real threat to Apple's £2,000-plus Macintosh.

This is due to the fact that it contains the Gem operating system, which provides it with a Mac environment at a greatly reduced price.

However the 520STs which appeared in Hannover were

offering Gem only on disc.

But the company intends to have it on ROM by the time the machine goes into the shops.

"We have had a few machines out with Gem on disc for development purposes in software houses", said an Atari technical spokesman.

"They will help us identify the bugs so we can eliminate them before offering Gem on ROM at the time the machines get into the UK shops".



Atari 520ST ... don't stir the

## Line up to become a millionaire...

**ATARI** boss Jack Tramiel has promised to train a new breed of UK millionaires — authors of successful software for the new ST range.

"The more there are the better as far as we are concerned", he told Atari User.

This is all part and parcel of the new look Atari's philosophy to call upon third parties to develop the software.

Since he took over at the top, Tramiel has used virtually all the company's programmes — with reports circulating that up to 80 lost their jobs in the United States alone.

"We are now actively promoting third party software for the ST", says Max Barnbridge, Atari's new European head of sales.

"And to help achieve this, we will be supporting software houses in every possible way".

However, the support does not include providing them with free development systems for the ST.

Instead, the software houses have had to pay \$4,500 for the privilege of being able to write programs for the new machine.



Bob Warding ... "companies realize they are backing a winner"

And it seems to be working. According to Bob Warding, Atari UK's sales boss, at least 50 major companies based in the United States are currently writing software for the 520ST.

"It doesn't stop there, either", he says. "For here in Britain companies are also queuing up to pay for development systems".

There is absolutely no doubt now that the ST will be there



Jack Tramiel ... "the more there are the better"

than well supported by good software. After all, the companies realize they are backing a winner.

And the final word from Jack Tramiel ...

"Eventually we would like to see the youngsters in the UK get in on the act."

"What would be better than turning lots of bright, 15-year-old programmers into millionaires..."



**GUESS** who's reading the Atari User? Find out on Page 9.

## Exciting, says W.H. Smith

The Atari 1000 has made a big impression at leading High Street chain W.H. Smith.

The main computer being sold at Smith's top 40 branches has been described by the buying team as 'one of the most exciting new products to be launched this year'.

Atari technicians accompanied the first machines delivered to Smith's and conducted on-the-spot staff training in the stores.

Atari has also set up a help line so that Smith's branch staff can ring with technical problems and customer queries.

W.H. Smith is also expecting big sales of the Atari 1000 program recorder.

The Atari 1000 also drive is being stocked on a trial basis by five branches - Birmingham, Brent Cross, Croydon, Manchester and Stratford.

## Probe into cut price games

LEADING software houses are urgently investigating a mail-order operation offering top-selling games at rock-bottom prices.

Popular Atari titles like Pole Position, Ghostbusters and Jet Set Jack are involved.

The software publishers were alerted by many users who had received in the post an offer from a firm calling itself A1 Software Services of Hainthorpe, Essex.

The mail shot invited people to choose one game from a list of 30 well-known titles which

would then be theirs for only the cost of postage and packing - 25p.

The offer continued: "When you have received your free tape you can buy the following" and gave details of three packs, each containing 15 top games.

Price for one pack was £30, for two packs £30 and for all three £40.

Another version of the mail shot offered a choice of 21 packs containing five games each at prices ranging from £5 for one pack to £30 for 10 packs. The offer stated: "All

titles are the ones from the well-known software houses. All copies are first-class quality and we will exchange any non-readers. Please be very despatched with this list".

Atari then tried to contact A1 Software Services by telephone. Directory inquiries could find no listing in Hainthorpe for the firm, nor for an "A. Craft" named as "proprietor" in the mail shot.

A visitor to the address given found it to be an accommodation agency - a run-down shop.

## SHARING THE GOODIES

THE Commodore disc drive for the 620 ST will eventually be made available - with the appropriate interfaces built in - for other computers.

## Good deal, says Atari

ATARI has hit back at allegations by a prominent UK distribution company that a deal offered by the corporation was "economical suicide".

The claim was made by Joe Woods, sales and marketing director of TBS, after his firm announced that it would no longer be handling Atari hardware.

"Conditions demanded by Atari - in terms of margins and stocking commitment - were quite simply unacceptable", he said.

"In the current market climate it would have been commercial suicide to go along with Atari's proposals."

"Atari has a good product and we took the decision to cease distribution with some reluctance".

Up until the announcement, TBS had in fact been distributing Atari hardware under what the company describes as an "arrangement".

However, it was when TBS pressed Atari for a formalisation of the relationship that the storm blew up.

Over at Atari, Max Rambridge, head of European sales, saw the "problem" in a somewhat different light.

"We made a genuine offer in good faith", he told AT User. "And this was made at the request of the distribution company itself."

"As far as we are concerned, if we are to get into bed with

someone, we need to judge their level of commitment."

"We have a very hot product coming over in the 620 ST and so we intend to do business the right way."

"There is no question that we'll find ourselves in the position of giving the body away with the halfhearted..."

## Heir of the dog

AFTER ditching the popular DOS 2 in favour of the DOS 3, which failed to appeal to users, Atari has now launched the new DOS 3.5.

The 2.5 version has the ability to format both enhanced and single density and is compatible with DOS 2 and 3.

"Our problem was that after DOS 3, which was very popular, DOS 3 turned out to be really a bit of a dog", admitted an Atari technical spokesman.

"So now we have incorporated all that was best in DOS and added a few enhancements and came up with DOS 3.5."

This didn't prevent too many problems as it has been written by the same people who came up with DOS 2.

## Are YOU a first rate PROGRAMMER?

*Then join the Professionals!*

Award-winning Database Software needs more programmers, both for freelance work and permanent positions.

Applicants must be fluent in both Basic and machine code on at least one of the popular micros, and preferably have experience of others.

Experience in the software industry is not essential, but obviously candidates must have written good quality software in the past and samples will be required.

Pay is negotiable, depending on age, experience and qualifications. There are excellent prospects for hard working, skilful programmers.

Please send DAE, CY and an example of your work which will be returned unopened.

to:

Peter Davidson, Software Manager, Database Software, Europe House, 66 Charter Road, Manor Green, Stockport SK7 8BY.

## 130 ST misses Hanover Show

ALTHOUGH the 530 ST dutifully took its bow at the Hanover Show, there was no sign of the 130i version, the 130 ST.

Alan is anyone at Atari prepared to give a firm date as to when the machine will appear.

"It may be at the end of the year or possibly even later," said one Atari UK source. "At the moment we are as much in the dark about it as anybody".

One person who admitted to being disappointed by the absence of the 130 ST at Hanover was Tony Deane, a director of Silex Shop.

"To be quite honest, one of the reasons we came over was in the hope of seeing that particular machine", he said.

"But we believe it will be well worth waiting for".

### Mystery monitor

A RW colour monitor with a built in disc drive made its appearance on the Atari stand at the Hanover Show.

Known as the PS 3000, it carried no price tag and there was no indication of when it would arrive in the UK.

## Good reception

REACTION to the new Atari 130XE has been exceedingly good according to Miss Barnidge, the corporation's European sales and marketing chief.

"It is early days yet, but it is far enough to say we are very pleased with the reception it has had", he told Atari UK.

A major selling point for the 130XE is likely to be the fact that it is able to run all the software currently available for the 800XE — estimated at around 3,000 titles.



## Precision Software rewrites for XE

A LEADING UK software house has jumped on to the Atari bandwagon.

Precision Software has announced it will be rewriting most of its titles for the new Atari 130XE.

However the company is taking its time before launching versions for the 800XE.

Already in the pipeline for the 130XE is the company's well known Superbase range — the Superbase database, SuperScript, a combination of word processor, calculator and mailshot facility, and Superbase, a keyboard trainer.

However the ST version, with extended series of applications templates for Superbase, are not likely to follow immediately.

"If software is made available for the ST (and it is becoming very popular)", said John Tramiel, marketing director at Precision.

"We are certainly looking very keenly at the ST. I myself feel very confident that it will be popular and we have the resources, as we see demand, to

schedule development for it".

Precision Software started its operations in 1980 and since then has produced 18 titles for the C64, 14 for the Apple II.

The company prides itself on specialising in high performance "productivity" software such as word processing and other database products.

These include Base Script and Spell, which have sold 250,000 copies, and Superbase 84, which has sold 70,000.

Reflecting its worldwide market, Precision produces titles in several languages.

Its recent move into the Atari market was explained by Tramiel.

"We sell serious software for the smaller computers", he said, "and because of this most of it goes to the small businessmen who cannot afford more than £1,000 for a system."

"The ST fits into this market. It is extremely well-engineered and its price offers a new level of technology to the serious home user or businessman."

"I think it will be a very successful product".

## Seal of approval from the man at the top

ATARI's Atari has already found its No. 1 fan. He turns out to be none other than Jack Tramiel, the battling boss of the corporation.

Presented with a copy of the first issue of the Hanover Show, the man who intends to do for Atari what he did for Commodore — \$1 billion in sales — gave it his seal of approval.

According to one of his top aides: "We showed it to everybody — and I mean everybody".

In fact, at the request of Atari, copies of the magazine were inserted in all the press packs for the international journalists visiting the corporation's stand at the show.

The launch issue's cover depicted Tramiel's head carved out of stone alongside the likenesses of the four United States presidents to be found at Mount Rushmore.

And this prompted the comment from one US Atari executive: "Gee, I recognise this guy" (looking at Jack). "But who are these other four?"

# Keep y and into



**THIS** month we are going to begin to write our own programs. Nothing spectacular mind, but enough to give you a quiet glow of satisfaction. Finally, let's discuss what we did last month.

We learned that to "talk" to the computer we had to speak to it in a language it already understood, called Basic. We also learned how to get the *Alt* to do sums for us and to print out messages, or things as they are known.

One Basic word we used quite frequently was **PRINT**, which instructs the micro to write or print things out on the screen. For instance, to do the sum  $4+4$  we typed:

**PRINT 4+4 [Return]**

where **[Return]** means you should press the Return key — this sends the message we have typed to the computer. Hopefully it then responds by printing the correct answer, 8.

Similarly, we could do subtraction, multiplication and division — the symbols for which are  $-$ ,  $*$  and  $/$  respectively. Notice particularly the division symbol.

We also learned that to print out messages we had to surround them

with quotes, as we do when recording speech. So, to print the message "GOOD MORNING" on the screen we type:

**PRINT "GOOD MORNING"  
[Return]**

which causes the message to be written on the screen. Now we can use lower case or small letters, so we can print "Good Morning" by using:

**PRINT "Good Morning"  
[Return]**

providing we use our Caps properly. Notice that **PRINT** itself remains in capitals. This is because it is a special Basic word — a keyword. For the *Alt* to realise that it has a special meaning, it must be written in capitals, as must all other Basic words. For the moment, stay in capitals all the time — this will prevent you from falling into this error.

So far we have given the computer one instruction at a time, which is carried out immediately after we pressed Return (assuming we'd typed it correctly).

Sometimes, though, we want to give the micro a series of instructions

and then tell it to carry them out. For instance, suppose we want the message:

**PROGRAMMING  
IS  
EASY**

to appear on the screen. With our step-by-step method, we would have used:

**PRINT "PROGRAMMING"  
[Return]  
PRINT "IS"  
[Return]  
PRINT "EASY"  
[Return]**

But, as you'll see if you try it, this doesn't produce the required effect, since each successive instruction spoils the layout.

We need to give the computer the instructions so that it:

1. Prints out PROGRAMMING
2. Prints out IS
3. Prints out EASY

in sequence, without stopping to ask us what to do next. Such a sequence of instructions is called a program. Notice also that the sequence is numbered — after all, the computer needs to know the order in which to



# your CAPS on you won't fall error!

*Start to write your own programs  
in PART TWO of MIKE BIBBY's  
guide through the micro jungle*

carry them out.

Now let's write a program to print out

## PROGRAMMING IS EASY

We were on the right lines with the first attempt, but this time, let's try numbering our instructions as we enter them.

First of all type:

### NEW [Return]

NEW is a Basic keyword that clears out the computer's memory. If you don't do this the program you are typing in might get jumbled up with a previous one — you'll see more clearly how this can happen later.

You probably think that you haven't got a program in at the moment, but use NEW anyway, because it is possible that you might have entered a line or two by chance.

Then type:

**10 PRINT "PROGRAMMING"  
[Return]**

Notice two things:

- The first instruction is number 10,

not number 1. In computing we tend to number our instructions in steps of ten for reasons that will become blindingly obvious later. We call the number of an instruction its line number.

■ The computer didn't immediately carry out the instruction — it didn't print out PROGRAMMING after we pressed Return. This is because of the line number. It tells the computer that what follows isn't to be done immediately but is to be remembered for later as it is just one in a series of instructions. I'll prove that the computer actually does remember it in a moment.

Now type:

**20 PRINT "10" [Return]  
30 PRINT "EASY" [Return]**

What I'm going to ask you to do next should test your faith in me! Clear the screen by typing:

**[Shift+Clear]**

All your typing should have disappeared, but don't worry — your work hasn't been wasted. Because of the line numbers, the computer has kept

a list of your instructions in its memory. To see the list, type:

### LIST [Return]

and your program should reappear. We'll call it Program 1:

```
10 PRINT "PROGRAMMING"  
20 PRINT "10"  
30 PRINT "EASY"
```

*Program 1*

An important point coming up now. We have entered a program in numbered sequence of Basic instructions into the Atari's memory and have got the computer to display those instructions with LIST. We have not, however, told the computer to do those instructions. It's like having written a shopping list — you still have to go out to the shops and turn your list into reality.

So to get the computer to actually do, or as we say, run the program in its memory, we type:

### RUN [Return]

and, if we've typed it in properly, we should see printed out:

```
PROGRAMMING  
IS  
EASY
```

If you've managed it, congratulations on running your first program. If not, don't worry, it's probably some simple error. List your program and look for the mistake. You might actually have a message telling you that there is an error in a particular line. What we're about to do next, although it assumes that you have been successful so far, will in fact show you how to correct your mistakes!

Now let's try to alter our program so that it prints out:

```
PROGRAMMING  
IS  
SIMPLE
```

If you look back at the first program you will see that you need to alter line 30.

Changing line 30 couldn't be

simpler — just type in the new line 30, remembering to start with the line number 30, then press Return. The latest version will replace the old version in the computer's memory.

To demonstrate this, type:

```
30 PRINT "SIMPLE" (Return)
```

and then:

```
LIST (Return)
```

You should obtain Program II which is:

```
10 PRINT "PROGRAMMING"  
20 PRINT "IS"  
30 PRINT "SIMPLE"
```

*Program II*

An examination of this listing should reveal that the new version of line 30 has indeed replaced the old one. (Notice also that we didn't precede LIST with a line number — we wanted the more to do it immediately.)

As a final proof that our amendment has been accepted, type:

```
RUN (Return)
```

You should now get the revised message.

If you accidentally typed line 10 as:

```
10 PINT "PROGRAMMING"
```

then, when you tried to run it you would get an error message.

To rectify such mistakes, simply retype the correct version of line 10 and press Return to enter it into the computer.

There are more sophisticated ways of correcting, or editing, a line, but they can wait for a while. For the moment we shall simply retype the line, with its line number, and press Return. Of course, if you notice a mistake while you are entering a line, use the Delete key to erase it, then continue typing from that point.

So far I have given you just two programs to run. However, using these as models, you can print out virtually any message you want on the screen, just use line numbers in increments of 10, each line printing out part of the message you want out on the screen, by enclosing it in quotes after PRINT.

An important point about this series is that I'm going to give you lots

of example programs to type in. Virtually all of them have two things in common:

- They make vital teaching points (otherwise they wouldn't be there in the first place).

- The output — that is, what appears on the screen — is trivial in content and in many cases there are far easier ways of doing it.

Programming is a skill like driving — you can only improve by doing it, not reading about it. Please carry out the examples, however silly or obvious they may seem to you.

Also, and this is far more important, I want you to go beyond the programs — try to alter, adapt and extend them, just to see what happens.

Adopt an experimental approach and a healthy scepticism for my pronouncements. If you are wondering whether something will work, go ahead and try it — you can't hurt the computer from the keyboard, so let your imagination run riot.

You'll learn far more from your own examples than you will by merely copying mine. And the good thing is that you get such prompt feedback from a computer. If what you write isn't acceptable you'll soon get an error message.

So what I'd like you to do now is to spend a good time writing simple "message" programs for the computer to run. For some reason, in my experience in computing classes the messages tend to become quite absurdities. There's one thing I've never been too sure of — is it slander or libel when it appears on a VDU?

Remember, type NEW before each new program, and use line numbers for each instruction. It's also good policy to LIST your program before you RUN it, just to make sure that all is as you intend.

Now suppose we wanted to alter Program II so that it printed out the message:

```
PROGRAMMING  
IS  
RATHER  
SIMPLE
```

We need a line in there between 20 and 30 to print out RATHER. Well, 25 is a number between 20 and 30, so let's try:

```
25 PRINT "RATHER" (Return)
```

If you feel it you'll see that the program

has now become Program III:

```
10 PRINT "PROGRAMMING"  
20 PRINT "IS"  
25 PRINT "RATHER"  
30 PRINT "SIMPLE"
```

*Program III*

So line 25 has "dropped in" between 20 and 30. Even though we entered it out of order, the Atari stores it in memory in its correct numerical position. Try running the program as final confirmation.

This ability to insert lines into programs is the reason our line numbers go up in steps of 10 when we are writing programs — it leaves us plenty of spare line numbers in between for when we are patching them up.

Now enter Program IV:

```
10 PRINT "END OF LINE"  
20 PRINT "AGAIN"  
30 PRINT "END"
```

*Program IV*

remembering to press Return after typing each line.

Now LIST it. Is there a phantom line 25 in there? If so, you didn't type NEW after the last program — the lines 10, 20 and 30 of the latest program have replaced those lines in the old program. But as the new program doesn't have a line 25, the old one remains to ruin your program. The moral is to use NEW before entering a new program.

If you have got an unwanted line 25, don't worry — you can easily get rid of it by typing:

```
25 (Return)
```

This will delete the line since you replace the old line 25 with a new line which contains nothing — which the computer then "forgets". This method holds good for deleting any line from a program — simply type out the line number, then press Return.

I'd better explain what line 10 does. It clears the screen. I don't want to devote much space to it here, so let's just accept it for the moment — we'll explain it fully later in the series. You'll soon see that it works when you run the program.

Now let's try to print out our

message with blank lines between. We can use a line containing just PRINT to obtain a blank line, so Program V should do the trick:

```
10 PRINT "HELLO"
15 PRINT
20 PRINT "WELL"
25 PRINT
30 PRINT "OUTTHERE"
```

Program V

Now try Program VI:

```
10 PRINT "HELLO"
20 PRINT "WELL"
30 PRINT "OUTTHERE"
40 PRINT "WELL"
```

Program VI

The output you will get is:

HELLO  
WELL  
OUTTHERE  
WELL

That is, each successive string is printed after the preceding one. The semicolon stops the next string being printed on a new line, "gluing" it to the end of the previous string printed.

Notice that since there are no spaces inside the strings, none appear between the words when they are printed out together.

Try to get the message to appear legibly by rewriting the program with appropriate spaces in the strings. Also notice that you can obtain the same output, far more simply, with Program VII:

```
10 PRINT "HELLO"
20 PRINT "WELL OUT THERE"
```

Program VII

However, as I said above, the programs I present to you are for making teaching points, which does not necessarily imply showing you the most efficient methods.

Experiment with joining up the output of successive PRINT statements with the use of the semicolon until you feel confident about it.

And now for something completely different.

Try running Program VIII. I think the effect is pretty impressive.

So far all our programs have

**The ability to repeat a simple operation rapidly is what gives the Atari much of its power**

```
10 PRINT "I"
20 PRINT "FEEL"
30 PRINT "WELL"
40 PRINT
50 PRINT
60 GOTO 10
```

Program VIII

merely copied back onto the screen what you have typed in. This program shows how, with the addition of one line (line 60), you can obtain a huge increase in the amount of output. It is this ability, to repeat a simple operation rapidly, that gives the Atari much of its power.

If things are happening a little too fast for you, you can temporarily suspend action by pressing:

[Control] + 1

This freezes the action until you press:

[Control] + 1

once more.

What is happening is that the computer follows lines 10, 20 and 30 and prints out:

```
1 (line 10)
FEEL (line 20)
WELL (line 30)
```

followed by two blank lines. It then encounters line 60, which tells it to go back to line 10. It duly does so and prints out:

```
1 (line 10)
FEEL (line 20)
```

and so on, until it reaches line 60, when it goes back to line 10 and so on ad infinitum. Notice that when the screen is full, it scrolls up to make more room.

Now the name for such a condition is a program, where you keep on repeating lines of code (as the program lines are known), is a loop.

We say here that we are in an unconditional loop because we haven't given the program any conditions for it to cease repeating itself. This is bad programming

practice — completely introspective computers are not useful machines!

To stop such unconditional loops you have to interrupt them from "outside" by pressing the break key. As you'll see, you get a message telling you which line the program stopped at.

If you want to have some fun with an unconditional loop, try Program IX. It repeatedly prints out an arrow composed of asterisks such as:

```

      *
    ***
  *****
*****
  *****
    ***
      *

```

which will scroll upwards off the screen.

Finally, apart from its being an unconditional loop, which is always

```
10 PRINT " "
20 PRINT " "
30 PRINT " "
40 PRINT " "
50 PRINT " "
60 PRINT " "
70 PRINT " "
80 PRINT " "
90 PRINT " "
100 PRINT
110 PRINT
120 PRINT
130 PRINT
140 GOTO 10
```

Program IX

naughty, can you see what else is going wrong with Program X?

● Next month we'll discover new ways to create programs.

```
10 PRINT "HELLO"
20 PRINT "WELL"
30 PRINT "WELL"
40 GOTO 10
```

Program X

# 130XE:



## Part of the new Atari generation

THE first Atari computers, in the days when Acorns were only found on trees, were revolution-ary to say the least. The 400 and 800 — both initially with 8k and subsequently with a massive 16k — featured such undreamed-of features as 256 colours, multiple uppers and a four channel sound chip.

Four years later a much upgraded unit — the 800XL, boasting 64k, enhanced graphics and a new operating system — was released.

Now Atari has done it again with the extensively updated 130XE. This 128k machine is based on the 800XL, so software written for that machine should work correctly on the new one.

Since the operating system is identical to that used on the 800XL, the "Translator" program will still be required for those programs which used "illegal" routines on the old 400 and 800 computers.

The Translator can be loaded from cassette or disc before running any program which works fine on a 400 or 800, but won't work otherwise on an XL/XE machine.

The 130XE is one of a series of computers in the proposed XE range — some of which will possibly not be seen in the UK in the near future at least.

The 85XE is a re-packaged 800XL, will probably not see daylight while the 800XL is still in the shops. The rumours say that the 8 bit portable 6502P has been scrapped in favour of

### Assessed by ANDRE WILLEY

a 16 bit portable, and that the 65KIM music computer is in doubt too, since the 16/32 bit ST range will have MIDI music interfaces built in.

Atari could neither confirm or deny this, but did confirm that currently all production efforts are being channelled into providing good stocks of the 130XE, and in getting ready for the launch of the new 130ST in May/June.

The XE range will support a whole host of new peripherals, including those printers and four disc drives varying in storage from 130k to 15mbyte capacity.

The disc drives will be driven by DOS 2.5, an upgrade of the old DOS 2.0. It will allow access to all of the new densities, the extra RAM of the 130XE and files from the abortive DOS 3.

The 130XE itself is a very sleek light-grey unit, looking similar to the keyboard portion of an IBM. The keys have a soft but positive feel and are slightly pigmented, which makes typing a joy.

The function keys (Shift, Option, etc) now lie just above the main keyboard, somewhat inconveniently for a previous Atari user.

I would have hoped that the

System Reset button would have had a stronger spring than the others, as on the XL, but this has not been the case.

One interesting point is that the graphics symbols are now printed on the front of each key, making typing programs very much simpler.

The power switch is at the rear, adjacent to the socket which takes the transformer lead. Also provided on the rear panel are TV and video outputs, the serial bus connector for tape recorder, disc drives, printer, etc, and the re-used cartridge and expansion ports.

The XE will support all of the add-ons for the XL range using the serial bus, and although there is no parallel bus interface, the expansion connector along with the cartridge port provide a supposedly compatible alternative.

These expansions designed for the XLs will hopefully work on the XEs with little or no modification and vice-versa. Such is the theory.

Switching on, the machine behaves just like an 800XL. Basic will greet you with its "Ready" prompt and you may start to program, load games and so on.

The implementation is standard Atari Basic, although existing users will be glad to note that it is Revision C, the bug-free version.

It gives you, in addition to the normal Fina, GOTOs and FOR ... NEXT loops, commands to handle the 16 graphics modes and 256



colours, the four sound generators, long strings (up to 32k) and complex input/output operations.

Although this Basic is somewhat dated now, it is still a good match for Spectrum Basic, and is vastly superior to the C64 64.

If you require a much more sophisticated Basic, don't despair — try Basic-XL from OSS. This provides structured programming, full sprite/player/missile graphical control, advanced record handling and formatted PRINT statements, high speed memory access and transfer, full string handling, full error messages and much more.

It comes as an 8k cartridge and is upwardly compatible with Atari's own Basic — in fact it was written by the same programmers. This works fine with the XL, and provides so many useful features that since I received mine I have never used built-in Basic again.

The screen display is excellent with a normal TV and the graphics are sharper and more clearly defined than on the XL range. However I found that when used with a monitor, there were vertical lines over the whole screen and the colour saturation was very poor — giving a generally waxy-waxy picture.

I hope that this was just a fault with my review machine, as Atari assured me, but I have heard stories of similar problems from some dealers.

My other gripe is the location and construction of the cartridge socket. It is very difficult to insert cartridges into the back of the machine, since you don't even see the socket without leaning over the computer. Also third-party cartridges have a tendency to wobble alarmingly. While this wasn't quite as bad as the famous Sinclair 'Ram-Pack-Mobile' and it caused me no problems during testing with AtariWriter, Autobot, Basic-XL and Atari Artist, it could well cause problems as the unit gets older.

I was, however, pleasantly surprised by the manual. It is well laid out and a good introduction into programming in Basic.

It clearly explains the keys and how to write simple programs, with examples throughout and a set of

complete programs to type in at the end.

The appendices cover pin connections, accessing the extra RAM and Error messages. I feel that the book still doesn't go far enough and that some mention at least should be made of file handling (such as OPEN, CLOSE and XIO), PEEKs and POKEs, ARRAYS, maths functions and the memory map.

Still, all credit to Atari for listening to the customers' complaints regarding the pretty little colour pamphlets which were enclosed with the XL instead of an instruction book.

Taking the cover off and looking inside, the main circuit board is actually quite spacious and superbly laid out. The number of chips has been reduced wherever possible, which should make for a very reliable machine.

All the chips are inside a metal shield, thus reducing interference. The keyboard itself is backed by a solid metal plate and there is no tendency to sag in the middle.

Perhaps Sir Clive Sinclair could get a hint or two about how computers should be made?

Unfortunately, the report in last month's issue that the XL would contain the new CMOS 6502 chip was over optimistic and Atari has fitted the same CPU chip as used on the old XL range — the 6502C. This is a pity, but the difference would only be noticeable to a machine code programmer, anyway.

Overall, then, the 128XE is

basically a 128k version of the 800XL, and is upwardly software compatible. The styling, keyboard and documentation have been vastly improved and let's hope that the rather minor video problems will soon be sorted out.

Still, at £169.99, it is a very good buy indeed, offering far more for the price than the equivalent C64, Acorn or Amstrad offerings. I don't really think that the Spectrum is quite in the running.

## How to use that extra RAM power

WHEN you power up the computer, loading

### PRINT PRG01

will print the number of bytes of memory available for your Basic program. This will normally read 27902 with nothing else loaded. This is about 37%, so what's all this about 128k?

Well, the 6502 chip, or Central Processing Unit (CPU), which does all of the hard work inside your machine, can access a maximum of 64k of memory at once. As the book said (28k...).

This means that within that 64k, memory must be the operating system (16k), Basic itself (8k), your text display (1k), various special information and pointers required by the OS and Basic (just under 2k). You



can put your program in the 37k that's left. (But what about...?)

However, there is a loophole that Atari has exploited in the 13000. The 6502 can access up to 64k at a time. Why not, for instance, have two sets of 64k, storing your program in one set and perhaps data or display information in the other? This is basically what has been done.

We must always leave the operating system intact for programs to function correctly — that means leaving 48k to 64k well alone. Also, if we are using Basic then the area from 40k to 48k containing Basic itself must be left intact.

Screens will normally be in the 32k to 40k area, although we can change this to our advantage (see program listing on next page).

Your Basic program will start at about 3k, which leaves a nice block from 19k up to 32k or \$4000 to \$7FFF in hex, relatively free.

You can tell the computer to use either the "normal" \$4000-\$7FFF memory, or one of four other "hidden" blocks inside the machine. Four lots of 16k being the extra 64k, of course. Let's see how it works in practice.

In Table 1 you can see the eight blocks of memory available for use and how they are allocated — think of them as two sets of four blocks. You may tell the computer that whenever you access memory between \$4000 and \$7FFF, you really mean to talk to one of blocks 0, 1, 2 or 3.

This will allow, for instance, a program that extends throughout most of the 37k free memory to "switch off" its middle portion and




Table 1: Memory allocation

"switch on" an empty block of memory. You may then manipulate data, set up screens, or anything else you wish within that area.

After you have finished working with the extra block you give another POKE and your Basic program is back intact.

By the way, DO remember to make sure that you don't want to use any

lines of program that may be in that middle block while you've got it switched off! This would cause a disaster and Basic would probably crash or lockup.

The safest way is to write a small routine at the start of the program to handle the memory switching and usage, then GOSUB to it whenever you want to use the additional

Bit	Value	Description
*0	1	Operating system select 1 = Operating system ROM enabled at \$C000 0 = RAM enabled at \$C000
*1	0 from Basic, 1 from m/Basic	Basic ROM select 1 = RAM enabled at \$4000 0 = Basic ROM enabled at \$4000
2	1	Memory bank select bit 0 (See text for full description) (Named: \$40 - USR of secondary bank address)
3	1	Memory bank select bit 1 (See text for full description) (Named: \$A1 - MSB of secondary bank address)

Bit	Value	Description
4	1	CPU bank enable (CBE) 1 = 6502 uses Normal memory bank at \$4000 0 = 6502 uses Extended memory bank at \$8000
5	1	Video/bank enable (VBE) 1 = Arlec uses Normal memory bank at \$4000 0 = Arlec uses Extended memory bank at \$4000
*6	1	Reserved for future use (Unused on the 13000)
*7	1	Self test ROM select 1 = RAM enabled at \$8000 0 = Self test ROM enabled at \$8000

\*Don't change these bits unless you know what you're doing

Table 2: Use of memory location \$4017 (\$D003)

memory (see example program).

So far we have treated this switchable bank of memory as being simply normal memory, or one of four other extended blocks of memory. In fact, just to make the whole issue more complicated, it can be both at the same time.

This is not quite as daft as it sounds, and is easier to understand if you remember that an Atari actually has two, not one, CPU chips. The 6502 is the main one, which does all of the work for Basic and input/output.

However, there is a second processor called Antic which is solely devoted to generating the screen display. This also accesses memory in order to do its job. You can tell Antic and the 6502 to access different banks of memory.

For example, in the above case, if you wanted to use the Basic program at \$4000 while you were displaying a screen from bank 1, you couldn't. But by telling Antic to use bank 1 for its display, and the 6502 (which handles Basic programs, remember?) to use normal memory, you have accomplished both tasks at the same time.

You can't of course tell the CPU to change the display data while you're in this mode - it doesn't see the same memory as the display chip.

This means that any graphics commands, PLOTs and DRAWTOs, etc., must be done when the CPU is accessing the memory containing the screen data, and the middle of the Basic program is switched off. You can still use SETCOLOR, though, which doesn't actually change the contents of the display area.

One memory location is used to control all of the switching. This is location \$4017 (\$D001 for machine code users). Each individual bit within that location does a different job, as described in Table II (see last month's Bit Wise article if you're not familiar with bits and bytes).

Bits 1, 2 and 3 must always be 1, and bit 4 must be 0 (from Basic; that is - do what you like from machine code, but remember to take over system control from the OS before you switch it off). This gives a base value of  $128+64+32=193$  for POKE into \$4017. The extra bit values to add on are worked out as follows.

Bits 2 and 3 tell the computer which of the four alternative blocks to

use. Bit 4 tells the 6502 CPU to use either Normal or Extended mode (that is normal memory, or the extra block selected by bits 2 and 3). Bit 5 tells Antic whether to use normal or extended memory for its display (assuming Antic wants to use the 16K - 32K area, that is).

Thus, for:

Bank 0, add 0 to the POKE,  
Bank 1, add 4 to the POKE,  
Bank 2, add 8 to the POKE,  
Bank 3, add 12 to the POKE.

CPU 'Normal' Mode: add 16 to the POKE,  
CPU 'Extended' Mode: add 0 to the POKE.

ANTIC 'Normal' Mode: add 32 to the POKE,  
ANTIC 'Extended' Mode: add 0 to the POKE.

To set the memory usage, use:

**POKE \$4017,193 + (Bank 4\*16) + (CPU Mode) + (ANTIC Mode)**

To reset the memory back to normal, use:

**POKE \$4017,193+16+32  
or POKE \$4017,193**

**Example 1:** To set the CPU to 'Normal' memory, and ANTIC to Bank 0:

**POKE \$4017,193+0+16+0**

**Example 2:** To set the CPU to Bank 1, and ANTIC to 'Normal' memory:

**POKE \$4017,193+4+16+0**

**Example 3:** To set the CPU and ANTIC to Bank 3:

**POKE \$4017,193+12+16+32**

You will quite quickly get used to working with location \$4017 as a matter of course, and it is far easier to use and more versatile than trying to get all the extra 16K or the 6502K.

If anyone finds any interesting applications for the extra memory write in - we send a listing of your program.

Above all, don't be afraid to experiment. Once your programs are saved, no matter what you do to the memory you can always switch off and start again if things go wrong. Have fun!

*My special thanks to Software Express, of Birmingham, for the kind loan of the very first 1200K Atari.*

## Example program

This program can only be used on a 1200K computer. If you haven't got one, add the line:

**END SCREEN**

or try using the pattern drawing routines separately to see some pretty displays.

Type in the listing, check it is correct, and SAVE it. When you run it a pattern will quickly be drawn. This will be left on the screen while the computer draws more patterns in other banks of memory (the screen will flash to let you know it's still working).

Once the screen has stopped flashing press keys 1 to 6 to view the pictures. Press Esc to stop the program. Try not to use Break to stop it, as you will confuse the computer into displaying the wrong screens, giving strange rubbish all over the screen.

You may experiment with the five pattern-drawing sections. Try changing several of the numbers in the loops to get different patterns. Start by setting one of the FOR ...-1 to 360 loops to a step value of 30.

```
100 REM
110 REM
120 GOTO 330:REM Jump to main program
130 REM
140 REM
150 REM *****
160 REM *****
170 REM *****
180 REM *****
190 REM *****
200 REM *****
210 REM *****
220 REM *****
230 REM *****
240 REM *****
250 REM *****
260 REM *****
270 REM *****
280 REM *****
290 REM *****
300 REM *****
310 REM *****
320 REM *****
330 REM *****
340 REM *****
350 REM *****
360 REM *****
370 REM *****
380 REM *****
390 REM *****
400 REM *****
410 REM *****
420 REM *****
430 REM *****
440 REM *****
450 REM *****
460 REM *****
470 REM *****
480 REM *****
490 REM *****
500 REM *****
510 REM *****
520 REM *****
530 REM *****
540 REM *****
550 REM *****
560 REM *****
570 REM *****
580 REM *****
590 REM *****
600 REM *****
610 REM *****
620 REM *****
630 REM *****
640 REM *****
650 REM *****
660 REM *****
670 REM *****
680 REM *****
690 REM *****
700 REM *****
710 REM *****
720 REM *****
730 REM *****
740 REM *****
750 REM *****
760 REM *****
770 REM *****
780 REM *****
790 REM *****
800 REM *****
810 REM *****
820 REM *****
830 REM *****
840 REM *****
850 REM *****
860 REM *****
870 REM *****
880 REM *****
890 REM *****
900 REM *****
910 REM *****
920 REM *****
930 REM *****
940 REM *****
950 REM *****
960 REM *****
970 REM *****
980 REM *****
990 REM *****
```

## SOFTWARE SPECIALIST



## VARIABLES

**CPU** Sets CPU mode for subroutine at 200.  
**ANTIC** Sets Antic mode for subroutine at 300.  
**BANK** Sets Bank number for subroutines at 200.  
**I** Angle value for graphics drawing loops.  
**J** Repeat value for graphics drawing loops.  
**CH** Ascii code of last key pressed (if valid, converted to a number between 1 and 50).

## FUNCTIONS

**180** Jumps past subroutine.  
**200-280** Check values, and set bank select. Could be re-used for your own ideas. Just set variables Antic, CPU and Bank, and GOSUB 200.  
**300** Sets screen to 32k and draws patterns in depress.  
**370-450** Set normal memory and draw pattern 1.

**470-550** Set CPU to Bank 0, leave Antic on normal memory and draw pattern 2.

**610-690** Set CPU to Bank 1, leave Antic on normal memory and draw pattern 2.

**730-810** Set CPU to Bank 2, leave Antic on normal memory and draw pattern 3.

**850-930** Set CPU to Bank 3, leave Antic on normal memory and draw pattern 4.

**1010** GOSUB to set colours.

**1070-1120** Get a key. If 1-5, GOSUB accordingly. If Esc, exit to Basic. Otherwise get another key.

**1170-1190** Set Antic and colours for picture 1.

**1240-1260** Set Antic and colours for picture 2.

**1310-1330** Set Antic and colours for picture 3.

**1370-1390** Set Antic and colours for picture 4.

**1440-1470** Set Antic and colours for picture 5.

**1520-1530** Subroutine 1 to set colour registers.

**1580-1600** Subroutine 2 to set colour registers.

```

300 GOSUB 1110
310 FOR I=0 TO 50 STEP 5
400 COLOR 0:PRINT 0$,0:GOTO 1000
1000 GOTO 1100
420 NEXT I
430 END
440 END
450 END
460 FOR I=0 TO 50 STEP 5, and draw a pattern
470 END
480 LET CH=ASC(11)GOTO 1000
490 GOSUB 1110
500 COLOR 110
510 FOR I=0 TO 50 STEP 5
520 PRINT 11,PRINTING NEW PATTERN
530 ...
540 FOR I=0 TO 50 STEP 5
550 FOR J=0 TO 50 STEP 50
560 PRINT 1000:PRINT 1000,PRINTING NEW
570 NEXT J
580 NEXT I
590 END
600 END
610 FOR I=0 TO 50 STEP 5, and draw a pattern
620 END
630 LET CH=ASC(11)GOTO 1000
640 GOSUB 1110
650 FOR I=0 TO 50 STEP 5
660 PRINT 11,PRINTING NEW PATTERN
670 ...
680 COLOR 110:PRINT 11,PRINTING NEW PATTERN
690 ...
700 FOR I=0 TO 50 STEP 5
710 PRINT 11,PRINTING NEW PATTERN
720 ...
730 PRINT 11,PRINTING NEW PATTERN
740 ...
750 PRINT 11,PRINTING NEW PATTERN
760 ...
770 PRINT 11,PRINTING NEW PATTERN
780 ...
790 PRINT 11,PRINTING NEW PATTERN
800 ...
810 PRINT 11,PRINTING NEW PATTERN
820 ...
830 PRINT 11,PRINTING NEW PATTERN
840 ...
850 PRINT 11,PRINTING NEW PATTERN
860 ...
870 PRINT 11,PRINTING NEW PATTERN
880 ...
890 PRINT 11,PRINTING NEW PATTERN
900 ...
910 PRINT 11,PRINTING NEW PATTERN
920 ...
930 PRINT 11,PRINTING NEW PATTERN
940 ...
950 PRINT 11,PRINTING NEW PATTERN
960 ...
970 PRINT 11,PRINTING NEW PATTERN
980 ...
990 PRINT 11,PRINTING NEW PATTERN
1000 ...

```

```

370 PRINT 1000:PRINT 1000,PRINTING NEW
380 FOR I=0 TO 50 STEP 5
390 PRINT 1000:PRINT 1000,PRINTING NEW
400 ...
410 NEXT I
420 NEXT J
430 END
440 END
450 END
460 FOR I=0 TO 50 STEP 5, and draw a pattern
470 END
480 LET CH=ASC(11)GOTO 1000
490 GOSUB 1110
500 COLOR 110
510 FOR I=0 TO 50 STEP 5
520 PRINT 11,PRINTING NEW PATTERN
530 ...
540 FOR I=0 TO 50 STEP 5
550 PRINT 11,PRINTING NEW PATTERN
560 ...
570 PRINT 11,PRINTING NEW PATTERN
580 ...
590 PRINT 11,PRINTING NEW PATTERN
600 ...
610 PRINT 11,PRINTING NEW PATTERN
620 ...
630 PRINT 11,PRINTING NEW PATTERN
640 ...
650 PRINT 11,PRINTING NEW PATTERN
660 ...
670 PRINT 11,PRINTING NEW PATTERN
680 ...
690 PRINT 11,PRINTING NEW PATTERN
700 ...
710 PRINT 11,PRINTING NEW PATTERN
720 ...
730 PRINT 11,PRINTING NEW PATTERN
740 ...
750 PRINT 11,PRINTING NEW PATTERN
760 ...
770 PRINT 11,PRINTING NEW PATTERN
780 ...
790 PRINT 11,PRINTING NEW PATTERN
800 ...
810 PRINT 11,PRINTING NEW PATTERN
820 ...
830 PRINT 11,PRINTING NEW PATTERN
840 ...
850 PRINT 11,PRINTING NEW PATTERN
860 ...
870 PRINT 11,PRINTING NEW PATTERN
880 ...
890 PRINT 11,PRINTING NEW PATTERN
900 ...
910 PRINT 11,PRINTING NEW PATTERN
920 ...
930 PRINT 11,PRINTING NEW PATTERN
940 ...
950 PRINT 11,PRINTING NEW PATTERN
960 ...
970 PRINT 11,PRINTING NEW PATTERN
980 ...
990 PRINT 11,PRINTING NEW PATTERN
1000 ...

```

```

1100 GOTO 1070
1110 GOTO 1070
1120 END
1130 END
1140 END
1150 END
1160 END
1170 END
1180 END
1190 END
1200 END
1210 END
1220 END
1230 END
1240 END
1250 END
1260 END
1270 END
1280 END
1290 END
1300 END
1310 END
1320 END
1330 END
1340 END
1350 END
1360 END
1370 END
1380 END
1390 END
1400 END
1410 END
1420 END
1430 END
1440 END
1450 END
1460 END
1470 END
1480 END
1490 END
1500 END
1510 END
1520 END
1530 END
1540 END
1550 END
1560 END
1570 END
1580 END
1590 END
1600 END
1610 END
1620 END
1630 END
1640 END
1650 END
1660 END
1670 END
1680 END
1690 END
1700 END
1710 END
1720 END
1730 END
1740 END
1750 END
1760 END
1770 END
1780 END
1790 END
1800 END
1810 END
1820 END
1830 END
1840 END
1850 END
1860 END
1870 END
1880 END
1890 END
1900 END
1910 END
1920 END
1930 END
1940 END
1950 END
1960 END
1970 END
1980 END
1990 END
2000 END

```

# Well-named Colossus

ENGLISH Software ask you what you'd call modest about their **Colossus Chess 3.0** package. In all their literature, and even in the manual, it's billed as "the best chess playing program for Atari computers".

Maybe that only makes it a big fish in a small pool, because there aren't that many alternative chess programs for the Atari.

However, before I see how it would fare in the bigger pool that includes other minis, let's look at what it offers.

I was glad to see that the program allows you to use a cursor to specify your move. You simply position it on the piece to be moved, press Return, position it on the square to move to, and press Return again.

I find this much easier than the more common "a2-a4" format. However, if you want to do it that way, the program will allow it.

As chess programs go this one is very comprehensive. I'll consider its standard of game later, but the extent of its features is very impressive.

An enormous variety of levels can be selected by varying the amount of time the program has to select a move.

Full tournament mode can be selected or you can play an all-the-moves game in which the total game time is specified.

You can even introduce a handicap for the program for yourself if you're that good by putting some time on one of the clocks before the game starts.

There's an "equality" mode in which the program will try to keep its clock as close as possible to your own, so if you can move quickly you can force the program to do the same.

There are plenty of other features too, like the replay facility enabling you to see how the game got to its present state. A useful tutorial feature is the "legal moves" option which will show all such moves for any piece selected.

The program can also be

used to set up and solve chess problems, and that's just the usual "white to move and mate black in five moves" type.

It claims to be the first home computer chess program ever to be able to solve self-mates and helpmates, and as far as I know the claim is true.

On features alone then, it's probably fair to say that Colossus is the best chess program available for the Atari.

The manual gives a good description of all the features and how to use them, and fully describes all the different sections of the screen display. In fact there's only the manual that I found to criticize. The content is fine, but the presentation is awful. It's printed in black on red paper — not a pretty sight.

It looks to have been photo-reduced to fit its size from A4 dot matrix printer output, which doesn't help, and you'll need a magnifying glass to read the loading instructions.

To consider whether the program is anything more than a big fish in a little pool we need to look at the standard of its game.

Rather than describe in detail how the program fare me to check, which doesn't

say much, there's a table at the end of the manual which gives the results of Colossus v The Rest.

The program was tested against over 30 other programs in a variety of machines ranging from the IBM to the Apple. Against each one a series of 16 games was played on various levels with an equal number of whites and blacks for each program.

Colossus beat them all — most of them by 16 games to nil. Samson II, widely recognised as an excellent program, went down 10-6. Parter Chess, another Atari version, went down 12-4, while Atari's own version lost 15-11. White Knight III it won only three of its 16 games.

About a year ago Colossus Chess 3.0 for the Commodore 64 was advertised as "the finest chess program ever written". I'd have been interested to see how 3.0 fared against its predecessor.

Since both were written by Martin Bryant we can assume that 3.0 would win ... but by what margin? How much improving can he do?

As the manual points out, the same set of results could not be guaranteed in every set of 16 games. Nevertheless, even if the results are taken as only a rough guide, they show

Colossus to be up there with the best of them.

Colossus Chess 3.0 comes on 48K cassette or disc, with prices of £39.95 and £12.95 respectively. To call it the best chess program for the Atari might just be damning it with faint praise!


Dave Russell

## One for joystick jockeys

AS they say on all the best sports shows, "It takes them in reverse order". Last month we reviewed Smash Hits volumes 1 and 2, this month it's look at Volume 1.

Like the other two volumes, it opens with **Jet-Rocket Jack**. This is probably the best known of the English Software games, which is presumably why they include it on all three volumes. It's a good game, so I'm not complaining.

Next is **Don Rickles Back**, the sequel to Diamonds from Volume 2. English Software



obviously watch the same points shown. Once again Dan rallies forth (or rather slouches with his hands as he slips his way to the diamond on level 6. Of course like the Blob and a variety of other names are out to stop him.

For my money this is miles better than the original. It's been a smash hit in our household—we've played it for hours and nobody's got beyond level 8 yet.

Next comes **Hyperblast**, which is exactly what you'd expect a game of that name to be. If it moves, blast it!

These last of games are great if you like them, and I usually do in moderation. **Hyperblast** will give your joystick and thumb plenty of exercise as you dodge the enemy, although it has the simplest space warp I've ever seen. Still, you only weep between levels as the quality of play isn't affected.

In **Captain Brickley's Gold** you play the part of the captain's hapless crew member who gets to die for the gold. Level 1 starts off nice and easy, with only some fish and an air tank to avoid while you're grabbing the gold.

Of course your oxygen is being used up all the time you're under water. You replenish your tanks by replenishing, but there is also a time gauge which shows how long you have left to complete the level.

When you've collected 10 bars of gold you move to the next level, where things are a

little harder. If you can complete eight levels you move to the next difficulty zone.

If **Hyperblast** is for the arcade addict, **Captain Brickley's Gold** starts off simple enough for the novice or the younger members of the family.

Finally, **Fireblast** calls for arcade reactions with a high level of precision. Your task is to steer your space cruiser through a series of canyons populated by tanks. It's a sort

of vertical AirStrike, with the steering being really well done.

I found it a bit strange at first because the same tanks from bottom to top, giving the impression of downward motion. Most other games start in the other direction.

The game requires a bit of strategy, a fair amount of selective shooting, and a lot of precision steering. If you hit the wall you're dead, and sometimes there's not much

room. Fortunately, response to the joystick is excellent.

**Fireblast** is a difficult game—it took me a few minutes to get anywhere—and the frustrating thing is that you are returned to the beginning when you get killed off. It was like a challenge, this one's for you.

All in all, if you're a joystick jockey then Volume 1 is good value for money at \$14.95 for the tape and \$19.95 for the disc.

Pat Cookson

## KEEP AN EYE OPEN FOR LUIGI

ONE of the features of the new Atari disc package is the inclusion of a new adventure game, **The Pay-Off**. Fortunately for this reviewer, who already owns a complete Atari system, the game is also available in its own right from "all good Atari dealers".

The game is a double first for Atari, being both their first disc game and also their first adventure. Based on this worthy effort, we can only hope that it won't be their last.

Despite the recent trend towards graphic adventures, Atari chose to launch a text-only game, billed in publicity as "an adventuresome adventure". This may be seen in some quarters as Atari once more swimming against the tide, but the tide is mightier than the gale, as any real adventure will assert.

You start out as a small time hoodlum determined to stake your last few dollars on a hopeless rag, a tank outside that only an out-and-out loser would touch. Unfortunately, as you quickly discover, Luigi, a whistle whirly betting shop owner, is in no mood to extend your credit. In fact he's calling in your marker, and boy does he mean business!

Leaving the shop, loudly if needs be, the threat of a quick trip to the bottom of the river ringing in your ears, you begin a search for some quick cash—\$5,000 greenbacks to be exact.

The lack of immediate exits soon had me climbing the wall,

but the writers were on a jump ahead and the real route to success was nothing more than a pipe dream.

Once over these initial obstacles I soon found plenty of real life places to explore and objects to use. I also discovered a multivalent game of hidden lurking beneath the surface. Just my climbing the fence in the car park.

In fact I found myself more and more saving my game-position and deliberately "dying" in order to escape the author's sense of humor.

The beauty of this adventure is that the more you think yourself into the character the easier it is to solve the various problems. A desperate situation calls for desperate measures, and at least two of the obstacles which confront you require a degree of violence to overcome them. Not too much though, or you will provide a swift repeat.

The game has several distinct phases, ranging from "What on earth are I supposed to be doing?" which is not entirely dear at the outset, to a phase where everything is proceeding in a straightforward manner.

This leads the astute adventurer to think that the solution to the game is a fairly obvious one. Many objects and places are found which

lead the villain of the piece, you, to the war of the Banks of New Jersey in search of a fabulous gem which, used on the street has it, could be the answer to all your problems.

Yet the greatest crime has been perpetrated (ironically I might add) by the programmers, who have allowed the adventurer just enough rope to hang himself.

While it is possible to gain access to the bank—and to explore it, despite the duty guard—are very important pieces of equipment is recovered where only the most persistent adventurer will locate it without difficulty. In fact, you've been warned!

The problem with reviewing an adventure such as **The Pay-Off** is that the game involves almost solving problems after problems, each new solution allowing more of the adventure to reveal itself.

It evokes a unique atmosphere so essential in preventing such games from becoming mere exercises in problem solving, and yet is subtle to solutions too obviously to spoil that feeling. Suffice it to say that the game left this adventurer peering warily over his shoulder for any sign of Luigi and his boys as he crunched at the next clue, preparing his last claim.

Eric Gibson



# A micro version of Indiana Jones?

**PITFALL II** from Activision is a follow-on from their original Pitfall game. And what a follow-on it is — a levels-and-ladders game with extra surprises.

The first surprise came in the form of an instruction booklet in French, German, Italian, Spanish and Dutch.

Not a mention of English — but from my shaky knowledge of French I managed to establish that you move Harry around in sort of Illinois/Indiana Jones, searching a huge underground cavern for his steed, Rhonda.

You must also find his pet cat, Gortekoo, a big diamond and a stone rat.

Collecting gold bars on the way to boost your points score seems to be the heart of over survival.

The quest starts in a red cross at the edge of a forest and as you progress to the cave you start to meet the enemy — the most vicious bunch of creatures that you could ever hope to encounter.

They take the form of frogs, snakes, bats and scorpions to name but a few, and they're all out to make life extremely unpleasant for you.

On the first level the frogs

do their utmost to prevent you going down ladders to the next platform.

The bats and snakes are out to stop you in your tracks by flying across the screen with your head as the prime target, while the scorpions are continuously attracted to your rather exposed for the same reason.

This is certainly not a game for the faint-hearted.

At the bottom of the cave there is an underground river full of different hazards, but to collect all the gold bars you must take your chance with these snakes at last.

You can in fact end up taking an unexpected ducking by misjudging some of your earlier leaps. There's no harm's done, though, as our hero is an excellent swimmer with a ring-a-ling cap.

I'd keep an eye open for the bats, though — they've a few tricks in store.

In another part of the cave a waterfall chatters away and one of the gold bars and you can only get at it by fishing a bit on a passing balloon. A quick grab for the rope and it's up, up and away.

And it's here that those infernal bats turn out to be a

bleeding in disguised.

If you can manoeuvre the balloon into the path of one of them, the bat'sian turns and you drop off on the ledge below.

Your ultimate target, a gold ring, can only be accessed by a well-judged death-defying leap from one of these ledges to a small platform halfway down the cave.

Surprise, automatically transports you to level two, which is a larger cave with more moanies and, I suspect, more gold bars and other treasures.

I say suspect because, as yet, I haven't been able to get any further. It's got something to do with the plants and giant ants — different hazards to contend with on this level.

Contact with any of these, as well as the earlier manies,

results in your return to the last red cross you walked over, and you lose some of your points.


One thing you don't lose, though, is your life, and this means the game can't last as long as you want it to.

A catch-up time plays throughout — quite entertaining in its own right. However, I was a little disappointed with the graphics, as I don't think they use the Atari's capabilities to the full.

And the game only supports joysticks, which is a shame and obviously rules out a lot of Atari owners who can only access the keyboard.

When played apart, the game is extremely addictive, great fun to play, and the number of levels to come will sustain a mystery to me until I get some more practice.

David McLachlan



## OUTDO THOSE GREMLINS



ALL is peaceful in the garden, in this US disto offering. **Mr Do** is going about his normal business harvesting the cherries when from behind a toadstool a hideous beastie suddenly tears its ugly head.

Can our hero destroy it? Will this year's cherry harvest be in ruins? Will Mr Do end up caught by the garden?

You mean Mr Do around the garden is an attempt to correct all the cherries. As you move through the long grass you clear a path behind you.

The gremlins, these 'em, appear at regular intervals from a central toadstool, and normally travel along the clear pathways in their pursuit.

You can confuse them for a while but when things get tough, and believe me they will, you can please send your crystal ball zig-zagging along the pathway in an effort to disperse of them.

Scattered around the garden are several large apples, and by placing a path underneath them you can

make them drop, hopefully onto one means that you've managed to enter under-ways.

If your luck's anything like mine you'll finish up squeaked more often than the moans.

If you're feeling brave you can always try an all-out assault on the central toadstool to gain extra points.

This is an extremely addictive game, great fun to play, and is a must for the repertoire of any serious arcade addict.

Paul Hewitt

OUT NOW ON CASSETTE AND DISK

# ARCHON

THE FORCES OF LIGHT & DARK BATTLE IT OUT IN  
THE ULTIMATE ACTION & STRATEGY PROGRAM FOR YOUR CPM 64

**NOW**  
AVAILABLE ON  
SPECTRUM 48K  
AMSTRAD CPC 464  
ATARI 680/800XL  
including FREE  
SOUND CARD  
CARTON, 256K EPROM  
ROM



ARCHON is brilliant. There's something in it for all games addicts; arcade, adventure and strategy are all here. My only complaint is that it's best played against a human opponent - the computer's just too good and you can't give it a handicap.

**Bryan Skinner**  
*Personal Computer News*

**Features** ● Play the computer or a friend ● Computer player gets tougher as you do ● 64 Battle combinations ● Separate battleground screen ● Medieval pieces like the wizard and the sorceress - magic spells and a board that changes as you play ● Deluxe boxed package includes full instruction and hints manual ● Joystick controlled \*

\*Optional joystick control. Spectrum & Amstrad versions.

AVAILABLE FROM ALL GOOD SOFTWARE RETAILERS - IF IT'S NOT THERE, ORDER DIRECT

**aria**



HIGH PERFORMANCE SOFTWARE

# A message from ENGLISH SOFTWARE<sup>TM</sup> to all owners of ATARI, COMMODORE 64, BBC B, ACORN ELECTRON and AMSTRAD Computers ...

Also through this and Computer Chess  
Library, AMSTRAD 1608B computers.

Software companies grow on trees ... at least that's the way it seems from the number of new companies springing up every week!

**ENGLISH SOFTWARE** was launched three years ago with a smashing little game for Atari Computers called **ARCADE TRIFE 1**, which quickly became one of the most popular U.K. programmed games for the Atari.

Then, as now, Atari Computers were amongst the most advanced on the planet, but they were a **TRIPLE EXPENSE!** But we knew that prices would come down, and that more people would soon appreciate the great range of Atari software (produced by **ENGLISH SOFTWARE**). But Atari owners **would** be a funny lot, being hard to utter such gemo-ib:

"It can't be any less, it's cost less than £20!"  
Honestly, that's what they used to say! Anyway, in the face of this rather strange attitude, we went ahead and committed the ultimate sin:

## ATARI GAMES AT £9.95!

We expected some slight resistance to these prices from Atari owners who only equated high quality with high prices, but we were wrong. Everybody thought the prices were great, and the games too!

We even produced the fantastic **ATARI CASSETTE EMULATOR** at £7.95, a superb utility program for BASIC programmers.

So now, for those of you who might have missed out on all our excellent Atari titles, we are releasing something very, very special!

**ATARI SPASH HITS** volumes 1, 2 and 3 from **ENGLISH SOFTWARE**.

Two great games on one cassette for only £14.95, or on disk at £17.95!

Each cassette features our top-rated **JET-BOOTS JACK** plus four other popular titles. So now you have no excuse to miss out on the best range of U.K. produced Atari 400/800/600K/800K software for 50K machines. If your dealer does not yet have them in stock, ask him to order them from his nearest Atari wholesaler. Until he's the best, Atari buy **YOU** will make all year!

We have also just released **COLONNARI CHIEF 3.0**, the best chess program available anywhere for Atari 400/800/600K/800K computers with 4096K. Very powerful, with lots of excellent features.

For our good friends with other home computers, our programmers are busy producing original games for you as well. They are all featured on this page: **HENRY'S HOUSE** (on the Commodore 64), and **JET-BOOTS JACK** on the Electron are now available at selected branches of W.H. SMITH.

Selected English Software titles are available at: **HAVERGODS** and selected branches of: **LASHLEY'S**, **BOOTS**, **BRANAGAN COMPUTER STORES**, **CD-OP STORES**, **THE SALICA SHOP**, Mail Order and Retail and all good software stores.

THE ENGLISH SOFTWARE COMPANY

1 North Parade, Personage Gardens, Manchester M60 1BA  
TRADE ENQUIRIES WELCOME: 061-835 1358



PROGRAMMERS AND PROGRAMS  
URGENTLY REQUIRED!  
— CONTACT US NOW —

ENGLISH SOFTWARE  
ENGLISH SOFTWARE  
ENGLISH SOFTWARE  
ENGLISH SOFTWARE

*Find out how to use your Atari to link up with the world network of communications in this special 12 page section*

DO you remember the days when you got your first Atari? It was love at first sight, wasn't it? Those rapturous hours at the keyboard, those agonies of frustration coupled with the mind-bending moments of triumph when you actually got the thing to do something.

Happy days, or at least they were for me. Still, like all infatuations it gave way to a more mundane love-hate relationship. Mirrors were still existing, but the first shells had gone, never to be revealed. At least that's what I thought until I was introduced to the world of comms. Then that was it. Gone was the debenser, "man of the micro world". "I can take Atari or leave them" attitude. I was hooked, demented, crazed, I'd joined the hacking fraternity!

If you're wondering what comms means, it's short for communications — in this case, communications between micros via the telephone lines. It sounds so innocent, doesn't it? Then I suppose heroin doesn't look too bad, but once you get hooked...

It started when a friend of mine who works for Atari User lent me a modem — that's the gadget for attaching a micro to the phone system — and his black book of bulletin board numbers.

A bulletin board is just an electronic notepad that you can leave messages on. And, of course, you can scan the messages other users leave.

It appears innocuous enough, doesn't it? But it's not. From my first session I was in its grip.

The messages are absolutely fascinating. There are people asking for (or supplying) help with programming problems, people swapping their experiences with various software packages (especially adventures), people airing their opinions on everything from politics to plane flying.

There are second-hand and swap pages — everything from cars to wheels, pages of micro-news, gossip ... the list goes on and on. I've even seen job advertised.

In my quieter, reflective moments (when the wife insists on using the phone) I think the attraction is the fact that microcomputing is normally such a lonely business.

As soon as you get into comms you're freed from your isolation. It's amazing how many interesting, like-minded fellow maniacs there are out there!

And then there's the free software. Most bulletin boards have software for downloading, as it's known.

A lot of it is excellent quality — and it's free! Given if I've no need for it I can't resist having it. The boards also

carry the phone numbers of other boards, which carry numbers of yet other boards ... and so on ad infinitum.

Of course, as with all addictions, you move on to harder stuff. My encounters with bulletin boards led inexorably onto flirting with Preset. No hobbyist bulletin board this, but a nationwide commercial network based on a series of powerful mainframes.

It's got scorefuls of information, latest news, special interest groups and software to download — although this time you have to pay. (My habit was getting serious by now.)

Still, you can get everything from train timetables to holiday bookings, electronic shopping to interactive adventure games. You can spend days on Preset (I did) and not exhaust the possibilities.

And then I discovered Telecom Gold. It's not a shiny product, no matter how it sounds. It's an incredibly sophisticated electronic mail system, a sort of mega-bulletin board.

I was lucky to get in at the beginning of MicroLink, one of the latest developments on Gold, as aficionados refer to it. This is a joint development between Telecom Gold and the people behind Atari User and promises to be the most addictive comms source yet.

For a start, everyone gets their

own electronic mailbox. If, like me, you can't wait to open your mail in the morning, you'll enjoy logging onto the system (as singing it up is known). There's a fresh crop of letters every few hours.

When I first logged onto it, MicroLink was in the development stage, so there were only magazine editors and the like to write to. By the time you read this, though, there should be hundreds of real people sharing the fun.

Mind you, MicroLink isn't just restricted to sending letters to people, although there are extremely powerful facilities for doing so I haven't even touched on.

There's a notice board and a mass powerful bulletin board. You can chat with anyone who happens to be "on-line" to the computer at the same time as you are. You can find out which dealer's selling the equipment you want at the price you want. The list of facilities goes on and on.

How could I resist? The truth is I didn't even try. Every spare minute I got I'm on the Atari communicating! I suppose really I should start mauling:

Go mother, tell your children,  
Never do what I have done

Or suggesting that every  
modem should have a government  
health warning.

Perhaps I should ... but I won't.  
Comms is just too much fun.

## Hooked on hacking

**PETER ATKINSON confesses his communications addiction!**

PETER TOTILL  
explains the  
advantages of  
using your  
Atari computer  
for interactive  
communication

ONE of the most interesting of modern methods of communication is the Bulletin Board system — often referred to as a BBS.

So what is such a system? The idea started in the USA, when a computer club decided that pinning messages to other members and notices onto a cork board on the wall was a bit too much behind the times for a high technology club like theirs.

They decided to hook a computer to a telephone and allow people with modems and minis, or even ordinary terminals, to dial in and leave their messages on the computer instead.

As modems were even then priced within the reach of the hobbyists in the USA, the idea was very successful.

It was soon taken up by other clubs and also by individuals, with the result that today there are at least 1,000 public and private BBSs operating in North America — and probably considerably more.

Since those early days the software that controls such systems has developed enormously and you can run a BBS on most of the popular minis available in the USA.

British BBS software is still in on the ground as yet, but some programs are being developed.

Bulletin boards will allow users to do a wide range of things, but the main emphasis is still on the traditional message and mailbox facilities.

For example, on most BBSs messages can be private or public, general interest or collected into special categories. They will tell you if you have a message waiting when you call, and also let you search for messages on a particular subject.

Other features that you will find on a BBS include information and news files, help for inexperienced users, software to download, games and diversions, commercial sections and even advertising.

The reason I prefer using bulletin boards to Prestel or Microtel, which are the other systems readily

## Get your across bulletin

available to the home micro user, is that they provide a very interactive type of environment, completely different in character to videotex systems such as Prestel.

With a BBS you are always able to respond to the information on the system.

If you see something that interests you, you can leave a message about it, either to the originator of the item or to anyone else who calls the system.

In fact exchanging messages is really what BBS are all about.

There will always be a good bit of straightforward information on such systems, but it is usually there in a secondary role. For example there will probably be:

- Information about the system itself and how to use it.
- Information about particular subjects in the special interest sections.
- Files you can download into your own micro.
- Telephone numbers of other systems.

But unless the system has a particular theme of its own, you are unlikely to find much information of general interest on it.

If you are looking for train times, weather reports, financial information, hotel bookings and suchlike the large commercial systems such as Prestel are the place to go.

There is, of course, a certain amount of overlap between Prestel systems and BBS. You will find some news about the micro scene on Microtel and Viewstar 258 on the Prestel system, and also on some



# message on a board

BBBs. But on the whole the Prestel systems are very much more one way.

They do have response frames, or places where you can leave messages to the operators of the database concerned, but they don't normally have the public message areas that BBBS have.

The other advantage of BBBS is that they are open to anyone with no subscriptions or membership, and are free of charge (except for the cost of the phone call).

On the other hand ordinary Prestel will cost you £8.50 a quarter (i.e. VAT), and Microw Prestel (which has the software and some other features from the Microwest system on it these days) is a further £10 a quarter.

However most people can get Prestel with a local call, which is something that cannot be said for a BBBS. A long distance call can soon chalk up a couple of quid.

If you are choosing a modem my advice would be — if you can possibly afford it — to look for a multi-mode type that will allow you to use both V.21 (300 bps) — most BBBS and V.23 (1200/75 bps) — Prestel systems.

The same applies to software. Buy a terminal program that will enable you to use both systems, but remember that to use both you need the right modem AND the right software.

There's no such thing as software that will allow you to use a V.21 system via a V.23 modem, or vice versa.

Happy communicating!

Board	Synop	Phone no.	Hours
<b>SAREX</b>	Nick Rimmer	0608-684004	24 hrs
<b>LEBS</b>	Ray Apperell	0500-38526	24 hrs
<b>BARBS</b>	Mark Temperley	0228-23276	21.00-05.00 weekdays 21.00-12.00 weekends
<b>NRABBS</b>	Dave Frost	(Ring-back) 0784-842324	21.30-24.00 daily
<b>Forum '84</b>	Dave Harvey	(Ring-back) 0800-42013	24 hrs
<b>Banthon (FEC)</b>	Tony Dwyer	(Ring-back) 0266-25152	24 hrs

All the above boards operate at 300 baud.

## Ring-back procedure

Where a board is listed as "Ring-back", it is important to use the following procedure:

- Dial the number of the board.
- Let the phone ring once and then HANG UP.
- Dial the number again and let it ring until you hear the carrier tone.
- Switch your modem into "connect mode" and converse with normal procedure.

About 90 per cent of people who ring these boards let the phone ring several times. Then when the tone answers, assuming it to be a valid call, they hang up. Synops find this very irritating!

Standard 65 332 setting  
for use with an old terminal:  
I bit word  
Inverting parity 00  
Even parity  
1 stop bit

Alternative setting that  
should work with most SAs:  
8 bit word  
No parity  
1 stop bit

I recommend that you use the second setting, as most terminal software just ignores parity anyway, and it will normally work satisfactorily. It also gives the added possibility of transferring binary data using standard CPM protocols or XMODEM protocols which give you the file transfer — and which aren't just for CPM systems.

# Trainees call link Basildon

**BASILDON ITEC** is a training centre in Basildon, Essex set up to offer courses on Information Technology, primarily for the Youth Training Scheme (YTS). The ITEC opened for trainees in February 1984 and has been extremely busy ever since.

Courses in office skills, such as word processing and database management, programming and electronics are available to trainees, using a variety of different computers. Currently we have four computer networks as well as many stand alone devices.

We have been using an Atari computer since the ITEC opened. Initially this was an Atari 900, but it has recently been replaced with an 800 XL, which is used for a variety of tasks, including the trainee and staff payroll.

The Atari is used as both the manager, Malcolm Bridges and myself have Ataris at home and can transfer data easily from one machine to another.

However the Atari's primary task is communications. It was initially used in this way in the summer of 1984 when we acquired some modems and a simple terminal program. This enabled us to log on to many private and commercial bulletin board systems. This stimulated considerable interest, particularly on my part, and our phone bills jumped through the roof.

Basildon ITEC's bulletin board runs on an Atari 800XL with a 1050 disc drive and an 850 interface to handle the signals to the modem and printer (an Epson MX100).

It uses software from the USA known as Airlis. This was sent to us by the Rainbow Computer Company in Orlando, Florida, after we had logged into their system and had a chat with the systems operator (myself).

The system operates at 300 baud (300 bits per second) transmit and receive, accepting calls from any computer system operating in Airlis at that rate. However it is rather clever in that it can recognise Atari computers. This is because Airlis can operate in an enhanced character mode known as AHARLIS or Atari Airlis.

When a user logs on it checks for the value transmitted by the Return

key. The system will then allow the user to download Atari programs from our database.

Calls can leave messages for each other, and privately for us to read. All incoming calls are logged to the disc and printer and all messages are printed out. Private messages to the sysop, however, are not logged to the disc.

The system is very easy to use and offers help menus for the inexperienced. The information on offer is in the main about Basildon ITEC.

## By TONY DWYER

although we do get some interesting messages.

If you would like to call our BS, you will need the following (assuming that you are an Atari user):

- An Atari computer (at least 48k)
- A disc drive (510 or 1050)
- A modem (I recommend HSC0000 or Pace Nightingale). Set it at 300 baud. Depending on the modem you choose, you may also need an Atari 850 interface unit.
- Terminal software
- A telephone line
- A printer would be handy

(Readers might like to take advantage of our special communications offer on Page 39.)

Having connected it all together and managed to get the software to run, you are ready to go.

Dial our BS number - it is Basildon 0288 25122. You will hear a ringing tone for a couple of seconds, then you will hear a continuous high pitched tone. This is the carrier tone.

At this point switch on your modem - its carrier detect light should come on. Press the Return key on your Atari a few times. A display

will appear asking you to press Return again.

At this point it is testing to see whether it has an Atari on line or some other computer. It will then start transmitting pure text, asking you some polite questions. As soon as you get plain, readable text, put your phone down.

After you answer it will log your call and let you in to the system. If you call during the day you might like to try the Yell command (menu option 'Y'). It will send a bell at our end and one of us may break in for a chat via the keyboard. We have made many new friends this way.

Once you get into our system you will find information which we hope you find interesting and useful. One file in which you may be particularly interested is a list of other bulletin boards in the UK. (Beware, if you don't transmit fast for more than two minutes you will be timed out and disconnected.)

Our system permits the downloading and uploading of programs using Xmodem protocols. Xmodem will ensure that you get a clean download of data.

It does this by sending a block of data and checking a checksum value returned by the receiving computer. If an error is detected it sends the block again. In this way complex programs can be sent. Even machine code is transmitted safely.

Many terminal programs are available for the Atari - commercial ones such as Telnet and the excellent Home Term. There are also some public domain programs around including Term and Amodem.

Our Atari is also used for other tasks. For example, we manufacture a light pen for the Atari computers. Each one is tested on our machine using our own software and sent out with a disc of introduction programs written by myself. The pens are made in our electronics laboratory by our

# on Atari to to the world!

## YTS trainees.

As our working day is very full I often work at home in the evenings on my own Atari 800. It is used to check out the bulletin board system and for looking away at ideas for use at work.

One of these is a recently completed program called Joe Bailey. This is an action maze game working in 80 column mode.

The main program consists of a file handler which reads in a file from the disc. In the file is data which the handler uses to identify the new available files (possible choices at nine). The user makes the choice — a

one-finger press and the next screen is displayed.

In this way it is possible to have nine different combinations from any of the 64 files available. The idea of the game is to demonstrate how a manager's decision affects the actions of others in a subordinate role. We use it as part of the "Life and social skills" training for our YTS trainees.

In addition to our normal daytime activities our computer club meets on Friday evenings. Most of the members are Atari owners. It is not a formal environment like some clubs, more a social gathering of interested

people. We even allow them access to some of our computers.

We have many plans for the future. One involves more Ataris — we have eight 800 XLs on order. These will be used to train primary school children in computer use, making use of the Atari teach tablets and probably Logo.

We plan to involve local schools in this project, intending to give large numbers of young children access to computers under supervised conditions. We also plan to run computer camps during the school summer holidays, again using the Ataris.

Children will be able to spend up to a week, maybe longer, on our premises with guidance on how to use, and possibly program, the computers. We feel that Logo will be very important in this activity. This idea has already been very successful in the USA and we hope to achieve similar results here. I hope to keep you posted in Atari User later in the year.



**Join the communications revolution**

# We've found the missing link!

By **DEREK MEAKIN**  
Managing Editor  
Atari User

NINETY months ago we knew that 1985 would be the Year of Communications. And so it is turning out.

Sales of modems are soaring. More users are joining Postal in their thousands. Bulletin boards are springing up all over the country.

But what was one thing has been missing.

What has been desperately needed was a national database for microcomputers that would combine a low-cost, electronic mail service with a giant bulletin board you could access first time every time, that would allow you to chat freely with other users, that would have no restriction on the length of material you could send or receive — and would also enable you to send telecopied telemessages from your own micros.

All this, and much much more, you can do with MicroLink. For this one comprehensive service is the missing link in Britain's communications network.

And the center through which all MicroLink's facilities are being

offered is the most respected name of all — Telecom Gold.

Until now, Telecom Gold has been the preserve of big business — used by the giants of industry, commerce and finance to link their operations in Britain with the rest of the world. And Telecom Gold's charges reflected its elevated status.

That has now changed. Thanks to MicroLink, every Atari user can afford to log into Telecom Gold and make use of its growing range of services. For less than the cost of a first class stamp you can have a message the size of this page delivered to one destination or hundreds — all in a fraction of a second. And that's just one example of the time and money you'll be able to save with MicroLink.

All of us at Atari User are very excited about the enthusiastic reception the new service has been given by our readers — and about its unlimited potential for future development.

Come and join us — and explore with us the whole new world that is being opened up by MicroLink.



## SOFTWARE WORLD

12 ETHEL STREET, BIRMINGHAM B2  
Tel: 021-643 7559

THE MIDLANDS LARGEST STOCKISTS OF ATARI



**SOFTWARE AT AMAZING PRICES!**  
(vs. Atari from £4.99)

**ATARI COMPUTERS**  
BOOK/1000 BBS DRIVE PAGE  
incl. Home Filing Manager  
Pay Off, Test Adventure  
Sound & Graphics Demo

**£249.99**

**BOOK/1000 BBS ORDER PAGE**  
incl. File Position  
Get To Programming  
Sound & Graphics Demo

**£129.99**

**BOOK/1000 COMPUTER**  
incl. JoyStick  
Program

**£99.99**

**ALL LATEST ATARI SOFTWARE**  
INCLUDING V.C.C. CARTRIDGES  
IN OUR NEW 1ST FLOOR  
ATARI CENTRE

**SEND S.A.E. FOR FREE LISTS**

(Specify Machine)

**ATARI BOOKS & MAGAZINES**

ANTIC

ANALOG

PAGE 6

ATARI USER

(incl. S.A.C. & S.A.B.)

**PLACE YOUR REGULAR  
ORDER WITH US NOW**

**MANY ATARI BOOKS IN STOCK**

**BACK IN STOCK**

Atari/Telecom Gold Home	£19.99
Atari/Telecom Gold	£19.99
Atari/Telecom Gold	£19.99
Atari/Telecom Gold	£19.99

**ATARI STOP PRESS!**

Atari/Telecom Gold Home	£19.99
Atari/Telecom Gold	£19.99
Atari/Telecom Gold	£19.99
Atari/Telecom Gold	£19.99
Atari/Telecom Gold	£19.99
Atari/Telecom Gold	£19.99
Atari/Telecom Gold	£19.99
Atari/Telecom Gold	£19.99
Atari/Telecom Gold	£19.99
Atari/Telecom Gold	£19.99

Please phone to check stock availability before sending money

**REMEMBER**

**IF WE DO NOT HAVE WHAT YOU REQUIRE IN STOCK  
WE CAN NORMALLY OBTAIN IT FAST!**

**U.S. & AMERICAN SOFTWARE IS AVAILABLE**

Most of our U.S. and Am. titles (including books and magazines)  
Quickly despatched by return post, sent for up to date lists


**ATARI SELECTED CARTRIDGES**

Atari/Telecom Gold Home	£19.99	Phone
Atari/Telecom Gold	£19.99	Phone
Atari/Telecom Gold	£19.99	Phone

# MicroLink

in association with

**TELECOM GOLD**



MicroLink is this year's most exciting - as well as most ambitious - development in the rapidly-expanding world of telecomputing.

For the first time, it combines the enthusiasm of many thousands of computer users with the power and versatility of Britain's national database, Telecom Gold.

The result is an international communications link that is your passport to new realms waiting to be explored, new experiences to be shared with kindred spirits who enjoy telecomputing just as much as you do yourself.

Communicating the MicroLink way is ultra-fast - and much cheaper than you might expect. Whenever you line, you get direct access to the Telecom Gold computer at local call rates.

With your own electronic mailbox you can send a message to one destination - or to 5000 - for less than you would pay for a first class stamp.

You can send and receive telex messages workable, or have a two-way chat with other users in real time.

And the cost of using MicroLink? Just £3 a month. Plus small additional access charges as detailed overleaf.

Join MicroLink now - and let you and your Atari be in the forefront of the new revolution in communications!

These are some of the innovative features  
you'll be able to use when you join...

# MicroLink

## What facilities you can use - directly from your micro:

- Access at any hour of the day or night to Microsearch, our exclusive product locator, which is constantly updated by Britain's major distributors. Powerful, easy-to-use keyword searching means you should find what you want within seconds.
- Direct contact, via electronic mail, with other users throughout the world. And because you're connected via PSS, and not the normal phone links, it's usually much, much cheaper.
- Full use of the closed user group bulletin board - with a special section for Atari users.
- Full service of news about new products and events. All presented in easy-to-read form to keep you right up to date with what is happening in the world of microcomputing and communications.
- Send and receive mailbox messages of any length with other Telecom Gold mailbox users, the number of which is rapidly growing.
- Send and receive telex messages, both within Britain and all over the world.
- Send telemessages to any address in the UK. If sent before 10pm they will get guaranteed delivery the next working day, including Saturday (This service commences shortly.)
- If you live outside the 01- local call area, use of PPS in local phone call charges, including access to the international Telecom systems. (This covers nearly 90 per cent of the population of the UK.)
- Use, should you require it, of the Telecom Gold mainframe for storage of your own data.
- Encouragement to combine with friends or colleagues to set up your own closed user group within MicroLink.
- Provision of free telesoftware, which you can download into your Atari.

## What you will receive when you join MicroLink:

- Free registration on Telecom Gold - and your own private mailbox.
- Free password, which you can change at any time you like. This gives you a high level of security in order to preserve confidentiality, and is known only to you.
- Free instructional manual to introduce you to Telecom Gold and its many services.
- Free Help facility should you require additional assistance.
- Free newsletter to keep you informed of future developments in this ever-expanding service.

## What you need to access MicroLink:

- Any personal computer, portable computer, hand-held device or electronic typewriter with communications facilities.
- Appropriate communications software.
- Modem (you can use 300/300, 1200/75 or 1200/1200 baud as you wish).

## What will it cost?

- Monthly standing charge of £3 (compared to Telecom Gold's normal £10 a month minimum charge).
- Connect charges: 3.5p a minute (cheap rate); 10.5p a minute (standard rate). Plus 2p a minute PPS charge if calling from outside the 01- call area.
- Once-only telex registration fee (if required): £30.
- Outgoing telex: 5.5p per 100 characters (UK), 11p (Europe) and 16.5p (USA).
- Incoming telex: 50p.
- International mail: 30p for first 2,048 characters, then 15p for each additional 1,024 characters.
- Telexmessages: £1.25 for a maximum of 360 words or 35 single spaced lines.
- Online databases on Telecom Gold: charges as indicated at time of inquiry.

To secure your immediate registration, complete the form opposite and return it to:  
MicroLink, Europa House, 68 Chester Road, Hazel Grove, Stockport SK7 8NY.

# MicroLink

In association with

**TELECOM GOLD**

## Application Form

On receipt of this application form you will be sent:

- your personal mailbox number and initial password
- a Green Card (code to find mailbox)
- a customer 168 1242 telephone number
- the status and mailbox number of your Telecom Gold contract

*Please allow 28 days to process your application.*

### Charges

**Initial Registration Fee:** £25

**Monthly Charge:** £2 per calendar month or part.

Customers charged for duration information, by any payment to the Service. Minimum call charge is 1 minute.

### Standard Rate

1900 1242 427 excluding public holidays 11.00 per minute or part.

### Class Rates

**Gold other than 1**

3.50 per minute or part

**Other than 1**

£1.00 per minute or part

**Extra charge for groups of information**

20p per call at 5500 - 5500000 per month

**Other:** The number of local calls is an average calculated by reference to a daily average. Calls will be charged by the unit of 100, above codes and mail filing.

### Information Database

There may be changes and are charged at the rate shown before you obtain access

**MicroLink 9000 service**

1000 local 3p per minute or part,

1000 local 3p per minute or part,

1000 local 3p per minute or part,

1000 local 3p per minute or part,

1000 local 3p per minute or part,

1000 local 3p per minute or part,

1000 local 3p per minute or part,

1000 local 3p per minute or part,

1000 local 3p per minute or part,

1000 local 3p per minute or part,

1000 local 3p per minute or part,

1000 local 3p per minute or part,

1000 local 3p per minute or part,

1000 local 3p per minute or part,

1000 local 3p per minute or part,

1000 local 3p per minute or part,

### International Mail

Charges for the transmission of information by the Telecom service to other Telecom systems operators outside the UK and the list of UK operators.

Area	Country	Rate	Rate
UK	UK	20p	20p
Europe	Europe	20p	20p
USA	USA	20p	20p
Canada	Canada	20p	20p
Japan	Japan	20p	20p
Other	Other	20p	20p

*Please refer to our address for more information on international rates.*

### Billing and Payment

Charges are paid on a monthly basis.

Currently, bills are provided monthly and payable on receipt of invoice.

### Telnet

Telnet registration: £10

Telnet outdialing: For the generation of calls by the Telecom service.

UK:

1.00 per 100 characters sent

Europe:

1.00 per 100 characters sent

USA:

1.00 per 100 characters sent

Canada:

1.00 per 100 characters sent

Japan:

1.00 per 100 characters sent

Other:

1.00 per 100 characters sent

1.00 per 100 characters sent

1.00 per 100 characters sent

1.00 per 100 characters sent

1.00 per 100 characters sent

1.00 per 100 characters sent

1.00 per 100 characters sent

1.00 per 100 characters sent

1.00 per 100 characters sent

1.00 per 100 characters sent

1.00 per 100 characters sent

1.00 per 100 characters sent

1.00 per 100 characters sent

1.00 per 100 characters sent

1.00 per 100 characters sent

1.00 per 100 characters sent

1.00 per 100 characters sent

1.00 per 100 characters sent

1.00 per 100 characters sent

1.00 per 100 characters sent

1.00 per 100 characters sent

1.00 per 100 characters sent

1.00 per 100 characters sent

1.00 per 100 characters sent

1.00 per 100 characters sent

1.00 per 100 characters sent

1.00 per 100 characters sent

### Name

\_\_\_\_\_

### Company

\_\_\_\_\_

### Address

\_\_\_\_\_

### Telephone

\_\_\_\_\_

### Telex

\_\_\_\_\_

### Other

\_\_\_\_\_

### Signature

\_\_\_\_\_

### Date

\_\_\_\_\_

### Address

\_\_\_\_\_

### Company

\_\_\_\_\_

### Address

\_\_\_\_\_

### Company

\_\_\_\_\_

### Address

\_\_\_\_\_

### Company

\_\_\_\_\_

### Address

\_\_\_\_\_

### Company

\_\_\_\_\_

### Address

\_\_\_\_\_

### Company

\_\_\_\_\_

### Address

\_\_\_\_\_

### Company

\_\_\_\_\_

### Address

\_\_\_\_\_

### Company

\_\_\_\_\_

### Address

\_\_\_\_\_

### Company

\_\_\_\_\_

### Address

\_\_\_\_\_

### Company

\_\_\_\_\_

### Address

\_\_\_\_\_

### Company

\_\_\_\_\_

### Address

\_\_\_\_\_

### Company

\_\_\_\_\_

### Address

\_\_\_\_\_

\_\_\_\_\_

\_\_\_\_\_

\_\_\_\_\_

\_\_\_\_\_

\_\_\_\_\_

\_\_\_\_\_

\_\_\_\_\_

\_\_\_\_\_

\_\_\_\_\_

\_\_\_\_\_

\_\_\_\_\_

\_\_\_\_\_

\_\_\_\_\_

\_\_\_\_\_

\_\_\_\_\_

\_\_\_\_\_

\_\_\_\_\_

\_\_\_\_\_

\_\_\_\_\_

\_\_\_\_\_

\_\_\_\_\_

\_\_\_\_\_

\_\_\_\_\_

\_\_\_\_\_

\_\_\_\_\_

\_\_\_\_\_

\_\_\_\_\_

\_\_\_\_\_

\_\_\_\_\_

\_\_\_\_\_

\_\_\_\_\_

\_\_\_\_\_

\_\_\_\_\_

\_\_\_\_\_

\_\_\_\_\_

\_\_\_\_\_

\_\_\_\_\_

\_\_\_\_\_

\_\_\_\_\_

\_\_\_\_\_

\_\_\_\_\_

\_\_\_\_\_

\_\_\_\_\_

\_\_\_\_\_

\_\_\_\_\_

\_\_\_\_\_

\_\_\_\_\_

\_\_\_\_\_

\_\_\_\_\_

\_\_\_\_\_

\_\_\_\_\_

\_\_\_\_\_

\_\_\_\_\_

\_\_\_\_\_

\_\_\_\_\_

\_\_\_\_\_

\_\_\_\_\_

\_\_\_\_\_

\_\_\_\_\_

\_\_\_\_\_

\_\_\_\_\_

\_\_\_\_\_

\_\_\_\_\_

\_\_\_\_\_

\_\_\_\_\_

\_\_\_\_\_

\_\_\_\_\_

\_\_\_\_\_

\_\_\_\_\_

\_\_\_\_\_

\_\_\_\_\_

\_\_\_\_\_

\_\_\_\_\_

\_\_\_\_\_

\_\_\_\_\_

\_\_\_\_\_

\_\_\_\_\_

\_\_\_\_\_

\_\_\_\_\_

\_\_\_\_\_

\_\_\_\_\_

\_\_\_\_\_

\_\_\_\_\_

\_\_\_\_\_

\_\_\_\_\_

\_\_\_\_\_

\_\_\_\_\_

\_\_\_\_\_

\_\_\_\_\_

\_\_\_\_\_

\_\_\_\_\_

\_\_\_\_\_

\_\_\_\_\_

\_\_\_\_\_

\_\_\_\_\_

\_\_\_\_\_

\_\_\_\_\_

\_\_\_\_\_

\_\_\_\_\_

\_\_\_\_\_

\_\_\_\_\_

\_\_\_\_\_

\_\_\_\_\_

\_\_\_\_\_

\_\_\_\_\_

\_\_\_\_\_

\_\_\_\_\_

\_\_\_\_\_

\_\_\_\_\_

\_\_\_\_\_

\_\_\_\_\_

\_\_\_\_\_

\_\_\_\_\_

\_\_\_\_\_

\_\_\_\_\_

\_\_\_\_\_

\_\_\_\_\_

\_\_\_\_\_

\_\_\_\_\_

\_\_\_\_\_

\_\_\_\_\_

\_\_\_\_\_

\_\_\_\_\_

\_\_\_\_\_

\_\_\_\_\_

\_\_\_\_\_

\_\_\_\_\_

\_\_\_\_\_

\_\_\_\_\_

\_\_\_\_\_

\_\_\_\_\_

\_\_\_\_\_

\_\_\_\_\_

\_\_\_\_\_

\_\_\_\_\_

\_\_\_\_\_

\_\_\_\_\_

\_\_\_\_\_

\_\_\_\_\_

\_\_\_\_\_

\_\_\_\_\_

\_\_\_\_\_

\_\_\_\_\_

\_\_\_\_\_

\_\_\_\_\_

\_\_\_\_\_

\_\_\_\_\_

\_\_\_\_\_

\_\_\_\_\_

\_\_\_\_\_

\_\_\_\_\_

\_\_\_\_\_

This contract is made between Continuum Publications Ltd, of Europa House 68 Chester Road, Broad Green, Liverpool L67 5NY (DPL) and the subscriber whose name and address appears marked.

Whereas DPL has agreed with British Telecommunications plc (BT) through its agent Telecom Gold Limited to sell and distribute the Official set Service (the Service) and BT through Telecom Gold Limited has agreed to supply the Service to customers of DPL.

It is agreed as follows:

- Access**
  - DPL shall cause the subscriber each and every installation/extension numbered as follows hereunder to allow the Subscriber and persons associated with the subscriber access to use the Service.
- The Service**
  - The Service shall be BT's Telephony Gold Business Service, and shall comprise such services and facilities as DPL, and in its discretion from time to time provides appropriate, subject to the supply by BT of such services and facilities.
- Charges**
  - The subscriber shall pay to all charges arising under this contract from its subscription and/or use of the Service, and/or from the transmission of any mailboxes, numbers issued by DPL, or the Subscriber. All charges are payable on demand.
  - DPL shall give to the Subscriber not less than business days' written notice of any alteration in the applicable charges for the Service. The charges applicable at the date of the Subscriptions are set out hereunder.
  - Subject to any provision of this contract, liability for charges for certain dual-rate services shall be the Subscriber's responsibility to the contrary with effect from the first day of the month in which BT first makes services available to the customer.
- Limitations on use**
  - The Subscriber shall not use, or permit any persons to use, the Service otherwise than in paying for connections, purely by DPL, or BT, existing for the time being and in particular, shall not use the Service for the purpose of sending abusive, offensive, indecent or menacing communications, or for sending communications which cause annoyance, inconvenience, or needless anxiety.
  - The Subscriber shall not permit any person to use the Service to transmit a mailbox number issued by DPL, unless the name and relationship of that person to the Subscriber has been disclosed to DPL.
- Termination**
  - This contract may be terminated by either party giving not less than one month's written notice in each notice to expire on the last day of any calendar month.
  - DPL may terminate this contract without notice if the Subscriber shall:
    - fail to pay any sums payable under this contract or payable under any other contract with DPL, or to which the Subscriber is a party;
    - be subject to bankruptcy, enter into liquidation or any arrangement in connection with its winding up, or a receiver is appointed of any part of the Subscriber's assets (which does not include within them, or if it is agreed in writing by the Subscriber otherwise provided for more than seven days, will not comply with any terms of this contract) or any other person, apart from DPL, or BT under clause 4 of this contract;
    - DPL may terminate this contract without notice in the event that BT and/or its agent Telecom Gold shall cease to supply the Service;
    - if the customer fails to comply with any provision of this contract he shall nevertheless continue to be liable for all charges due and to become due for services provided during any period of such failure.
- Assignment**
  - The subscriber shall not, without the written consent of DPL, assign this contract, or any rights or obligations arising under this contract.
- Limitation of liability**
  - Neither subscriber nor DPL nor BT has any obligation that is liability contract, tort, tortious or statutory, duty or otherwise beyond that of a duty to exercise reasonable skill and care.
  - In any event no compensation shall either DPL, or BT be liable in contract, tort or tortious negligence or breach of statutory duties or otherwise for loss (whether direct or indirect) of profits, business, or anticipated savings or for any indirect or consequential loss whatsoever.
  - In any event DPL's liability contract, tort (including negligence or breach of statutory duties) or otherwise arising in respect of or in connection with this contract or transaction otherwise shall be limited to £500,000 for any one incident or series of incidents and £2 for any one series of incidents calculated or combined in any period of 12 months.
  - DPL, does not include or intend to include in liability for death or personal injury, claims made in or as a result of the negligence of DPL, or its employees.
  - The Subscriber shall indemnify DPL, against all loss, actions, proceedings, costs, claims and damages arising from:
    - any breach by the Subscriber of its obligations hereunder;
    - the use of the Service by third parties for reasons of any mailbox number issued to the Subscriber.
  - DPL shall neither be liable for any loss or damage occurring through any act or omission of BT or its agent Telecom Gold Limited, neither employee or failure to supply the Service to DPL. Notwithstanding anything to the contrary contained hereby the supply of the Service under this contract shall be subject to the standard terms and conditions of BT, from time to time and of which the subscriber shall be deemed to be aware.
  - Neither party shall be liable for failure to perform its obligations if the failure results from an Act of God, Act of Government or other Authority or Statutory requirement, war, epidemic, accident, power failure, industrial dispute, rioting, or other materials or anything beyond its reasonable control.
  - DPL accept liability/underwriter for three days (three) in the event of a subscriber whose call has been received by BT or its agent Telecom Gold Limited, the subscriber under the provision of service to the subscriber to aggregate maximum of £1,000.00 a year apart to one month's average service charge to the subscriber over the previous 12 months' period, subsequent to another three or otherwise provided herein, DPL shall be under no liability for any loss suffered by the subscriber or by any other person arising from negligence or otherwise.
- Assignment**
  - Assignment to other persons and assignment to other persons is hereby prohibited by either party to the other, shall be made in writing and may be made by deed (but not by deed) to the address of the other as set out herein, and shall be deemed to have been received 48 hours from the time of posting.
- Agreement**
  - This agreement constitutes the entire agreement between the Subscriber and DPL, and covers all business and re-consideration, statement, warranty or condition not expressly contained in this agreement or incorporated herein by reference, shall be binding upon DPL in a variety of situations.
- Other**
  - This agreement shall be governed and construed in accordance with the laws of England, and the English Courts shall have exclusive jurisdiction to determine any disputes arising hereunder.



**A money-saving special offer from** **ATARI USER**

# THIS is your passport into the exciting world of telecomputing!



*Price includes HWT, post & packing*

ITS by far the fastest growing field in micro-computing. All over the world micros are talking to each other over the telephone line. As well as to the ever-increasing number of public and private databases, bulletin boards - and even giant mainframe computers.

We want all Atari User readers to share in the new technology that makes all this possible. So we're offering a unique starter pack at an unbeatable price. It gives you everything you need to get in touch with the big wide world outside:

- Modem
- Software
- Serial Interface

The modem is the amazing Miracle Technology WS2000. One of the most powerful on the market, it provides all the facilities you require. Yet it's simplicity itself to use. Just plug it into a standard British Telecom jack and you're away!

The package also features the superb Atari serial interface, which links the modem directly to the Atari's peripheral port without the need for the 850 serial interface.

The best hardware deserves the best

software to drive it, and with the specially written Multi-Viewterm program the package is complete. It supports all the standard baud rates - 1200/75, 75/1200, 1200/1200 and 300/300 full duplex.

Your Atari User package will allow you to talk directly to other computers, to send your own telex messages, to go tele-shopping - even to download free software programs directly into your Atari.

You will be able to join Micronews/Prestel, which will immediately open up to you a vast menu of 750,000 pages of information - instant world news, sports, holidays, hotels, train and airline timetables, all regularly updated.

And you can become one of a growing number of enthusiasts who are joining MicroLink, the giant database set up in conjunction with Telecom Gold, which is described more fully in this issue.

But first, send for the Miracle package - and enter the fascinating, limitless world of communications!

**Use the order form on Page 61**

**ROBIN HUDSON** says: Forget the past, get on to the right number and...

**COMMUNICATIONS** is, perhaps, the most interesting area of microcomputing that has yet to be explored by the majority of home computer users.

For many years now the public telephone network has been used to transfer data between computers which are often many hundreds of miles apart.

For companies using computers in this way the advantages are obvious. Large volumes of data, including programs, can be transferred between various establishments very rapidly and without the necessity to physically transport discs, tape or any other storage media.

It is only recently however that the additional equipment — both hardware and software — that was needed to take advantage of the telephone in this way has become sufficiently inexpensive to be used widely in the home.

So let's examine the possibility of using the *Asal* to communicate via the telephone system.

There are many advantages in doing so.

One major application is the ability to access data which is held on other, often very large, computer systems. The best known example of this is the *Telecom* (job service, although many other public database systems exist.

This is an area which is currently arousing great interest, and which will no doubt become one of the more significant aspects of computing in the future.

The transfer of files to other computers, in the same way as is done between mainframe installations, is another area that has great potential in the home.

You've just written a new utility program which you would like a friend, who happens to live at the other end of the country, to test for you.

Instead of sending a fragile disc, which could take days to arrive, you could simply send a copy of the file over the telephone in the space of a phone call.

Another type of system, the "bulletin board" is peculiar to microes. Bulletin boards were first developed

# Serialise, modulate, communicate!

in America where micro communications has progressed to a more advanced state than in Europe.

It is simply a micro which accepts telephone calls from other micro-users and allows them to access its files, download programs, and, as with electronic mail systems, leave messages for other callers.

It is quite common to find that such systems operate on a worldwide basis with users calling from countries as far apart as Australia, Britain and America.

These are just a few of the possible applications. But what about the equipment required to use the telephone network in this way?

Fortunately the rapid development of large and very large scale integration technology in recent years has made it possible to produce suitable equipment at prices which are no longer prohibitive.

The obvious starting point is some form of interface. In the case of the *Asal*, until recently this has meant the

9600 serial interface module.

The reason for using a serial interface, as opposed to a parallel interface such as that used with Centronics-type printers, is fundamental to the whole area of long distance transmission of data.

Since the telephone network uses only two, three or four wire circuits, data must be transferred in serial form, one bit at a time, in sequence.

However data within a computer is transferred in parallel. This means that in an 8 bit machine such as the *Asal*, eight individual wires, known collectively as the data bus, are used to move information around a byte at a time. This is termed parallel transfer because eight bits are transferred simultaneously.

We have noted that the primary reason for serialising data for transmission over the telephone network is simply that there are insufficient wires to transmit eight bits at a time. Indeed, it would be




Figure 1: Data shown in parallel transfer

extremely expensive to lay eight cables instead of one, and even if this were possible there are further complications with respect to parallel data transfer.

These revolve around the fact that the individual bits of data tend to travel at different speeds within the wires and introduce what is known as data skew. The result is that the data becomes garbled.

This effect, illustrated in Figure 1, is more noticeable over greater distances. It is one of the reasons that data cables used with parallel printers are rarely longer than about a metre.

We see then that the function of a serial interface is to convert data from a computer into serial form so that it may be transmitted via a circuit consisting of as little as two wires.

The parallel transfer of  $n$  data bits requires  $n+1$  individual wires,  $n$  wires for the data and one ground line.

In addition to the obvious economies of using fewer wires, serial data may be transmitted over longer distances than is possible with a parallel interface due to the absence of the skew effect in serial circuits.

What are the other ingredients of a communications system?

Consider the type of signals that a computer generates. These are digital in nature. The 1s and 0s are represented by two separate and distinct voltage or current levels, generally the former.

The public telephone network however was developed for a different application – the transmission of the human voice which is analogue, as opposed to digital, in nature.

The difference between the two types of signal, analogue and digital, can be seen in Figure 2.

The point is that the square waveforms produced by digital computers will not pass through the telephone network because of the nature of the network itself and various filters and switching equipment used in telephone exchanges.

To overcome this problem a further piece of equipment is required that will convert digital data into analogue form so that it can then be transmitted via the telephone net-




Figure 2. Analogue and digital waveforms

work. This task, termed modulation, is the function of a modem.

In practice a modem carries out two jobs. Digital data for transmission is modulated into analogue form before being passed to the telephone system.

Conversely, received analogue data is demodulated into digital form before being given to the computer.

Hence a modem is used to both *Modulate* and *Demodulate* electrical signals.

The final element involved is the software.

The facilities offered by communications software may vary greatly, but essentially it provides the means by which the serial interfaces, and the data passed between them, can be controlled.

Just as a disc filing or disc management system is used to store and retrieve information from disc, communications software may be regarded as the communications management system.

Thus, although the hardware provides the physical means by which data and files can be transferred, some form of protocol is required in order that each computer can understand and use the signals it receives from the other.

These protocols may be regarded as the equivalent of word, sentence and paragraph structure in a spoken language.

In the case of written text, punctuation is used in order to ensure that it makes sense to the reader. Similarly a protocol structure of some form is required to allow two computers to communicate sensibly with each other.

It is the software that provides this

structure, along with the facilities for storing and manipulating received data or data to be transmitted.

So we can see that three basic elements, apart from the computer, must be present in a communications system using the telephone network – a serial interface, a modem and the appropriate software.

On a smaller scale, within a particular room for example, it is perfectly possible to link the two computers together without using the telephone system.

In this case a direct wire link between the two serial interfaces is sufficient to allow communication to take place and no modulation is required. Provided that the distance between the computers is not too great there should be no problems.

Using a hard-wired link in this way, however, reveals a further advantage of using the telephone system.

When a hard-wired connection is used only the two computers involved can communicate with each other. The telephone system, however, offers far greater flexibility in that any two computers with access to a phone may be linked.

The 850 module allows a wide variety of modems to be used. Also, modems are now being marketed which don't require an 850 module.

Modems themselves may be obtained with various levels of sophistication, ranging in price from as little as £70 to several hundred pounds.

Communication between your Atari and almost any other type of mainframe, mini or micro is possible, so give it a try.

Serialise, modulate and communicate!



## Go Space-hopping with your Atari – plus a little help from TeleLink

TeleLink, Britain's pioneering communications magazine, is full of helpful advice about all the fascinating things you can do when you link your Atari to your telephone.

In the latest issue, now on sale, are special features on . . .

- How to cut down your phone bill: Taking the mystery out of the phone charging system.
- Start of a guided tour of the massive America database. Knowledge links.
- Telecom Gold: What it is, what it does, and how much it can cost.
- Round up of all the latest advances in the development of databases for schools.

- Ports and phone numbers of all the latest UK bulletin boards.
- Why FDS is the most economical way of accessing systems all over the world.
- Communicating with a portable: a detailed survey of all the latest lap-held micros.
- Guide to the latest telesoftware you can download from Petnet.
- Pages of up-to-the-minute news of happenings in the internet and database industries.
- Setting up a database system: a first hand report of how it's done.
- Communications in the City: a look at what can happen when financiers go on-line.

### ORDER FORM

#### Subscription for 12 issues

UK/EU	<input type="checkbox"/>	£60
US/CA/Mex	<input type="checkbox"/>	£80
Germany (Postnet) £20	<input type="checkbox"/>	£80
Germany (Normal) £30	<input type="checkbox"/>	£90

Payment: please indicate method [✓]

☐ Access Mastercard/Visacard/Postcard, Visa

☐ No payment needed (send no money)

☐ Cheque/PD made payable to: Database Publications Ltd.

Name \_\_\_\_\_ Signed \_\_\_\_\_

Address \_\_\_\_\_

Send to: TeleLink, FREEPOST, Europa House,  
48 Chandler Road, Hazel Grove, Stockport SK7 5PP.

(No money needed if paid in UK) Please allow 28 days for delivery.

YOU CAN ALSO ORDER BY PHONE: 061-480-0175 (24 hours)

Don't forget to quote your credit card number and full address. A/c



TeleLink deliberately  
steers away from  
technicalities to present  
the facts in vivid detail –  
to help you play YOUR  
individual part in the  
communications  
revolution that is going  
to change all our lives.

# Silicon Chip

## No. 1 FOR ATARI\*

### Atari 520 ST

#### **GUARANTEE**

Our **EXCLUSIVE** Direct Exchange Guarantee is available **FREE OF CHARGE** to all our customers. If a product purchased from **SILICON CHIP** becomes faulty due to a manufacturing or component defect, within **ONE YEAR** of purchase, we will, subject to availability, exchange for new.



#### **PRICES**

Atari 520 ST	£299.99
+ 500k Disk Drive	£299.99
+ Black & White Monitor	£199.99

The prices of the ST from **SILICON CHIP** Ltd. include Basic, Logo, a word Processor, GDM Drive and 68000 ports.

#### **POWER WITHOUT THE PRICE**

Chipsoft: Integrated Accounts Package - Including Stock Control, Nominal, Sales and Purchase Ledgers. **£290**. Final prices and specs may be subject to change.

#### **SPECS**

512K RAM.  
Expandable Ram.  
MGDI Interface. 85233  
Serial/Centronics Parallel  
Interfaces. Floppy Disk and Hard  
Disk interfaces. RGB Video and TV  
outputs. Sound Generator with 3 channels.  
2 Joystick Ports. 3 Graphics and Text Modes -  
320x200 - 512 colours, 640x380 - 4 colours, 640x400 B&W.  
16 Bit Motorola 68000 Microprocessor running at 8 mHz.

**SILICON CHIP LTD.** Showroom address:  
302 High Street, Slough, Berkshire. Tel: 0753 70629

- \* 1st Atari Business Centre.
- \* 1st Dealer for 130 XE.
- \* 1st Dealer for 1029 Printers.
- \* 1st Dealer with our own Software House for Software Support.
- \* 1st Dealer for 520 ST?

*Please phone or write for full details.*



# SUBMARINE

YOU are a destroyer captain alone in a hostile sea surrounded by a pack of submarines which are travelling secretly to a rendezvous. The submarines cannot break radio silence or send for help and must not attack you for fear of giving their position away, but you can sink as many of them as you can - with as few depth charges as possible.

On the screen will be shown a board divided into 100 squares. The submarine is hiding in one of these squares. The bottom (horizontal) line is called X and the upright (perpendicular) line is called Y.

Each line of boxes goes from 0 to 9 and you have to give the box numbers to the computer when it asks for your entry. You will be



asked to type in a number for the X and Y lines. If you think that the submatrix is in a box 8 across and 5 high then return 8 and 5 when the X and Y positions are asked for.

Wiederum ist eine weitere Variante möglich:

If you make a direct hit you will hear a noise and the screen will show you how many tries you took to sink the submarine.

If you wish, the computer will tell you if your shot was North.

South, East or West of the target and you must then plan your next shot. As soon as the submarine is sunk your computer will search


WILSON, J. W. 1994. *Field Guide to Reptiles and Amphibians*, 3rd ed. Houghton Mifflin, Boston, Massachusetts. 450 pp.

270	Open grid.
370	Header.
470	Print score.
500	Submarine hit.
670	Submarine missed.

[illegible][illegible]

```

100 FOR I=1 TO 10
200 PRINT I; I*2; I*3; I*4; I*5; I*6; I*7; I*8; I*9; I*10; I*11; I*12; I*13; I*14; I*15; I*16; I*17; I*18; I*19; I*20; I*21; I*22; I*23; I*24; I*25; I*26; I*27; I*28; I*29; I*30; I*31; I*32; I*33; I*34; I*35; I*36; I*37; I*38; I*39; I*40; I*41; I*42; I*43; I*44; I*45; I*46; I*47; I*48; I*49; I*50; I*51; I*52; I*53; I*54; I*55; I*56; I*57; I*58; I*59; I*60; I*61; I*62; I*63; I*64; I*65; I*66; I*67; I*68; I*69; I*70; I*71; I*72; I*73; I*74; I*75; I*76; I*77; I*78; I*79; I*80; I*81; I*82; I*83; I*84; I*85; I*86; I*87; I*88; I*89; I*90; I*91; I*92; I*93; I*94; I*95; I*96; I*97; I*98; I*99; I*100; I*101; I*102; I*103; I*104; I*105; I*106; I*107; I*108; I*109; I*110; I*111; I*112; I*113; I*114; I*115; I*116; I*117; I*118; I*119; I*120; I*121; I*122; I*123; I*124; I*125; I*126; I*127; I*128; I*129; I*130; I*131; I*132; I*133; I*134; I*135; I*136; I*137; I*138; I*139; I*140; I*141; I*142; I*143; I*144; I*145; I*146; I*147; I*148; I*149; I*150; I*151; I*152; I*153; I*154; I*155; I*156; I*157; I*158; I*159; I*160; I*161; I*162; I*163; I*164; I*165; I*166; I*167; I*168; I*169; I*170; I*171; I*172; I*173; I*174; I*175; I*176; I*177; I*178; I*179; I*180; I*181; I*182; I*183; I*184; I*185; I*186; I*187; I*188; I*189; I*190; I*191; I*192; I*193; I*194; I*195; I*196; I*197; I*198; I*199; I*200; I*201; I*202; I*203; I*204; I*205; I*206; I*207; I*208; I*209; I*210; I*211; I*212; I*213; I*214; I*215; I*216; I*217; I*218; I*219; I*220; I*221; I*222; I*223; I*224; I*225; I*226; I*227; I*228; I*229; I*230; I*231; I*232; I*233; I*234; I*235; I*236; I*237; I*238; I*239; I*240; I*241; I*242; I*243; I*244; I*245; I*246; I*247; I*248; I*249; I*250; I*251; I*252; I*253; I*254; I*255; I*256; I*257; I*258; I*259; I*260; I*261; I*262; I*263; I*264; I*265; I*266; I*267; I*268; I*269; I*270; I*271; I*272; I*273; I*274; I*275; I*276; I*277; I*278; I*279; I*280; I*281; I*282; I*283; I*284; I*285; I*286; I*287; I*288; I*289; I*290; I*291; I*292; I*293; I*294; I*295; I*296; I*297; I*298; I*299; I*300; I*301; I*302; I*303; I*304; I*305; I*306; I*307; I*308; I*309; I*310; I*311; I*312; I*313; I*314; I*315; I*316; I*317; I*318; I*319; I*320; I*321; I*322; I*323; I*324; I*325; I*326; I*327; I*328; I*329; I*330; I*331; I*332; I*333; I*334; I*335; I*336; I*337; I*338; I*339; I*340; I*341; I*342; I*343; I*344; I*345; I*346; I*347; I*348; I*349; I*350; I*351; I*352; I*353; I*354; I*355; I*356; I*357; I*358; I*359; I*360; I*361; I*362; I*363; I*364; I*365; I*366; I*367; I*368; I*369; I*370; I*371; I*372; I*373; I*374; I*375; I*376; I*377; I*378; I*379; I*380; I*381; I*382; I*383; I*384; I*385; I*386; I*387; I*388; I*389; I*390; I*391; I*392; I*393; I*394; I*395; I*396; I*397; I*398; I*399; I*400; I*401; I*402; I*403; I*404; I*405; I*406; I*407; I*408; I*409; I*410; I*411; I*412; I*413; I*414; I*415; I*416; I*417; I*418; I*419; I*420; I*421; I*422; I*423; I*424; I*425; I*426; I*427; I*428; I*429; I*430; I*431; I*432; I*433; I*434; I*435; I*436; I*437; I*438; I*439; I*440; I*441; I*442; I*443; I*444; I*445; I*446; I*447; I*448; I*449; I*450; I*451; I*452; I*453; I*454; I*455; I*456; I*457; I*458; I*459; I*460; I*461; I*462; I*463; I*464; I*465; I*466; I*467; I*468; I*469; I*470; I*471; I*472; I*473; I*474; I*475; I*476; I*477; I*478; I*479; I*480; I*481; I*482; I*483; I*484; I*485; I*486; I*487; I*488; I*489; I*490; I*491; I*492; I*493; I*494; I*495; I*496; I*497; I*498; I*499; I*500; I*501; I*502; I*503; I*504; I*505; I*506; I*507; I*508; I*509; I*510; I*511; I*512; I*513; I*514; I*515; I*516; I*517; I*518; I*519; I*520; I*521; I*522; I*523; I*524; I*525; I*526; I*527; I*528; I*529; I*530; I*531; I*532; I*533; I*534; I*535; I*536; I*537; I*538; I*539; I*540; I*541; I*542; I*543; I*544; I*545; I*546; I*547; I*548; I*549; I*550; I*551; I*552; I*553; I*554; I*555; I*556; I*557; I*558; I*559; I*560; I*561; I*562; I*563; I*564; I*565; I*566; I*567; I*568; I*569; I*570; I*571; I*572; I*573; I*574; I*575; I*576; I*577; I*578; I*579; I*580; I*581; I*582; I*583; I*584; I*585; I*586; I*587; I*588; I*589; I*590; I*591; I*592; I*593; I*594; I*595; I*596; I*597; I*598; I*599; I*600; I*601; I*602; I*603; I*604; I*605; I*606; I*607; I*608; I*609; I*610; I*611; I*612; I*613; I*614; I*615; I*616; I*617; I*618; I*619; I*620; I*621; I*622; I*623; I*624; I*625; I*626; I*627; I*628; I*629; I*630; I*631; I*632; I*633; I*634; I*635; I*636; I*637; I*638; I*639; I*640; I*641; I*642; I*643; I*644; I*645; I*646; I*647; I*648; I*649; I*650; I*651; I*652; I*653; I*654; I*655; I*656; I*657; I*658; I*659; I*660; I*661; I*662; I*663; I*664; I*665; I*666; I*667; I*668; I*669; I*670; I*671; I*672; I*673; I*674; I*675; I*676; I*677; I*678; I*679; I*680; I*681; I*682; I*683; I*684; I*685; I*686; I*687; I*688; I*689; I*690; I*691; I*692; I*693; I*694; I*695; I*696; I*697; I*698
```



Journal of Management Inquiry 22(1)

Report captions should be able to detect and sink the enemy within six seconds.

**VARIABLES**

SHOTS	Number of shots.
HITS	Number of hits.
SHOTX	X coordinate of shot.
SHOTY	Y coordinate of shot.
SUBX	X coordinate of sub.
SUBY	Y coordinate of sub.

**SUMMARY** is just one of the games listed in "40 Educational Games for the Atari" by Vince Apple, price \$5.95. We're grateful to Granada College for permission to reprint it here.

## 40 EDUCATIONAL GAMES FOR THE ATARI



```

0000 00000000
0000 0000 0000 0000
0000 0000000000000000
0000 POSITION 00 000000, 00 000000 0000 0000
0000 00000000
0000 0000 0000 0000 0000
0000 000000000000
0000 POSITION 00, 00 000000 0000 000000 0000 0000
0000 000000, 000, 000 0000 0000 0000 0000 0000
0000 000000 0, 0000, 00 0000 0000 0000 0000
0000 000000 0, 000, 00, 00 0000 0000 0000 0000
0000 000000 0, 00, 00 000000 0000 0000 0000 0000

```

[illegible]

THE POLYMER IS, IN FACT, AN "IN-  
TERMEDIATE"



**MIKE BIBBY**  
continues his series  
of articles aimed at  
lifting the veil of  
mystery cloaking  
the fundamentals  
of the Atari's  
workings

We have seen that we can code our numbers in ways other than our usual denary, or decimal, system. We also looked last month at a way of coding known as the binary system, which uses the digits 0 to 1 to represent any number — unlike the denary system which uses the digits 0 to 9.

To distinguish the two systems, we decided to prefix binary numbers with the symbol "B".

The number "one hundred and sixty two" is encoded in each system like this:

In denary,

$$162 = 100 + 60 + 2$$

In binary,

$$100 \ 60 \ 32 \ 16 \ 8 \ 4 \ 2 \ 1$$

$$\% \ 1 \ 0 \ 1 \ 0 \ 0 \ 0 \ 1 \ 0$$

$$= 128 + 32 + 2$$

Each column in the binary system, known as a "bit", contains either a one or a zero.

Although the binary representation of a number is rather cumbersome to write, this simple two-state system is easily represented by electrical circuits — which are either **on** or **off**.

We saw that the computer handled bits in groups of eight at a time. Such a group is called a byte. Thus a byte contains eight bits labelled, somewhat perversely, bits 0 to 7. (See figure 1.)

Bit 0, as you can see, is the "1" column. As this is the smallest value

bit we say that bit 0 is the least significant bit (LSB). Bit 7, the "128" column, is called the most significant bit (MSB).

The reason for using the numbers 0 to 7 to label the bits instead of the more logical 1 to 8 has to do with powers, a subject you almost certainly covered at school.

3 to the power 2 is  $2^2 = 4$   
2 to the power 3 is  $2^3 = 8$   
2 to the power 4 is  $2^4 = 16$   
2 to the power 5 is  $2^5 = 32$   
2 to the power 6 is  $2^6 = 64$   
2 to the power 7 is  $2^7 = 128$

Notice that as the powers of two increase — that is, as we multiply more twos together — the answers are doubling, just as our column or bit values do.

Also, 2 to the power of 2 is 4, the value of bit 2, while 2 to the power of 3 is 8, the value of bit 3. It shouldn't come as any surprise to you to find that 2 to the power of 7 is 128, the value of bit 7.

You can verify this on the Atari by

using the symbol "B" which stands for "to the power of". It shows a key with the "B" sign.

Try:

**PRINT 2^4**

**PRINT 2^0**

Be sure to try  $2^1$ , which will show you why bit 1 has the value 2. Also try  $2^0$ . The answer may surprise you. The fact is that any number to the power 0 is 1.

Hence bit zero has the column value of one. Figure 1 illustrates this.

Look at this sum:

$$\begin{array}{r} \% \ 1 \\ + \% \ 1 \\ \hline \% 10 \end{array}$$

If you think about it, that is correct, since the sum adds one and one, and the answer 10 in binary for two.

One way of relating this to our usual way of doing sums is to see that we carry when we get to two, instead of ten as we do in our normal, denary, sums.

Another way to look at it is that we have to carry when we get to two because we aren't allowed to use the digit "2".

If you remember, last month we had a rule forbidding two "coins" of the same value.

Try this sum:

$$\begin{array}{r} 4 \ 2 \ 1 \\ \% \ 1 \ 1 \ 1 \text{ in} \ 3 \\ + \% \ 1 \ 0 \text{ denary} \ 2 \\ \hline \% 1 \ 0 \ 1 \end{array}$$

Here we carry from the second column to the third.

Addition is not very hard at all — just make sure that you always "put 0 down and carry 1" when you get a two.

If you get a three then "carry one for two and put one down".

For example:

$$\begin{array}{r} 8 \ 4 \ 2 \ 1 \\ \% \ 1 \ 1 \ 1 \text{ in} \ 7 \\ + \% \ 1 \ 1 \text{ denary} \ 4 \\ \hline \% 1 \ 0 \ 1 \ 0 \end{array}$$

Subtraction is a little more complicated, and depends on whether

# There are two schools of thought on subtraction — do you borrow



you borrow or decompose! The latter phrase doesn't describe the current economic climate. It's just that there are two schools of thought on the way subtraction should be taught — the borrowers and the decomposers.

Fortunately, we can ignore binary subtraction since we can manage without it — as does the microprocessor inside your machine.

If you want to do some binary subtraction it is straightforward enough provided that you remember that it is two you're borrowing or taking, not ten. Figure 11 illustrates the process — without any attempt to explain it.

Before we leave the realm of simple sums, look what happens if we shift everything in a binary number over to the left, putting a zero into bit 0, which would be left vacant otherwise.

For example:

**8 4 2 1**

% 1 0 1 which is 5

becomes

**8 4 2 1**

% 1 0 1 0 which is 10

This shifting to the left doubles the number automatically. This isn't too hard to visualise, because the value of each bit is transferred to the next higher bit, which is of course double in value — so the end result is that the whole number is doubled in value.

Similarly, we can do the binary equivalent of 12 divided by 2 by shifting to the right.

For example:

**8 4 2 1**

% 1 1 0 0 which is 12

becomes

**8 4 2 1**

% 1 1 0 which is 6

and, of course, 12 divided by 2 gives you 6.

As each bit is moved to the right, it occupies a column exactly one half lower in value, thus the sum total of all the bits is one half lower. Note the original bit 0 has disappeared altogether. The loss of this bit can

Bit number	7	6	5	4	3	2	1	0
	1	0	0	0	1	1	0	1
Bit value	128	64	32	16	8	4	2	1

Figure 3: The bit pattern for 147

Bit number	7	6	5	4	3	2	1	0
Bit value	$2^7$	$2^6$	$2^5$	$2^4$	$2^3$	$2^2$	$2^1$	$2^0$
	128	64	32	16	8	4	2	1
	1	1	0	0	1	1	0	0

Figure 10: The bit pattern for 304

cause some inaccuracies. After all, if it were 1, when it's halved it should contribute 0.5 to the answer. As it is, it's ignored.

For example, if we try to do 12 divided by 2 in binary by shifting each bit right, the equivalent of 1.5,

**8 4 2 1**  
% 1 1 0 1

becomes

**8 4 2 1**  
% 1 1 0

which is 6 in decimal. Now 12 divided

by 2 gives 6.5, not 6, so what happened to the 0.5?

Well, when we shifted over the original bit 0 (which had the value 1), we shifted it "out of the byte". If you like, it dropped off the end, and doesn't appear in the answer.

Of course, it's this disappearing 1 that should give us the missing 0.5 when it's halved.

This sort of division, where you're only concerned with the wholes in the answer, and ignore any remainders, or decimal parts, is called integer division.

■ Well, that's enough binary for one month. Next month it's hexadecimal

4	2	1		4	2	1	
% $2^2$	$2^1$	$2^0$		% $2^2$	$2^1$	$2^0$	
-%	1	1		-%	1	1	
%	1	1		%	1	1	
Decomposition				Borrowing			

Figure 10: Binary subtraction

# Now or just decompose?

PETE BIBBY strikes a chord with his Atari

# Have fun with these musical experiments ...

LET's start off this month with four notes played at once by entering:

```
SOUND 0,171,10,0 SOUND 1,76,10,0
SOUND 2,61,10,0 SOUND 3,66,10,0
```

While not likely to make Beethoven roll, the above should refresh your memories of the structure of the SOUND command. As you'll remember, it takes the form:

**SOUND channel,pitch,duration, volume**

Hence, the SOUNDS we've just entered in command mode produced a note on each channel with frequency 0, and duration 10. Each note had a different pitch parameter. The result was the chord you heard and are still hearing if you haven't done anything about it.

If you're still plagued by the chord you can bring things to an end with:

**END**

or, more elegantly, with:

```
FOR CHANNEL=0 TO 3:
SOUND CHANNEL,0,0,0:
NEXT CHANNEL
```

which switches off each channel in turn. Table I summarises the SOUND parameters.

Program 1 produces the same chord, but this time the length of time it plays for is limited.

As you can see and hear, lines 20 to 60 produce the familiar sounds. Line 60 does nothing, it's just a delay loop.

While the program is still going, working its way round the loop, the

```
10 REM PROGRAM 1
20 SOUND 0,171,10,0
30 SOUND 1,76,10,0
40 SOUND 2,61,10,0
50 SOUND 3,66,10,0
60 FOR DELAY=1 TO 60:NEXT DELAY
```

Program 1

notes will sound. When the loop finishes, the program comes to an end and so do the notes.

Try changing the values of the loop variables in line 60 or even leaving it out altogether and see what happens.

And, while you're feeling experimental, try altering the volume parameters. So far, I've had the total volume parameter of each note adding up to 32 (0+0+0+0).

If you start playing notes with volume parameters that total over 32, strange things can happen. You have been warned.

Program 11 has us entering the world of music by playing the scale of C. If you don't understand what a scale is, don't worry too much. Just listen to the notes played and I think you'll agree that the sequence has a "complete" feeling to it.

This is because the series of notes follows a common pattern, the pitch rising by a standard unit known as a tone, then by another tone, then a half tone and so on.

Don't be too concerned with the musical terms, just compare the pitch parameters of the notes in Program 11 with the series of the notes in Table II and you'll see the pattern.

Because the first note played is C (pitch parameter 121), the scale is known as the scale of C (or, more

properly, C major). The pitch range it covers (from 121 to 263) is called an octave.

We could start the scale on D or F and, provided we follow the same

NOTE	PITCH PARAMETER	
C	121	OCTAVE 1
D	131	
E	143	
F	155	
G	167	
A	180	
B	193	
C	207	
D	221	
E	235	
F	250	
G	263	
C	276	OCTAVE 2
D	288	
E	302	
F	316	
G	330	
A	345	
B	360	
C	375	
D	390	
E	406	
F	422	
G	438	
C	453	OCTAVE 3
D	469	
E	486	
F	503	
G	520	
A	538	
B	557	
C	576	
D	595	
E	615	
F	635	
G	655	

Table II

channel	pitch	duration	volume
0 to 3	0 to 255	0 to 14 (in 2's)	0 to 255

Table I



one tone.

The whole series played by Program M is known as a chromatic scale.<sup>1</sup>

Again, don't worry too much about the theory—just listen to the program as it works its way from a note with pitch parameter 60 to one with a parameter of 255.

Although it's hardly musical, there's a certain inevitability to it. Compare the pitch values in the DATA statement with the notes in Table II and you'll see the pattern.

Try creating a chromatic scale starting on another note, say one with pitch parameter 100 or 144.

We're not just restricted to scales. Program V uses the same technique of READING from DATA statements to produce an eight-note tune.

You'll see that the structure of the program is more or less the same as Program M.

What's different is the DATA statement, which now holds the pitch parameters of the tune. As before, these are read one by one and used to produce the notes.

Using this method, it's easy to write tunes, playing your own values

have several subroutines, each consisting of delay loops of different lengths.

You could then select the particular loop needed for a note and GOSUB to that routine.

The trouble with this is that you end up with a lot of subroutines and, in long tunes, things get unwieldy. Program M shows another method that can be used to vary the length of notes.

As you can hear, the fifth and sixth notes of the tune are longer than the others. In fact they are twice as long.

This has been achieved by changing the delay loop of line 1010 so that instead of going from 1 to 600 as previously, it goes from 1 to 100 times a variable LENGTH. As the value of LENGTH changes, so will the number of times the loop cycles.

If LENGTH is 2 then the loop will cycle from 1 to 300. If it is 10, then it will go from 1 to 1000.

Obviously as LENGTH varies, so the loop cycles for a longer period. And as the period of the loop changes, so does the length of the note.

Line 60 has been changed so that it reads in both the PITCH and LENGTH of each note. Similarly the data in line 1010 has been altered to supply both the pitch and length of each note.

In this case the fifth and sixth notes have a LENGTH of 10 while the rest have a LENGTH of 5. Hence these notes last twice as long as the others.

This technique of using a variable in the delay loop is extremely flexible. In the above example I've used LENGTH values of 5 and 10. The more-musical may prefer to use

values of 2, 4, 8, 16, to mimic Western note-structures. It's up to you.

One thing about Program M is that it's slow. Program V'll show how to speed things up, using another variable TEMPO.

Again, we've tampered with the delay loop in line 1010. Now it cycles from 1 to TEMPO\*LENGTH.

Before we always had a value of 100. Now this has been replaced with TEMPO which was given the value 50 in line 20. As a result, the delay loop is shorter and the tune is played more quickly.

Notice that the effect of altering TEMPO is the same on every note of the tune. Each one plays for exactly

```
10 REM PROGRAM V
20 DELAY=1000
30 FOR TUNE=1 TO 8
40 READ PITCH
50 SOUND 1,PITCH,10,0
60 SOUND DELAY
70 NEXT TUNE
80 END
900 REM DELAY LOOP
1000 FOR COUNT TO TEMPO*LENGTH:
NEXT COUNT
1010 RETURN
1000 REM PITCH/LENGTH DATA
1010 DATA 121,5,100,5,121,5,100,
5,72,10,71,10,10,5,121,5
```

Program VI

half as long as it did before.

However, relative to each other, the lengths are still in the same proportion. The fifth and sixth notes are still twice as long as the others.

And that's where we'll leave the SOUND command. As I think you'll agree, it's not all that difficult to use if you take it step-by-step.

Now it's up to you. Program VI contains the basis of any tune you may wish to play. All you have to do is discover the notes that make up the tune and how long they last.

It sounds like fun.

*I WOULD like to correct the impression given by the title of last month's article that I thought Apple sound on the Atari was difficult. In fact, the whole point was that it's not all that hard—certainly easier than it looks at first sight.*

*My apologies to all Atari sound devotees who felt I'd done the sound an injustice. — PG*

```
10 REM PROGRAM V
20 DELAY=1000
30 FOR TUNE=1 TO 8
40 READ PITCH
50 SOUND 1,PITCH,10,0
60 SOUND DELAY
70 NEXT TUNE
80 END
900 REM DELAY LOOP
1000 FOR COUNT TO TEMPO*LENGTH:
NEXT COUNT
1010 RETURN
1000 REM PITCH DATA
1010 DATA 121,100,121,100,71,71,
60,121
```

Program V

in the DATA line.

Table II, trial and error, experimentation and inspiration in equal parts should go a long way to making you an Atari musician. However, one thing that you'll notice before long is that no matter how nice your tune is, it's boring.

The reason is that the notes in it are all the same length. There's no variety. This is because we've been using the same subroutine to produce the delay that allows the notes to be heard.

One way round this would be to

```
10 REM PROGRAM VI
20 DELAY=1000
30 FOR TUNE=1 TO 8
40 READ PITCH,LENGTH
50 SOUND 1,PITCH,10,0
60 SOUND DELAY
70 NEXT TUNE
80 END
900 REM DELAY LOOP
1000 FOR COUNT TO TEMPO*LENGTH:
NEXT COUNT
1010 RETURN
1000 REM PITCH/LENGTH DATA
1010 DATA 121,5,100,5,121,5,100,
5,72,10,71,10,10,5,121,5
```

Program VI

For the Atari Computers  
1400 2000 300 3000



Chapman and P.O. 's are:  
P.F. Chapman, 14, Marshall Avenue,  
Littleton, Colorado 80120, U.S.A.

[illegible][illegible]

THE BELMONT ROAD, CHURCH  
CHESHIRE, N.W. 10 0JUN

## NEED MORE?

**PAGE 6**

TWO  
YEARS OLD  
AND  
STILL GOING STRONG

Published  
by monthly.  
Subscription rates:  
\$3.00 U.S.  
\$3.50 Europe  
to PAGE & Magazine  
P.O. BOX 24,  
STAFFORD,  
STIC 1100  
Tel: 0200 44 112

Our Guaranteed Satisfaction MONY. If when you receive your first copy you do not think FPA® is worth having, write and tell us and we will refund your subscription to full price or keep the copy yourself. With a promise like that we must be confident that FPA® is in good. Thousands of our existing subscribers think so, too.

# 1ST ON MEDSIDE FOR AT&T

Figure 1 consists of two bar charts side-by-side. The left chart is titled 'All respondents' and the right chart is titled 'Respondents who have been personally affected by the economic crisis'. Both charts show the percentage of respondents for four levels of agreement with the statement 'The government should do more to help people who are struggling financially'. The categories are 'Strongly agree' (dark grey), 'Somewhat agree' (medium grey), 'Somewhat disagree' (light grey), and 'Strongly disagree' (white). The y-axis represents the percentage from 0 to 100.

Level of Agreement	All respondents (%)	Respondents who have been personally affected by the economic crisis (%)
Strongly agree	~65	~75
Somewhat agree	~25	~20
Somewhat disagree	~8	~5
Strongly disagree	~2	~0

**RESEARCH DESIGN**

100

■ SOFTWARE FROM ALL THE BEST SUPPLIERS, OVER THE COUNTRY

**Figure 1**

- **PLACES, EDUCATION, AND PROFESSIONAL LIFE**

■ **LATE NIGHT OPENING:**  
MON.-SAT. 10PM-2AM

■ SEE IT & TRY IT  
 BEFORE YOU BUY IT

## Microbyte

1998, 1999, 2000, 2001, 2002, 2003, 2004, 2005, 2006, 2007, 2008, 2009, 2010, 2011, 2012, 2013, 2014, 2015, 2016, 2017, 2018, 2019, 2020, 2021, 2022, 2023, 2024, 2025, 2026, 2027, 2028, 2029, 2030, 2031, 2032, 2033, 2034, 2035, 2036, 2037, 2038, 2039, 2040, 2041, 2042, 2043, 2044, 2045, 2046, 2047, 2048, 2049, 2050, 2051, 2052, 2053, 2054, 2055, 2056, 2057, 2058, 2059, 2060, 2061, 2062, 2063, 2064, 2065, 2066, 2067, 2068, 2069, 2070, 2071, 2072, 2073, 2074, 2075, 2076, 2077, 2078, 2079, 2080, 2081, 2082, 2083, 2084, 2085, 2086, 2087, 2088, 2089, 2090, 2091, 2092, 2093, 2094, 2095, 2096, 2097, 2098, 2099, 2100, 2101, 2102, 2103, 2104, 2105, 2106, 2107, 2108, 2109, 2110, 2111, 2112, 2113, 2114, 2115, 2116, 2117, 2118, 2119, 2120, 2121, 2122, 2123, 2124, 2125, 2126, 2127, 2128, 2129, 2130, 2131, 2132, 2133, 2134, 2135, 2136, 2137, 2138, 2139, 2140, 2141, 2142, 2143, 2144, 2145, 2146, 2147, 2148, 2149, 2150, 2151, 2152, 2153, 2154, 2155, 2156, 2157, 2158, 2159, 2160, 2161, 2162, 2163, 2164, 2165, 2166, 2167, 2168, 2169, 2170, 2171, 2172, 2173, 2174, 2175, 2176, 2177, 2178, 2179, 2180, 2181, 2182, 2183, 2184, 2185, 2186, 2187, 2188, 2189, 2190, 2191, 2192, 2193, 2194, 2195, 2196, 2197, 2198, 2199, 2200, 2201, 2202, 2203, 2204, 2205, 2206, 2207, 2208, 2209, 2210, 2211, 2212, 2213, 2214, 2215, 2216, 2217, 2218, 2219, 2220, 2221, 2222, 2223, 2224, 2225, 2226, 2227, 2228, 2229, 2230, 2231, 2232, 2233, 2234, 2235, 2236, 2237, 2238, 2239, 2240, 2241, 2242, 2243, 2244, 2245, 2246, 2247, 2248, 2249, 2250, 2251, 2252, 2253, 2254, 2255, 2256, 2257, 2258, 2259, 2260, 2261, 2262, 2263, 2264, 2265, 2266, 2267, 2268, 2269, 2270, 2271, 2272, 2273, 2274, 2275, 2276, 2277, 2278, 2279, 2280, 2281, 2282, 2283, 2284, 2285, 2286, 2287, 2288, 2289, 2290, 2291, 2292, 2293, 2294, 2295, 2296, 2297, 2298, 2299, 2300, 2301, 2302, 2303, 2304, 2305, 2306, 2307, 2308, 2309, 2310, 2311, 2312, 2313, 2314, 2315, 2316, 2317, 2318, 2319, 2320, 2321, 2322, 2323, 2324, 2325, 2326, 2327, 2328, 2329, 2330, 2331, 2332, 2333, 2334, 2335, 2336, 2337, 2338, 2339, 2340, 2341, 2342, 2343, 2344, 2345, 2346, 2347, 2348, 2349, 2350, 2351, 2352, 2353, 2354, 2355, 2356, 2357, 2358, 2359, 2360, 2361, 2362, 2363, 2364, 2365, 2366, 2367, 2368, 2369, 2370, 2371, 2372, 2373, 2374, 2375, 2376, 2377, 2378, 2379, 2380, 2381, 2382, 2383, 2384, 2385, 2386, 2387, 2388, 2389, 2390, 2391, 2392, 2393, 2394, 2395, 2396, 2397, 2398, 2399, 2400, 2401, 2402, 2403, 2404, 2405, 2406, 2407, 2408, 2409, 2410, 2411, 2412, 2413, 2414, 2415, 2416, 2417, 2418, 2419, 2420, 2421, 2422, 2423, 2424, 2425, 2426, 2427, 2428, 2429, 2430, 2431, 2432, 2433, 2434, 2435, 2436, 2437, 2438, 2439, 2440, 2441, 2442, 2443, 2444, 2445, 2446, 2447, 2448, 2449, 2450, 2451, 2452, 2453, 2454, 2455, 2456, 2457, 2458, 2459, 2460, 2461, 2462, 2463, 2464, 2465, 2466, 2467, 2468, 2469, 2470, 2471, 2472, 2473, 2474, 2475, 2476, 2477, 2478, 2479, 2480, 2481, 2482, 2483, 2484, 2485, 2486, 2487, 2488, 2489, 2490, 2491, 2492, 2493, 2494, 2495, 2496, 2497, 2498, 2499, 2500, 2501, 2502, 2503, 2504, 2505, 2506, 2507, 2508, 2509, 2510, 2511, 2512, 2513, 2514, 2515, 2516, 2517, 2518, 2519, 2520, 2521, 2522, 2523, 2524, 2525, 2526, 2527, 2528, 2529, 2530, 2531, 2532, 2533, 2534, 2535, 2536, 2537, 2538, 2539, 2540, 2541, 2542, 2543, 2544, 2545, 2546, 2547, 2548, 2549, 2550, 2551, 2552, 2553, 2554, 2555, 2556, 2557, 2558, 2559, 2560, 2561, 2562, 2563, 2564, 2565, 2566, 2567, 2568, 2569, 2570, 2571, 2572, 2573, 2574, 2575, 2576, 2577, 2578, 2579, 2580, 2581, 2582, 2583, 2584, 2585, 2586, 2587, 2588, 2589, 2590, 2591, 2592, 2593, 2594, 2595, 2596, 2597, 2598, 2599, 2600, 2601, 2602, 2603, 2604, 2605, 2606, 2607, 2608, 2609, 2610, 2611, 2612, 2613, 2614, 2615, 2616, 2617, 2618, 2619, 2620, 2621, 2622, 2623, 2624, 2625, 2626, 2627, 2628, 2629, 2630, 2631, 2632, 2633, 2634, 2635, 2636, 2637, 2638, 2639, 2640, 2641, 2642, 2643, 2644, 2645, 2646, 2647, 2648, 2649, 2650, 2651, 2652, 2653, 2654, 2655, 2656, 2657, 2658, 2659, 2660, 2661, 2662, 2663, 2664, 2665, 2666, 2667, 2668, 2669, 2670, 2671, 2672, 2673, 2674, 2675, 2676, 2677, 2678, 2679, 26

FL. DEPARTMENT OF REVENUE

# FROG JUMP



## By PAUL DUNNING

IN Frog Jump you use the joystick to control a frog which is trying to get home. The object of the game is to get five frogs safely home, past the road and river.

You must dodge the cars on the road and jump in to passing boats on the river, but do not jump on the yellow boats.

Sometimes you may see your girlfriend on one of the boats. You can get 200 bonus points by picking her

up and taking her home. Choosing brings its own reward.

If you manage to get all your frogs home you'll receive a bonus based on the amount of time you have left. Then you'll advance to a even harder round.

```

10 REM *****
20 REM *      FROG JUMP      *
30 REM *      *****      *
40 REM * BY PAUL DUNNING *
50 REM *****
60 REM FROGS, 1,2,3,4,5,6,7,8,9,10,11,12,13,14,15,16,17,18,19,20,21,22,23,24,25,26,27,28,29,30,31,32,33,34,35,36,37,38,39,40,41,42,43,44,45,46,47,48,49,50,51,52,53,54,55,56,57,58,59,60,61,62,63,64,65,66,67,68,69,70,71,72,73,74,75,76,77,78,79,80,81,82,83,84,85,86,87,88,89,90,91,92,93,94,95,96,97,98,99,100
70 REM *****
80 IF FROG(1)=1 THEN GOTO 1100
90 REM *****
100 REM *****
110 REM *****
120 REM *****
130 REM *****
140 REM *****
150 REM *****
160 REM *****
170 REM *****
180 REM *****
190 REM *****
200 REM *****
210 REM *****
220 REM *****
230 REM *****
240 REM *****
250 REM *****
260 REM *****
270 REM *****
280 REM *****
290 REM *****
300 REM *****
310 REM *****
320 REM *****
330 REM *****
340 REM *****
350 REM *****
360 REM *****
370 REM *****
380 REM *****
390 REM *****
400 REM *****
410 REM *****
420 REM *****
430 REM *****
440 REM *****
450 REM *****
460 REM *****
470 REM *****
480 REM *****
490 REM *****
500 REM *****
510 REM *****
520 REM *****
530 REM *****
540 REM *****
550 REM *****
560 REM *****
570 REM *****
580 REM *****
590 REM *****
600 REM *****
610 REM *****
620 REM *****
630 REM *****
640 REM *****
650 REM *****
660 REM *****
670 REM *****
680 REM *****
690 REM *****
700 REM *****
710 REM *****
720 REM *****
730 REM *****
740 REM *****
750 REM *****
760 REM *****
770 REM *****
780 REM *****
790 REM *****
800 REM *****
810 REM *****
820 REM *****
830 REM *****
840 REM *****
850 REM *****
860 REM *****
870 REM *****
880 REM *****
890 REM *****
900 REM *****
910 REM *****
920 REM *****
930 REM *****
940 REM *****
950 REM *****
960 REM *****
970 REM *****
980 REM *****
990 REM *****
1000 REM *****

```

```


110 POSITION 0,0:GOTO 1100
120 POSITION 0,0:GOTO 1100
130 POSITION 0,0
140 REM *****
150 REM *****
160 REM *****
170 REM *****
180 REM *****
190 REM *****
200 REM *****
210 REM *****
220 REM *****
230 REM *****
240 REM *****
250 REM *****
260 REM *****
270 REM *****
280 REM *****
290 REM *****
300 REM *****
310 REM *****
320 REM *****
330 REM *****
340 REM *****
350 REM *****
360 REM *****
370 REM *****
380 REM *****
390 REM *****
400 REM *****
410 REM *****
420 REM *****
430 REM *****
440 REM *****
450 REM *****
460 REM *****
470 REM *****
480 REM *****
490 REM *****
500 REM *****
510 REM *****
520 REM *****
530 REM *****
540 REM *****
550 REM *****
560 REM *****
570 REM *****
580 REM *****
590 REM *****
600 REM *****
610 REM *****
620 REM *****
630 REM *****
640 REM *****
650 REM *****
660 REM *****
670 REM *****
680 REM *****
690 REM *****
700 REM *****
710 REM *****
720 REM *****
730 REM *****
740 REM *****
750 REM *****
760 REM *****
770 REM *****
780 REM *****
790 REM *****
800 REM *****
810 REM *****
820 REM *****
830 REM *****
840 REM *****
850 REM *****
860 REM *****
870 REM *****
880 REM *****
890 REM *****
900 REM *****
910 REM *****
920 REM *****
930 REM *****
940 REM *****
950 REM *****
960 REM *****
970 REM *****
980 REM *****
990 REM *****
1000 REM *****

```

```

1100 REM *****
1110 REM *****
1120 REM *****
1130 REM *****
1140 REM *****
1150 REM *****
1160 REM *****
1170 REM *****
1180 REM *****
1190 REM *****
1200 REM *****
1210 REM *****
1220 REM *****
1230 REM *****
1240 REM *****
1250 REM *****
1260 REM *****
1270 REM *****
1280 REM *****
1290 REM *****
1300 REM *****
1310 REM *****
1320 REM *****
1330 REM *****
1340 REM *****
1350 REM *****
1360 REM *****
1370 REM *****
1380 REM *****
1390 REM *****
1400 REM *****
1410 REM *****
1420 REM *****
1430 REM *****
1440 REM *****
1450 REM *****
1460 REM *****
1470 REM *****
1480 REM *****
1490 REM *****
1500 REM *****
1510 REM *****
1520 REM *****
1530 REM *****
1540 REM *****
1550 REM *****
1560 REM *****
1570 REM *****
1580 REM *****
1590 REM *****
1600 REM *****
1610 REM *****
1620 REM *****
1630 REM *****
1640 REM *****
1650 REM *****
1660 REM *****
1670 REM *****
1680 REM *****
1690 REM *****
1700 REM *****
1710 REM *****
1720 REM *****
1730 REM *****
1740 REM *****
1750 REM *****
1760 REM *****
1770 REM *****
1780 REM *****
1790 REM *****
1800 REM *****
1810 REM *****
1820 REM *****
1830 REM *****
1840 REM *****
1850 REM *****
1860 REM *****
1870 REM *****
1880 REM *****
1890 REM *****
1900 REM *****
1910 REM *****
1920 REM *****
1930 REM *****
1940 REM *****
1950 REM *****
1960 REM *****
1970 REM *****
1980 REM *****
1990 REM *****
2000 REM *****

```



## SUBROUTINES

- 600 Draws the frog.
- 700 Frog safely home. Adjusts score.
- 800 Sound routine.
- 850 (Split)
- 880 Calculates bonus and sets up next level.
- 1140 Redefines character set.

## Making the Most of your Atari

Paul Bono

Frog Jump is just one of the many simple programs in "Making the Most of Your Atari" by Paul Bono. We're grateful to Intertec Publications for permission to reprint it.

```

FOR OF 011 THEN COLOR DUPLOT 0,0
FOR COLOR DUPLOT 0,1,2,3,4,5,6,7,8,9,10,11,12,13,14,15,16,17,18,19,20,21,22,23,24,25,26,27,28,29,30,31,32,33,34,35,36,37,38,39,40,41,42,43,44,45,46,47,48,49,50,51,52,53,54,55,56,57,58,59,60,61,62,63,64,65,66,67,68,69,70,71,72,73,74,75,76,77,78,79,80,81,82,83,84,85,86,87,88,89,90,91,92,93,94,95,96,97,98,99,100,101,102,103,104,105,106,107,108,109,110,111,112,113,114,115,116,117,118,119,120,121,122,123,124,125,126,127,128,129,130,131,132,133,134,135,136,137,138,139,140,141,142,143,144,145,146,147,148,149,150,151,152,153,154,155,156,157,158,159,160,161,162,163,164,165,166,167,168,169,170,171,172,173,174,175,176,177,178,179,180,181,182,183,184,185,186,187,188,189,190,191,192,193,194,195,196,197,198,199,200,201,202,203,204,205,206,207,208,209,210,211,212,213,214,215,216,217,218,219,220,221,222,223,224,225,226,227,228,229,230,231,232,233,234,235,236,237,238,239,240,241,242,243,244,245,246,247,248,249,250,251,252,253,254,255,256,257,258,259,260,261,262,263,264,265,266,267,268,269,270,271,272,273,274,275,276,277,278,279,280,281,282,283,284,285,286,287,288,289,290,291,292,293,294,295,296,297,298,299,300,301,302,303,304,305,306,307,308,309,310,311,312,313,314,315,316,317,318,319,320,321,322,323,324,325,326,327,328,329,330,331,332,333,334,335,336,337,338,339,340,341,342,343,344,345,346,347,348,349,350,351,352,353,354,355,356,357,358,359,360,361,362,363,364,365,366,367,368,369,370,371,372,373,374,375,376,377,378,379,380,381,382,383,384,385,386,387,388,389,390,391,392,393,394,395,396,397,398,399,400,401,402,403,404,405,406,407,408,409,410,411,412,413,414,415,416,417,418,419,420,421,422,423,424,425,426,427,428,429,430,431,432,433,434,435,436,437,438,439,440,441,442,443,444,445,446,447,448,449,450,451,452,453,454,455,456,457,458,459,460,461,462,463,464,465,466,467,468,469,470,471,472,473,474,475,476,477,478,479,480,481,482,483,484,485,486,487,488,489,490,491,492,493,494,495,496,497,498,499,500,501,502,503,504,505,506,507,508,509,510,511,512,513,514,515,516,517,518,519,520,521,522,523,524,525,526,527,528,529,530,531,532,533,534,535,536,537,538,539,540,541,542,543,544,545,546,547,548,549,550,551,552,553,554,555,556,557,558,559,560,561,562,563,564,565,566,567,568,569,570,571,572,573,574,575,576,577,578,579,580,581,582,583,584,585,586,587,588,589,590,591,592,593,594,595,596,597,598,599,600,601,602,603,604,605,606,607,608,609,610,611,612,613,614,615,616,617,618,619,620,621,622,623,624,625,626,627,628,629,630,631,632,633,634,635,636,637,638,639,640,641,642,643,644,645,646,647,648,649,650,651,652,653,654,655,656,657,658,659,660,661,662,663,664,665,666,667,668,669,670,671,672,673,674,675,676,677,678,679,680,681,682,683,684,685,686,687,688,689,690,691,692,693,694,695,696,697,698,699,700,701,702,703,704,705,706,707,708,709,710,711,712,713,714,715,716,717,718,719,720,721,722,723,724,725,726,727,728,729,730,731,732,733,734,735,736,737,738,739,740,741,742,743,744,745,746,747,748,749,750,751,752,753,754,755,756,757,758,759,760,761,762,763,764,765,766,767,768,769,770,771,772,773,774,775,776,777,778,779,780,781,782,783,784,785,786,787,788,789,790,791,792,793,794,795,796,797,798,799,800,801,802,803,804,805,806,807,808,809,810,811,812,813,814,815,816,817,818,819,820,821,822,823,824,825,826,827,828,829,830,831,832,833,834,835,836,837,838,839,840,841,842,843,844,845,846,847,848,849,850,851,852,853,854,855,856,857,858,859,860,861,862,863,864,865,866,867,868,869,870,871,872,873,874,875,876,877,878,879,880,881,882,883,884,885,886,887,888,889,890,891,892,893,894,895,896,897,898,899,900,901,902,903,904,905,906,907,908,909,910,911,912,913,914,915,916,917,918,919,920,921,922,923,924,925,926,927,928,929,930,931,932,933,934,935,936,937,938,939,940,941,942,943,944,945,946,947,948,949,950,951,952,953,954,955,956,957,958,959,960,961,962,963,964,965,966,967,968,969,970,971,972,973,974,975,976,977,978,979,980,981,982,983,984,985,986,987,988,989,990,991,992,993,994,995,996,997,998,999,1000,1001,1002,1003,1004,1005,1006,1007,1008,1009,1010,1011,1012,1013,1014,1015,1016,1017,1018,1019,1020,1021,1022,1023,1024,1025,1026,1027,1028,1029,1030,1031,1032,1033,1034,1035,1036,1037,1038,1039,1040,1041,1042,1043,1044,1045,1046,1047,1048,1049,1050,1051,1052,1053,1054,1055,1056,1057,1058,1059,1060,1061,1062,1063,1064,1065,1066,1067,1068,1069,1070,1071,1072,1073,1074,1075,1076,1077,1078,1079,1080,1081,1082,1083,1084,1085,1086,1087,1088,1089,1090,1091,1092,1093,1094,1095,1096,1097,1098,1099,1100,1101,1102,1103,1104,1105,1106,1107,1108,1109,1110,1111,1112,1113,1114,1115,1116,1117,1118,1119,1120,1121,1122,1123,1124,1125,1126,1127,1128,1129,1130,1131,1132,1133,1134,1135,1136,1137,1138,1139,1140,1141,1142,1143,1144,1145,1146,1147,1148,1149,1150,1151,1152,1153,1154,1155,1156,1157,1158,1159,1160,1161,1162,1163,1164,1165,1166,1167,1168,1169,1170,1171,1172,1173,1174,1175,1176,1177,1178,1179,1180,1181,1182,1183,1184,1185,1186,1187,1188,1189,1190,1191,1192,1193,1194,1195,1196,1197,1198,1199,1200,1201,1202,1203,1204,1205,1206,1207,1208,1209,1210,1211,1212,1213,1214,1215,1216,1217,1218,1219,1220,1221,1222,1223,1224,1225,1226,1227,1228,1229,1230,1231,1232,1233,1234,1235,1236,1237,1238,1239,1240,1241,1242,1243,1244,1245,1246,1247,1248,1249,1250,1251,1252,1253,1254,1255,1256,1257,1258,1259,1260,1261,1262,1263,1264,1265,1266,1267,1268,1269,1270,1271,1272,1273,1274,1275,1276,1277,1278,1279,1280,1281,1282,1283,1284,1285,1286,1287,1288,1289,1290,1291,1292,1293,1294,1295,1296,1297,1298,1299,1300,1301,1302,1303,1304,1305,1306,1307,1308,1309,1310,1311,1312,1313,1314,1315,1316,1317,1318,1319,1320,1321,1322,1323,1324,1325,1326,1327,1328,1329,1330,1331,1332,1333,1334,1335,1336,1337,1338,1339,1340,1341,1342,1343,1344,1345,1346,1347,1348,1349,1350,1351,1352,1353,1354,1355,1356,1357,1358,1359,1360,1361,1362,1363,1364,1365,1366,1367,1368,1369,1370,1371,1372,1373,1374,1375,1376,1377,1378,1379,1380,1381,1382,1383,1384,1385,1386,1387,1388,1389,1390,1391,1392,1393,1394,1395,1396,1397,1398,1399,1400,1401,1402,1403,1404,1405,1406,1407,1408,1409,1410,1411,1412,1413,1414,1415,1416,1417,1418,1419,1420,1421,1422,1423,1424,1425,1426,1427,1428,1429,1430,1431,1432,1433,1434,1435,1436,1437,1438,1439,1440,1441,1442,1443,1444,1445,1446,1447,1448,1449,1450,1451,1452,1453,1454,1455,1456,1457,1458,1459,1460,1461,1462,1463,1464,1465,1466,1467,1468,1469,1470,1471,1472,1473,1474,1475,1476,1477,1478,1479,1480,1481,1482,1483,1484,1485,1486,1487,1488,1489,1490,1491,1492,1493,1494,1495,1496,1497,1498,1499,1500,1501,1502,1503,1504,1505,1506,1507,1508,1509,1510,1511,1512,1513,1514,1515,1516,1517,1518,1519,1520,1521,1522,1523,1524,1525,1526,1527,1528,1529,1530,1531,1532,1533,1534,1535,1536,1537,1538,1539,1540,1541,1542,1543,1544,1545,1546,1547,1548,1549,1550,1551,1552,1553,1554,1555,1556,1557,1558,1559,1560,1561,1562,1563,1564,1565,1566,1567,1568,1569,1570,1571,1572,1573,1574,1575,1576,1577,1578,1579,1580,1581,1582,1583,1584,1585,1586,1587,1588,1589,1590,1591,1592,1593,1594,1595,1596,1597,1598,1599,1600,1601,1602,1603,1604,1605,1606,1607,1608,1609,1610,1611,1612,1613,1614,1615,1616,1617,1618,1619,1620,1621,1622,1623,1624,1625,1626,1627,1628,1629,1630,1631,1632,1633,1634,1635,1636,1637,1638,1639,1640,1641,1642,1643,1644,1645,1646,1647,1648,1649,1650,1651,1652,1653,1654,1655,1656,1657,1658,1659,1660,1661,1662,1663,1664,1665,1666,1667,1668,1669,1670,1671,1672,1673,1674,1675,1676,1677,1678,1679,1680,1681,1682,1683,1684,1685,1686,1687,1688,1689,1690,1691,1692,1693,1694,1695,1696,1697,1698,1699,1700,1701,1702,1703,1704,1705,1706,1707,1708,1709,1710,1711,1712,1713,1714,1715,1716,1717,1718,1719,1720,1721,1722,1723,1724,1725,1726,1727,1728,1729,1730,1731,1732,1733,1734,1735,1736,1737,1738,1739,1740,1741,1742,1743,1744,1745,1746,1747,1748,1749,1750,1751,1752,1753,1754,1755,1756,1757,1758,1759,1760,1761,1762,1763,1764,1765,1766,1767,1768,1769,1770,1771,1772,1773,1774,1775,1776,1777,1778,1779,1780,1781,1782,1783,1784,1785,1786,1787,1788,1789,1790,1791,1792,1793,1794,1795,1796,1797,1798,1799,1800,1801,1802,1803,1804,1805,1806,1807,1808,1809,1810,1811,1812,1813,1814,1815,1816,1817,1818,1819,1820,1821,1822,1823,1824,1825,1826,1827,1828,1829,1830,1831,1832,1833,1834,1835,1836,1837,1838,1839,1840,1841,1842,1843,1844,1845,1846,1847,1848,1849,1850,1851,1852,1853,1854,1855,1856,1857,1858,1859,1860,1861,1862,1863,1864,1865,1866,1867,1868,1869,1870,1871,1872,1873,1874,1875,1876,1877,1878,1879,1880,1881,1882,1883,1884,1885,1886,1887,1888,1889,1890,1891,1892,1893,1894,1895,1896,1897,1898,1899,1900,1901,1902,1903,1904,1905,1906,1907,1908,1909,1910,1911,1912,1913,1914,1915,1916,1917,1918,1919,1920,1921,1922,1923,1924,1925,1926,1927,1928,1929,1930,1931,1932,1933,1934,1935,1936,1937,1938,1939,1940,1941,1942,1943,1944,1945,1946,1947,1948,1949,1950,1951,1952,1953,1954,1955,1956,1957,1958,1959,1960,1961,1962,1963,1964,1965,1966,1967,1968,1969,1970,1971,1972,1973,1974,1975,1976,1977,1978,1979,1980,1981,1982,1983,1984,1985,1986,1987,1988,1989,1990,1991,1992,1993,1994,1995,1996,1997,1998,1999,2000,2001,2002,2003,2004,2005,2006,2007,2008,2009,2010,2011,2012,2013,2014,2015,2016,2017,2018,2019,2020,2021,2022,2023,2024,2025,2026,2027,2028,2029,2030,2031,2032,2033,2034,2035,2036,2037,2038,2039,2040,2041,2042,2043,2044,2045,2046,2047,2048,2049,2050,2051,2052,2053,2054,2055,2056,2057,2058,2059,2060,2061,2062,2063,2064,2065,2066,2067,2068,2069,2070,2071,2072,2073,2074,2075,2076,2077,2078,2079,2080,2081,2082,2083,2084,2085,2086,2087,2088,2089,2090,2091,2092,2093,2094,2095,2096,2097,2098,2099,2100,2101,2102,2103,2104,2105,2106,2107,2108,2109,2110,2111,2112,2113,2114,2115,2116,2117,2118,2119,2120,2121,2122,2123,2124,2125,2126,2127,2128,2129,2130,2131,2132,2133,2134,2135,2136,2137,2138,2139,2140,2141,2142,2143,2144,2145,2146,2147,2148,2149,2150,2151,2152,2153,2154,2155,2156,2157,2158,2159,2160,2161,2162,2163,2164,2165,2166,2167,2168,2169,2170,2171,2172,2173,2174,2175,2176,2177,2178,2179,2180,2181,2182,2183,2184,2185,2186,2187,2188,2189,2190,2191,2192,2193,2194,2195,2196,2197,2198,2199,2200,2201,2202,2203,2204,2205,2206,2207,2208,2209,2210,2211,2212,2213,2214,2215,2216,2217,2218,2219,2220,2221,2222,2223,2224,2225,2226,2227,2228,2229,2230,2231,2232,2233,2234,2235,2236,2237,2238,2239,2240,2241,2242,2243,2244,2245,2246,2247,2248,2249,2250,2251,2252,2253,2254,2255,2256,2257,2258,2259,2260,2261,2262,2263,2264,2265,2266,2267,2268,2269,2270,2271,2272,2273,2274,2275,2276,2277,2278,2279,2280,2281,2282,2283,2284,2285,2286,2287,2288,2289,2290,2291,2292,2293,2294,2295,2296,2297,2298,2299,2300,2301,2302,2303,2304,2305,2306,2307,2308,2309,2310,2311,2312,2313,2314,2315,2316,2317,2318,2319,2320,2321,2322,2323,2324,2325,2326,2327,2328,2329,2330,2331,2332,2333,2334,2335,2336,2337,2338,2339,2340,2341,2342,2343,2344,2345,2346,2347,2348,2349,2350,2351,2352,2353,2354,2355,2356,2357,2358,2359,2360,2361,2362,2363,2364,2365,2366,2367,2368,2369,2370,2371,2372,2373,2374,2375,2376,2377,2378,2379,2380,2381,2382,2383,2384,2385,2386,2387,2388,2389,2390,2391,2392,2393,2394,2395,2396,2397,2398,2399,2400,2401,2402,2403,2404,2405,2406,2407,2408,2409,2410,2411,2412,2413,2414,2415,2416,2417,2418,2419,2420,2421,2422,2423,2424,2425,2426,2427,2428,2429,2430,2431,2432,2433,2434,2435,2436,2437,2438,2439,2440,2441,2442,2443,2444,2445,2446,2447,2448,2449,2450,2451,2452,2453,2454,2455,2456,2457,2458,2459,2460,2461,2462,2463,2464,2465,2466,2467,2468,2469,2470,2471,2472,2473,2474,2475,2476,2477,2478,2479,2480,2481,2482,2483,2484,2485,2486,2487,2488,2489,2490,2491,2492,2493,2494,2495,2496,2497,2498,2499,2500,2501,2502,2503,2504,2505,2506,2507,2508,2509,2510,2511,2512,2513,2514,2515,2516,2517,2518,2519,2520,2521,2522,2523,2524,2525,2526,2527,2528,2529,2530,2531,2532,2533,2534,2535,2536,2537,2538,2539,2540,2541,2542,2543,2544,2545,2546,2547,2548,2549,2550,2551,2552,2553,2554,2555,2556,2557,2558,2559,2560,2561,2562,2563,2564,2565,2566,2567,2568,2569,2570,2571,2572,2573,2574,2575,2576,2577,2578,2579,2580,2581,2582,2583,2584,2585,2586,2587,2588,2589,2590,2591,2592,2593,2594,2595,2596,2597,2598,2
```





adventure-like theme to them.

The sequence seems to have been that from the development of the first adventures, on large mainframe computers, which by the nature of the machines were text-only, the home-micro adventures which emerged were cutdown versions of the game.

The introduction of graphics to these games stem from two factors.

Firstly, home micros have an ability to produce colour drawings without having to sacrifice huge chunks of memory, which their mainframe ancestors did not.

Secondly, using graphics in a game took away the dry text-only appearance of the adventure, making it more appealing to the arcade-game buyers for whom adventures were classified under "Q" for Qu!t!

Now this adventurer is a confirmed "text" person, so any conclusions drawn from this article should be seen in that light.

Last, as anyone who has played an Infocom game will know, can be far more illuminating than some state-of-the-art graphics.

That is not to say that there are no good graphic adventures.

The recent *Adventure International "Questprobe"* releases, *The Incredible Hulk* and *Sokolman*, have some of the best illustrations seen in adventures, and the addition of graphics to the previous Scott Adams games series shows the demand for these games is obviously there.

However, as Scott himself admits, once a picture has been seen, it can become a little tedious waiting for it every time you wish that location.

The addition of graphics also reduces the amount of memory left available to the programmer for his game.

Like it or not, the amount of actual playability is reduced by the introduction of graphics. More pictures equals less text.

While this may not be a handicap to the smaller game, it is an equation which means a game the size of, say, any of the *Zork Trilogy* will not be given graphics for some time to come.

If I had to think of the best reason for the inclusion of graphics in a game, then it would have to be as a

visual stimulation to the player's own imagination.

This is the main reason why the "Questprobe" series works.

The characters depicted are faithfully reproduced from their comic-book origins, and so the player's imagination is not being forced to accept something which is at odds with his own ideas.

At the same time, it seems clear that the software producers see the inclusion of graphics as a means of improving the appeal, and therefore the sales, of their products.

This by no means signals the end of the text adventure.

Rather I see graphics as a stepping-stone for people who would otherwise probably never play an

adventure to see how enjoyable such a game can be.

And to be totally fair, there is nothing quite as dull as a badly-written text adventure, full of spelling mistakes, inadequate descriptions, or full of hundreds of locations where nothing, or very little happens.

With the recent spate of announcements of new machines with improved memories and better graphics, I can only look forward to reliving a game with the textual excellence of Infocom, combined with the artistic brilliance of *Adventure International*.

Just as long as they leave this poor stick-in-the-mud with the option to turn off the pictures.

**Brügg**

## Now lock up the Filthy Fifteen

**If you like adventures you like solving puzzles, so here's one to test your brain cells around.**

No doubt you've heard of the *Dirty Dozen*. Well in this little concoction you are a prison guard responsible for the *Filthy Fifteen* - the toughest, dirtiest, most unsolvable bunch of prisoners you could ever wish to meet.

In fact they're so unfriendly they can't even stand each other's company for more than one night. This means that no pair of prisoners

can ever be together more than once, and they sleep three to a cell.

It's your job, with only five cells at your disposal, to keep them happy for a week, otherwise you'll have a riot on your hands.

You should have seen the last place they stayed at when they'd finished with it!

Of course the real challenge is not simply to find an answer but to work out the solution. If you manage it, don't write to us...we'll print the solution next month.

DO YOU THE FILTHY FIFTEEN

DO YOU HAVE 100 POINTS

DO YOU CALL TO US

DO YOU?

DO YOU CALL TO US

DO YOU?

DO YOU?

DO YOU?

DO YOU?

DO YOU?

DO YOU?

DO YOU?

DO YOU?

DO YOU?

DO YOU?

DO YOU?

DO YOU?

DO YOU?

DO YOU HAVE 100 POINTS AND A

DO YOU HAVE 100

DO YOU HAVE 100 POINTS AND A LOCKER?

DO YOU?

DO YOU HAVE 100 POINTS AND A LOCKER?

DO YOU?

DO YOU HAVE 100 POINTS AND A LOCKER?

DO YOU?

DO YOU HAVE 100 POINTS AND A LOCKER?

DO YOU?

DO YOU HAVE 100 POINTS AND A LOCKER?

DO YOU?

DO YOU HAVE 100 POINTS AND A LOCKER?

DO YOU?

DO YOU HAVE 100 POINTS AND A LOCKER?

DO YOU?

DO YOU HAVE 100 POINTS AND A LOCKER?

DO YOU?



# ARCHON

THE FORCES OF LIGHT & DARK BATTLE IT OUT IN  
THE ULTIMATE ACTION & STRATEGY PROGRAM FOR YOUR C64 64

**NOW**  
AVAILABLE ON  
SPECTRUM 48K  
AMSTRAD CPC464  
ATARI 800/800XL  
JUGUET 486  
THOMAS 486/586  
486



ARCHON is brilliant. There's something in it for all games addicts: arcade, adventure and strategy are all here. My only complaint is that it's best played against a human opponent — the computer's just too good and you can't give it a handicap.

**Bryan Skinner**  
*Personal Computer News*

**Features** ● Play the computer or a friend ● Computer player gets tougher as you do ● 64 Battle combinations ● Separate Battleground screen ● Medieval pieces like the wizard and the sorceress — magic spells and a board that changes as you play ● Deluxe boxed package includes full instruction and hints manual ● Joystick controlled \*

ONE of the many Basic commands which is taken for granted is RND. Simple in use, it conceals some very clever goings on in the heart of your Atari.

When RND is executed the Basic interpreter generates a random number between 0 and 1. Typical results could be 0.233146332 and 0.851782314.

One area where RND is used a great deal is in shuffling a pack of cards. Without random numbers the same cards would be dealt in the same order. This results in a very boring game — the next card can be predicted.

Any serious card game must have some random element involved in the card shuffling and dealing to make the game realistic.

Other uses include simulating dice, controlling movement in games and so on. All in all, RND is well worth exploring.

The following command will print a random number between 0 and 1:

```
PRINT RND(1)
```

The number within the brackets after the RND has no real effect on the random number returned. Try changing the 1 in the above example to 100. As you will see, it still prints a number between 0 and 1.

For the majority of cases random numbers between 0 and 1 are useless. What we need to do is turn

# RaNDom thoughts

**KEVIN EDWARDS considers RND — the Basic command which can produce some unexpected results**

results of the RND(1) is multiplied by 6. This is done to increase the number so that it is between 0 and 5.999999999 instead of 0 and 1.

Now the INT command takes the integer part of the result. This means that 1.999 would become 1 and 2.23478 would become 2. You see, INT doesn't round the number, but chops off all the digits after the decimal point. In our case the resulting integer will be between 0 and 5 (inclusive).

Now the final part of the command, the +1, is executed. This adds one to the result and produces a number between 1 and 6. It's as easy

as that. And there's as much chance of getting a 1 as a 6 — no loaded dice here!



them into more useful integers (whole numbers). For example, to simulate a six-faced die we would use the following program:

```
10 PRINT INT(RND(1)*6)+1
20 GOTO 10
```

This will print random integers between 1 and 6. Let's take a closer look at line 10. As you can see, the

option usually being taken because it is easier to implement in machine code. Location 53770 (\$D0DA in hex) is a random number generator that produces random values between 0 and 255 (a byte). To prove it try the following program:

```
10 PRINT POKE($D0DA)
20 GOTO 10
```

This is the same as the more long-winded program given below:

```
10 PRINT INT(RND(1)*256)
20 GOTO 10
```

An obvious drawback of PEERing

```
seed=40770
4000 00 04      random LOY 04
4002 00 00 3F  ag2
4004 00 04 3F      DEC seed+2
4006 00 00 3F      DEC seed+1
4008 00 04 3F      LOY 04
400A 00 04 3F      ag2+1
400C 00 00 3F      DEC seed+2
400E 00 00 3F      DEC seed+1
4010 00 00 3F      DEC seed+1
4012 00 00 3F      DEC seed+2
4014 00 00 3F      ag2
4016 00 00 3F      DEC seed+2
4018 00 00 3F      DEC seed+1
401A 00 00 3F      DEC seed+2
401C 00 00 3F      ag2
401E 00 00 3F      DEC seed+2
4020 00 00 3F      DEC seed+1
4022 00 00 3F      DEC seed+2
4024 00 00 3F      DEC seed+1
4026 00 00 3F      DEC seed+2
4028 00 00 3F      DEC seed+1
402A 00 00 3F      DEC seed+2
402C 00 00 3F      DEC seed+1
402E 00 00 3F      DEC seed+2
4030 00 00 3F      DEC seed+1
4032 00 00 3F      DEC seed+2
4034 00 00 3F      DEC seed+1
4036 00 00 3F      DEC seed+2
4038 00 00 3F      DEC seed+1
403A 00 00 3F      DEC seed+2
403C 00 00 3F      DEC seed+1
403E 00 00 3F      DEC seed+2
4040 00 00 3F      DEC seed+1
4042 00 00 3F      DEC seed+2
4044 00 00 3F      DEC seed+1
4046 00 00 3F      DEC seed+2
4048 00 00 3F      DEC seed+1
404A 00 00 3F      DEC seed+2
404C 00 00 3F      DEC seed+1
404E 00 00 3F      DEC seed+2
4050 00 00 3F      DEC seed+1
4052 00 00 3F      DEC seed+2
4054 00 00 3F      DEC seed+1
4056 00 00 3F      DEC seed+2
4058 00 00 3F      DEC seed+1
405A 00 00 3F      DEC seed+2
405C 00 00 3F      DEC seed+1
405E 00 00 3F      DEC seed+2
4060 00 00 3F      DEC seed+1
4062 00 00 3F      DEC seed+2
4064 00 00 3F      DEC seed+1
4066 00 00 3F      DEC seed+2
4068 00 00 3F      DEC seed+1
406A 00 00 3F      DEC seed+2
406C 00 00 3F      DEC seed+1
406E 00 00 3F      DEC seed+2
4070 00 00 3F      DEC seed+1
4072 00 00 3F      DEC seed+2
4074 00 00 3F      DEC seed+1
4076 00 00 3F      DEC seed+2
4078 00 00 3F      DEC seed+1
407A 00 00 3F      DEC seed+2
407C 00 00 3F      DEC seed+1
407E 00 00 3F      DEC seed+2
4080 00 00 3F      DEC seed+1
4082 00 00 3F      DEC seed+2
4084 00 00 3F      DEC seed+1
4086 00 00 3F      DEC seed+2
4088 00 00 3F      DEC seed+1
408A 00 00 3F      DEC seed+2
408C 00 00 3F      DEC seed+1
408E 00 00 3F      DEC seed+2
4090 00 00 3F      DEC seed+1
4092 00 00 3F      DEC seed+2
4094 00 00 3F      DEC seed+1
4096 00 00 3F      DEC seed+2
4098 00 00 3F      DEC seed+1
409A 00 00 3F      DEC seed+2
409C 00 00 3F      DEC seed+1
409E 00 00 3F      DEC seed+2
40A0 00 00 3F      DEC seed+1
40A2 00 00 3F      DEC seed+2
40A4 00 00 3F      DEC seed+1
40A6 00 00 3F      DEC seed+2
40A8 00 00 3F      DEC seed+1
40AA 00 00 3F      DEC seed+2
40AC 00 00 3F      DEC seed+1
40AE 00 00 3F      DEC seed+2
40B0 00 00 3F      DEC seed+1
40B2 00 00 3F      DEC seed+2
40B4 00 00 3F      DEC seed+1
40B6 00 00 3F      DEC seed+2
40B8 00 00 3F      DEC seed+1
40BA 00 00 3F      DEC seed+2
40BC 00 00 3F      DEC seed+1
40BE 00 00 3F      DEC seed+2
40C0 00 00 3F      DEC seed+1
40C2 00 00 3F      DEC seed+2
40C4 00 00 3F      DEC seed+1
40C6 00 00 3F      DEC seed+2
40C8 00 00 3F      DEC seed+1
40CA 00 00 3F      DEC seed+2
40CC 00 00 3F      DEC seed+1
40CE 00 00 3F      DEC seed+2
40D0 00 00 3F      DEC seed+1
40D2 00 00 3F      DEC seed+2
40D4 00 00 3F      DEC seed+1
40D6 00 00 3F      DEC seed+2
40D8 00 00 3F      DEC seed+1
40DA 00 00 3F      DEC seed+2
40DC 00 00 3F      DEC seed+1
40DE 00 00 3F      DEC seed+2
40E0 00 00 3F      DEC seed+1
40E2 00 00 3F      DEC seed+2
40E4 00 00 3F      DEC seed+1
40E6 00 00 3F      DEC seed+2
40E8 00 00 3F      DEC seed+1
40EA 00 00 3F      DEC seed+2
40EC 00 00 3F      DEC seed+1
40EE 00 00 3F      DEC seed+2
40F0 00 00 3F      DEC seed+1
40F2 00 00 3F      DEC seed+2
40F4 00 00 3F      DEC seed+1
40F6 00 00 3F      DEC seed+2
40F8 00 00 3F      DEC seed+1
40FA 00 00 3F      DEC seed+2
40FC 00 00 3F      DEC seed+1
40FE 00 00 3F      DEC seed+2
40FF 00 00 3F      DEC seed+1
```

Listing 1: Random number generator source program.

location \$3770 is that only random bytes can be generated, limiting us to numbers in the range 0 to 255. Problems arise when we want to use this PEEKing method to generate a random number between, say, 1 and 62. Unfortunately there is no simple way of doing this.


Anyway, PEEKing ready-built random number generators is cheating. It's more of a challenge to write your own routine to create such numbers.

The next program we'll look at is a machine code equivalent to PEEKing location \$3770. Take a look at Listing 1. This is the source listing of the random number routine.

Those of you with last month's issue can enter the program using Hexas. The code should be entered at location \$4000 (16384). Remember, all you enter is the hexadecimal bytes at the right of the memory locations. If you are one of the unfortunate people who do not have Hexas type in Program 1.

Hexas users should use the relocate option to test the routine. The execution address is \$4000. When the routine has finished five random bytes will have been stored in memory starting at location \$3F8 (16376). Use the examine option to see them.

If you've typed in Program 1 and RUN it the random numbers will be printed out automatically. Now each



byte printed may look very random, but in fact the numbers are identical each time you RUN the program.

Write down the first five bytes generated by the new routine and compare them with the numbers printed when the program is re-run if you don't believe me.

What we have done is to generate pseudo-random numbers. By this I mean the sequence of numbers printed repeats itself each time the routine is executed, but individual numbers appear to have no relation to one another.

If the numbers printed had been 1,2,4,8,16,32 we would reject them automatically — we could easily predict what the next number is, 64, and could therefore say the numbers are not random.

Creating a routine to generate pseudo-random numbers is very awkward. What we have to do is perform several operations on a series of numbers to produce another set of numbers (random) so that both sets bear no obvious relation to each other.

There is, of course, a relationship between the two sets, but it is so complex that it cannot be readily calculated from a list of numbers generated by the routine.

To produce different sequences of random numbers you can seed the random number generator with different values before calling the routine.

Seeding means setting up the initial values of the set of numbers used by the routine. Changing these initial numbers causes the sequence of numbers generated to be different.

In Program 1 line 40 seeds all the bytes with the value 20.

If you're using Hexas you can change the seeds by altering the contents of locations \$3FF8 to \$3FFC.

If you change the seed number in line 40 from 20 to 30 and RUN the program, the number sequence will be different. In fact, if you delete the line which seeds the random number generator you'll get different random bytes each time you RUN the program, since your "new" seeds are what's left over from the last time it was called.

The Atari computers are very intelligent because they always generate true random numbers. If you use a friend's micro, such as a BBC, and you turn it off then on and enter the command:

PRINT RND(1)

you'll always get the same number. This is because it always seeds the random number generator with the same values.

I hope this has thrown some light on random numbers for you. I'm sure you'll agree that working through random numbers routines can be a lot of fun. It's always interesting to see how each routine differs.

Why not try writing one yourself? Be careful though, you often find your generator has a bias in it. For example, some routines seem to pick a lot of 0s and 155s.

Has anyone out there come up with a program to test how random a particular generator is? If so — or if you've got any "random contribution" to make — we'd love to hear from you.

```

10 REM RANDOM NUMBER
20 REM BY NICK COOPER
30 REM 155 4000 0000 0000
40 FOR L=0:15:50:16384:16385:16386:16387:16388:16389:16390
50 NEXT L
60 FOR L=0:15:50:16384:16385:16386:16387:16388:16389:16390
70 NEXT L
80 REM 16384:16385:16386:16387:16388:16389:16390:16391:16392:16393:16394:16395:16396:16397:16398:16399
90 FOR L=0:15:50:16384:16385:16386:16387:16388:16389:16390:16391:16392:16393:16394:16395:16396:16397:16398:16399
100 NEXT L
110 REM
120 REM
130 REM
140 REM 16384:16385:16386:16387:16388:16389:16390:16391:16392:16393:16394:16395:16396:16397:16398:16399
150 NEXT L
160 REM
170 REM
180 REM
190 REM 16384:16385:16386:16387:16388:16389:16390:16391:16392:16393:16394:16395:16396:16397:16398:16399
200 NEXT L
210 REM
220 REM
230 REM
240 REM 16384:16385:16386:16387:16388:16389:16390:16391:16392:16393:16394:16395:16396:16397:16398:16399
250 NEXT L
260 REM
270 REM
280 REM
290 REM 16384:16385:16386:16387:16388:16389:16390:16391:16392:16393:16394:16395:16396:16397:16398:16399
300 NEXT L
310 REM
320 REM
330 REM
340 REM 16384:16385:16386:16387:16388:16389:16390:16391:16392:16393:16394:16395:16396:16397:16398:16399
350 NEXT L
360 REM
370 REM
380 REM
390 REM 16384:16385:16386:16387:16388:16389:16390:16391:16392:16393:16394:16395:16396:16397:16398:16399
400 NEXT L
410 REM
420 REM
430 REM
440 REM 16384:16385:16386:16387:16388:16389:16390:16391:16392:16393:16394:16395:16396:16397:16398:16399
450 NEXT L
460 REM
470 REM
480 REM
490 REM 16384:16385:16386:16387:16388:16389:16390:16391:16392:16393:16394:16395:16396:16397:16398:16399
500 NEXT L
510 REM
520 REM
530 REM
540 REM 16384:16385:16386:16387:16388:16389:16390:16391:16392:16393:16394:16395:16396:16397:16398:16399
550 NEXT L
560 REM
570 REM
580 REM
590 REM 16384:16385:16386:16387:16388:16389:16390:16391:16392:16393:16394:16395:16396:16397:16398:16399
600 NEXT L
610 REM
620 REM
630 REM
640 REM 16384:16385:16386:16387:16388:16389:16390:16391:16392:16393:16394:16395:16396:16397:16398:16399
650 NEXT L
660 REM
670 REM
680 REM
690 REM 16384:16385:16386:16387:16388:16389:16390:16391:16392:16393:16394:16395:16396:16397:16398:16399
700 NEXT L
710 REM
720 REM
730 REM
740 REM 16384:16385:16386:16387:16388:16389:16390:16391:16392:16393:16394:16395:16396:16397:16398:16399
750 NEXT L
760 REM
770 REM
780 REM
790 REM 16384:16385:16386:16387:16388:16389:16390:16391:16392:16393:16394:16395:16396:16397:16398:16399
800 NEXT L
810 REM
820 REM
830 REM
840 REM 16384:16385:16386:16387:16388:16389:16390:16391:16392:16393:16394:16395:16396:16397:16398:16399
850 NEXT L
860 REM
870 REM
880 REM
890 REM 16384:16385:16386:16387:16388:16389:16390:16391:16392:16393:16394:16395:16396:16397:16398:16399
900 NEXT L
910 REM
920 REM
930 REM
940 REM 16384:16385:16386:16387:16388:16389:16390:16391:16392:16393:16394:16395:16396:16397:16398:16399
950 NEXT L
960 REM
970 REM
980 REM
990 REM 16384:16385:16386:16387:16388:16389:16390:16391:16392:16393:16394:16395:16396:16397:16398:16399
1000 NEXT L

```

Program 1

## Second in DAVE RUSSELL's series on the Atari's graphics modes

LAST month we looked at Graphics Mode 0, the text mode that appears when you switch on your micros. This month we'll take a look at two other text modes, Graphics 1 and Graphics 2.

As you might expect, there are some differences between Modes 1 and 2, but they're similar enough for us to consider them together.

You may recall that the Mode 0 screen was like a piece of graph paper with 40 columns and 24 rows.

If you imagine the columns slunk together in pairs, you've got something similar to Mode 1.

To be more accurate, the Mode 1 screen has two pairs. The top part is like pairs of Mode 0 columns slunk together, while the bottom part is exactly the same as Mode 0 columns.

That is, Mode 1 has a 20 rows by 20 columns section, immediately underneath which are four rows of 40 columns.

The conceptual move to Mode 2 simply requires you to imagine the Mode 1 "40" rows slunk together in pairs. This gives a 10 rows by 20 columns section, again with four rows of 40 columns beneath.

You can see the way these sections are separated quite clearly by typing GRAPHICS 1 and pressing Return.

Assuming you were in Mode 0 before you did this, your screen has suddenly been transformed into a large black area with a small strip of Mode 0 lines at the bottom.

This strip is four lines deep, and you should see the word **READY** on the second line and the cursor immediately beneath it on the third line.

If you press Return a few times, the word **READY** will move up the screen. On the third press, it will disappear.

If you had a program in memory and typed LIST now, the listing would be displayed on these four lines only.

It's not very useful being able to read only four lines of a program at a time, which is why program writing and debugging tends to get done in Mode 0.

The four lines are what is sometimes called a "text window" and anything you **PRINT** will appear here.

Try the simple exercise in Program

# TAKE A LOOK AT MODES 1 and 2



1. When you Run it, the cursor will end up on the bottom line.

#### ON GRAPHICS 1


#### ON PRINT "MODE 1 TEXT WINDOW"

Program 1

This means that if you'd had another line of print, the first would scroll out of the window. Add a line 40 to Program 1 as follows:

#### ON PRINT "THIS IS AN EXTRA LINE"

When you Run the program now, the first line of print scrolls off, leaving



only the output from line 40 visible.

At this point, you might be tempted to ask what use the text window is if it can only display the last line to be printed.

We can make better use of it by causing the program to wait after it has written something to the text window.

In this way, the text already there won't scroll off until we want it to do so.

For example, type in and Run Program 2. You should now have three lines of text in the window and

```

10 DIM A$(10)
20 GRAPHICS 1
30 PRINT "MODE 1 TEXT WINDOW"
40 PRINT "MODE 15 AN EXTRA LINE"
50 PRINT "PRESS RETURN"
60 INPUT A$

```

Program 11

the cursor should be on the fourth line, just after a question mark.

The reason the text stays there is because the program is waiting for something before it continues.

Line 60 tells the machine to expect an input from the keyboard, and it will wait until it gets the signal that an input has been made—the signal that is sent when Return is pressed.

If you now press Return, all the text scrolls out of the window to make way for the Ready message and the cursor.

I wouldn't want to claim Program 11 as a major contribution to programming, but it should illustrate one possible use of the text window.

You can print simple messages and take inputs while all the main action is happening on the rest of the screen.

Oh yes, I'd forgotten about the top 20 rows of the screen which are what Mode 1 is all about! Getting something on there is almost as easy as getting it into the text window.

Program 111 shows how you can write some text to the main part of the screen.

Instead of a single PRINT, you must use PRINT#0. That's 0 (read as hash-zero) means 'print to channel 0'.

If you Run this program you'll see our name in lights. Note the orange colour of the letters.

```

10 GRAPHICS 1
20 POSITION 5,5
30 PRINT #0;"NAME HERE"

```

Program 111

Now, type in line 30 again, only this time put our name in lower case as follows:

```
30 PRINT #0;"name here"
```

When you Run this version, the name still appears in upper case (capital) letters, but the colour has

changed to green.

Try typing our name in inverse upper case or inverse lower case and see what colours are produced.

This illustrates two aspects of Mode 1. Firstly, it's a five-colour mode, and secondly only half of the character set is available.

We'll take a closer look at the character set next month, but for now let's look at controlling the colours.

Our use of PRINT#0 followed by upper case letters meant that register 0 was selected and this register defaults to orange.

By using lower case letters, register 1 was selected and this defaults to green.

If you typed the message in upper case letters, this selects register 2

**Mode 1: A five colour mode with just half the character set available**

and so it should have appeared in blue.

Finally, using lower case inverse selects register 3 and as the message should have appeared in red.

You'll notice that no matter how you type it in, our name still gets printed in upper case letters. That's what I mean by saying that only half of the character set is available.

We can access the other half and get lower case letters, but we'll leave that for next month.

Register 4 controls the background colour and this defaults to black. You can change this using the SETCOLOR command as we did in Mode 0.

If you are in Mode 1, enter SETCOLOR 4, 2, 6 and press Return to see the effect of changing the background colour.

The 4 selects register 4, the 2 selects colour 2 (orange) and the 6 sets the luminance.

The SETCOLOR command is the key to changing the other registers from their default values. You can see the effect of this by entering Listing IV and running it.

Because the message in line 60 is

```

10 GRAPHICS 1
20 FOR A=0 TO 5
30 FOR B=0 TO 5
40 POSITION 5,5
50 SETCOLOR A,B,6
60 PRINT #0;"NAME HERE"
70 FOR DELAY=10 TO 10000000
80 NEXT B
90 NEXT A

```

Program IV

in upper case, we can change its colour by altering register 0.

Line 50 performs the alteration and the loop set up by line 30 cycles through all the available colours.

The luminance is kept at a constant value of 6, and line 70 simply keeps each colour on the screen long enough for it to be seen.

There is another way to get a character on the Mode 1 screen, by using the COLOR and PLOT commands.

For example, with a clear Mode 1 screen (which you can get by pressing Reset and typing GR 1), type COLOR 65:PLOT 5,5 and press Return.

The slightly confusing aspect of this method is that the COLOR command doesn't select a colour in Mode 1.

Instead, it selects the character to be PLOTTed, in this case character 65 or A as we know it.

Hence, if you entered the line as suggested, you should have an orange A at screen position 5,5.

You can still use SETCOLOR to change the colour of the character that you plot. If you change line 60 in Program IV to read:

```
60 COLOR 65:PLOT 5,5
```

and delete line 40 (because it isn't needed), you can see the A cycle through the same colours as our name did.

If you want to put a large piece of text on the Mode 1 screen, it's obviously easier to use PRINT#0 than lots of COLOR/PLOT combinations.

However, there are times when you might need to use COLOR, so Program V shows how to produce a familiar result with line 30 READING

```

10 GRAPHICS 1
20 FOR A=1 TO 10
30 READ B
40 COLOR B
50 PLOT A*10,B
60 NEXT A
70 DATA 45,44,46,42,71,37,48,47,
  45,42

```

Program V

the character DATA from line 70.

Selecting a colour register is not quite as straightforward with **COLOR/LOT** as it is with **PRINT+B**. It's over it in detail next month because the difficulties are connected with the missing half of the character set.

However, to see the sort of thing you can do, change line 40 of Program V to read:

```
40 COLOR A*10
```

The message should now appear in green.

Instead of adding 32 to all the numbers in the DATA statement, you

can use the method selectively to produce a mixed colour display.

For example, retype line 40 as it originally appeared in Program V and alter line 70 to read:

```
70 DATA 37,44,37,42,48,4,45,42,
  45,44
```

If you compare the two versions of line 70, you'll notice that I've added 32 to some of the values, causing those characters to be printed in green while the remainder are still printed in orange.

So far, I've not discussed Mode 2 at all. That's because everything I've said about Mode 1 applies to Mode 2.

If you change the **GRAPHICS 1** in all the programs to read **GRAPHICS 2**, you'll get very nearly the same results.

The only differences will be the size of the text and its position on the screen.

As I said earlier, Mode 2 rows are like two Mode 1 rows stuck together, so Mode 2 characters are twice as

Mode 2 characters are twice as high as those of Mode 1

high as those of Mode 1.

This in turn means that the command **POSITION 5,5** will refer to a different point on the TV screen depending on whether Mode 1 or Mode 2 is in use.

Mode 1 and 2 also differ in terms of the amount of memory they require - Mode 2 needs less than Mode 1 - but that needn't bother us here.

The programs we'll use won't be long enough to worry about memory considerations!

Next month we'll look at how to access the missing half of the character set and how to select a colour register with **COLOR/LOT**.

## Computer Support PRESENTS

### A whole new range of affordable software and hardware products for every Atari user

<b>80 COLUMN PACK</b> At last! 80 columns built in to your Atari, available on personal, work, main compatible software.	<b>£29.95</b>
<b>ATTENTION!</b> A built in machine code monitor capable of stepping any program on the fly, examining registers/memory, read from disk, write to disk, return to program and many other commands available. A must for all assembly language programmers.	<b>£49.95</b>
<b>THE GAP</b> Fill the 4k gap in your 480K/512K with this hardware modification, once fitted to a 486 machine there will be 512k of user RAM.	<b>£39.95</b>
<b>ROM EMULATOR</b> Monitor and record cartridge software quickly and effectively. Use both a watch and cartridge RAM because ROMs can also be used to corporation with CARTRIDGE DUPLICATION to backup these extremely protected cartridges then produce a custom copy.	<b>£39.95</b>
<b>OVER DRIVE</b> Use the other side of all your diskettes, simple to operate just flip a switch.	<b>£14.95</b>
<b>BACKUP/FORMAT</b> A hardware modification, write head encoders to any diskette, can be used for optional addition of 540 sectors or to backup some protected files.	<b>£19.95</b>
<b>POSTSCRIPT</b> Run a standard Postscript compatible printer using the postscript ports of any Atari computer. Includes a replacement header, runs with any font cartridge, works compatible with Postscript font.	<b>£39.95</b>
<b>DISK DATA RECOVERER</b> Recover any disk, cartridge or cartridge, view system files, examine input (or pre-decoding data bytes), the wild result file can be reconstructed then re-assembled using an assembler.	<b>£24.95</b>
<b>FILE LOADER</b> An emulator for 1024 memory which does not require DOS on the disk, ideal for games.	<b>£14.95</b>
<b>BOOT LOADER</b> A self booting menu, completely boot data/operating to a file format, additional includes tape to disk, disk to tape, disk to disk, format, write rom memory.	<b>£14.95</b>

We are continually adding new products to our range please send 'CAT' for full details.

© 1988 All rights reserved. Computer Support is a trademark of C.S.P. Ltd.  
C.S.P. Ltd. is a trademark of C.S.P. Ltd.

<b>Other items available:</b>	<b>Cost</b>	<b>Stock</b>
320000-500000	£9.95	£9.95
400000-500000	£9.95	£9.95
500000-500000	£9.95	£9.95
600000-500000	£9.95	£9.95
700000-500000	£9.95	£9.95
800000-500000	£9.95	£9.95
900000-500000	£9.95	£9.95
1000000-500000	£9.95	£9.95
1100000-500000	£9.95	£9.95
1200000-500000	£9.95	£9.95
1300000-500000	£9.95	£9.95
1400000-500000	£9.95	£9.95
1500000-500000	£9.95	£9.95
1600000-500000	£9.95	£9.95
1700000-500000	£9.95	£9.95
1800000-500000	£9.95	£9.95
1900000-500000	£9.95	£9.95
2000000-500000	£9.95	£9.95
2100000-500000	£9.95	£9.95
2200000-500000	£9.95	£9.95
2300000-500000	£9.95	£9.95
2400000-500000	£9.95	£9.95
2500000-500000	£9.95	£9.95
2600000-500000	£9.95	£9.95
2700000-500000	£9.95	£9.95
2800000-500000	£9.95	£9.95
2900000-500000	£9.95	£9.95
3000000-500000	£9.95	£9.95
3100000-500000	£9.95	£9.95
3200000-500000	£9.95	£9.95
3300000-500000	£9.95	£9.95
3400000-500000	£9.95	£9.95
3500000-500000	£9.95	£9.95
3600000-500000	£9.95	£9.95
3700000-500000	£9.95	£9.95
3800000-500000	£9.95	£9.95
3900000-500000	£9.95	£9.95
4000000-500000	£9.95	£9.95
4100000-500000	£9.95	£9.95
4200000-500000	£9.95	£9.95
4300000-500000	£9.95	£9.95
4400000-500000	£9.95	£9.95
4500000-500000	£9.95	£9.95
4600000-500000	£9.95	£9.95
4700000-500000	£9.95	£9.95
4800000-500000	£9.95	£9.95
4900000-500000	£9.95	£9.95
5000000-500000	£9.95	£9.95
5100000-500000	£9.95	£9.95
5200000-500000	£9.95	£9.95
5300000-500000	£9.95	£9.95
5400000-500000	£9.95	£9.95
5500000-500000	£9.95	£9.95
5600000-500000	£9.95	£9.95
5700000-500000	£9.95	£9.95
5800000-500000	£9.95	£9.95
5900000-500000	£9.95	£9.95
6000000-500000	£9.95	£9.95
6100000-500000	£9.95	£9.95
6200000-500000	£9.95	£9.95
6300000-500000	£9.95	£9.95
6400000-500000	£9.95	£9.95
6500000-500000	£9.95	£9.95
6600000-500000	£9.95	£9.95
6700000-500000	£9.95	£9.95
6800000-500000	£9.95	£9.95
6900000-500000	£9.95	£9.95
7000000-500000	£9.95	£9.95
7100000-500000	£9.95	£9.95
7200000-500000	£9.95	£9.95
7300000-500000	£9.95	£9.95
7400000-500000	£9.95	£9.95
7500000-500000	£9.95	£9.95
7600000-500000	£9.95	£9.95
7700000-500000	£9.95	£9.95
7800000-500000	£9.95	£9.95
7900000-500000	£9.95	£9.95
8000000-500000	£9.95	£9.95
8100000-500000	£9.95	£9.95
8200000-500000	£9.95	£9.95
8300000-500000	£9.95	£9.95
8400000-500000	£9.95	£9.95
8500000-500000	£9.95	£9.95
8600000-500000	£9.95	£9.95
8700000-500000	£9.95	£9.95
8800000-500000	£9.95	£9.95
8900000-500000	£9.95	£9.95
9000000-500000	£9.95	£9.95
9100000-500000	£9.95	£9.95
9200000-500000	£9.95	£9.95
9300000-500000	£9.95	£9.95
9400000-500000	£9.95	£9.95
9500000-500000	£9.95	£9.95
9600000-500000	£9.95	£9.95
9700000-500000	£9.95	£9.95
9800000-500000	£9.95	£9.95
9900000-500000	£9.95	£9.95
10000000-500000	£9.95	£9.95

Coming soon:  
**NEW DATA SELECT**  
For more data on new memory for the 80080.  
**NEW DATA SELECT**  
Select from any one of up to eight options from a menu or pointing, includes board and ROM.  
**CARTRIDGE SELECTION**  
Select from any one of up to four ready plugged in cartridges.  
**NEW DATA SELECT**  
Simple the best menu assembler yet.  
**NEW DATA SELECT**  
Loaders from 1024-bit drive to true double density (1024) with automatic format to single or double density.  
**NEW DATA SELECT**  
A very interesting sports programmer.  
Send cheque or postal order to:

## Computer Support

20 Seacourt Road, Alders Wood, London SE12 8JW  
Tel: 01-311 7338

After 1000 for Post & Packing  
Please allow up to 28 days for delivery



*I HAVE just purchased issue 1 of Atari User after weeks of hawking at its impending launch. Congratulations! You have immense potential - I hope your aim is to become the British version of the brilliant Analog.*

*I am not going to give a lot of suggestions for you to consider. I just want to say you fail to go in-depth on the games aspect of the Atari, since very few magazine listings can approach commercial programs for quality and durability (and personally, even these don't keep my interest for very long).*

*Actually, the Atari utility was a superb start to what looks like becoming an institution in the magazine world.*

*Hopefully - in the near future after I have managed to get one or two rather important items out of the way - I will submit some of my own programs and hardware reviews for publication.*

*That point brings me to my only suggestion. Please keep your eyes open for DTP peripherals: MS202, printer, cassette interfaces, and other assorted devices that cost an arm and a leg to buy ready built were when the manufacturers claim great value.*

*I don't want to put any one person down, but commercial models cost well over £100. For example, whereas Maplin Electronics Supplies supply desktop kits for around £60-£70 and a nice little interface can be built for less than £30. That is what you call value!*

*Finally, my copy of Atari*

## Just a little DIY can save you quite a lot!

*Use came from a company called Software Express in Birmingham who advertise in your pages. Can I use your paper to thank them for a really express service, and incredibly helpful and polite staff to whom nothing seems too much trouble.* — **Martin Sisson, Nottingham.**

■ We hope to bring you a range of hardware projects - everything from left-handed joysticks to complete piano-style keyboards.

Even so, some people just don't feel confident about using a soldering iron, which is why there is a market for ready-built modules.

### A turn of the screw...

*I AM the proud owner of an 80080. On April 23 I ordered the new 1380C from the fabulous Silice Shop, it arrived 72 hours later on the Friday.*

*Now this is not just a letter of congratulations to Silice Shop, my point is that already having an 80 I know what the 80 is going to be like. So as soon as I turned on my new 80, I knew that something was wrong.*

*Basically the colours were*

*extremely dull. Even with the TV colour knob turned on full, the screen bright colours were still dull. I ring Silice Shop to find out what was wrong with my new 80. They told me "Well your 80 is all right mate, if you want it to be we will either fix it or send a new one".*

*Well I was extremely disappointed at the prospect of having to send the 80 back after all the attention that I had created at work about this brilliant machine.*

*But luckily at the last minute I discovered a small hole on the base of the computer giving access to a screw adjustment, that enabled me to change the colour output of the computer.*

*If only Silice Shop had told me that in the beginning. Please tell all your readers about this so that they do not have the same disappointment that I had.* — **A.J.C. Bishop, Chesham, Herts.**

■ Well spotted! You must have some very small screwdrivers. In general, though, it's best not to go poking about lest you do some damage and simultaneously invalidate your warranty.

### How a group can help

*CONGRATULATIONS on a first class magazine. The first issue was very informative and useful. I can't wait for the next.*

*I am really willing to express my feelings towards Atari devoted user groups. I am very proud to be a listed member of the Lee Valley Atari Users Group (LVUAG), and have been since it started three years ago.*

*I was at first an Atari 400 user, but was fired with the keyboard and so upgraded to an Atari 800.*

*I soon became bored with playing games, and began to*

*use my computer as it should be used - to program with.*

*I started learning Basic with great help from the group, and am now programming quite well (not as good as the officials of the group, but good within my potential).*

*It is even I for the help and advice given at the bi-monthly meetings of the LVUAG I would still be a 400 owner playing 18k games. Instead I am using a 48k 800 and making my own games.*

*This week I bought a Gemini printer with the help of Matthew, the group's vice president and main contributor. He helped me select a printer for my specific needs and within my price range. And so far I haven't had a problem.*

*I feel that many people around the country just haven't bothered to meet at a local group. They feel it will be boring, too difficult and self-serving, or just too demanding. Indeed, I have found it none of these.*

*The LVUAG I feel has done me a good job in educating me in the computing world, giving me advice, hints, tips, ideas, and most of all knowledge of what to do.*

*It is one of my main social events of my week, and I look forward to it. If the officials are too tired or with problems at the meeting, they are always pleased to see me at their own homes, or even at the pub afterwards.* — **Mr. Saunders, Brookmans, Herts.**

### Can I use these games?

*I'VE got an Atari 800 and I keep seeing people wanting to sell the VCS game cartridges, paddles and joysticks.*

*If I buy them will I be able to*

# ATARI USER

## Mailbag

WE welcome letters from readers - about your experiences using the Atari micros, about tips you would like to pass on to other users... and about what you would like to see in future issues.

The address to write to is:

**Mailbag Editor**

**Atari User**

**Europe House**

**66 Chester Road**

**Hazel Grove**

**Stockport, M20 5NT**

use them on my 800? — **Brian Perguesano, Wilmet, Maryland.**

■ The good news is that the paddles and joysticks are compatible with all Atari computers, so you can buy some of those.

The not-so-good news is that the 1000 game cartridges are different from the cartridges that your 800 accepts, so it's no good your buying any of those.

## Crashing the buffers

I agree with you that *Alphabet Train* (Atari User, May, page 127) is a delightful little program... when it works!

I spent a lot of time in the typing as printed and it works fine as long as you don't try to go further than the end of the alphabet. If you try to move the train to before A or after Z, the program crashes rather spectacularly.

Is this a deliberate feature, or was there an error in the listing? I hope it's not deliberate because it spoils an otherwise great game, but my teenage children in Illinois can't spell anything advantageously wrong. — **B.M. Millington, Urbana, Michigan.**

■ One man's feature is another man's bug, which is what there was in this *Alphabet Train* listing. It was in when we added the keyboard option and results from the order of precedence of the logical operators in Basic.

All that is required to fix the bug is to add some parentheses to lines 800 and 810 as follows:

```
800 G=STR$(CHR$(ASC(CHR$(
41: IF (G< "A" OR G>"Z") AND I
34 THEN G=CHR$(ASC(CHR$(
62: MID$(G,2,1)
310 IF (G<"A" OR G>"Z") AND
1110 THEN G=CHR$(ASC(CHR$(
8000: MID$(G,2,1)
```

With the parentheses added the program works fine and doesn't allow the user to go beyond the end of the train.

## High in the Drop Zone

CONGRATULATIONS on a great new magazine. Your articles are all very good, up to date and interesting. Also special offers are a new and very good idea. For the help now we *Atarians* have had it too rough, with software being so expensive.

What I would like to see in your magazine are high score tables and tips on adventures. My high score on *Drop Zone* is 87,810 and I really need some help on Levels of Time.

Also here is another good idea you may wish to consider which no other magazine offers — a price of a piece of software for every letter and program published.

Please keep your magazine the same and as fun as it is. I'd like an excellent magazine in return for my ideas. — **D. Grotzke, Leicester.**

■ We suspect you must have those hands if you scored 87,810 on *Drop Zone*!

The only way we could get a score like that was with one of us operating the joystick and another pressing the appropriate keys.

The problem with high score tables is that they take up a lot of space, particularly when there are a lot of games around. Also, there's no way of telling that the scores were genuinely obtained — although we're sure that no Atari user would exaggerate!

Hints and tips on adventures will form part of Billig's Advertising section, so do send them in. Please try to ask a specific question and we'll try to print the answers in a way that doesn't spoil the game for other people.

There's a good reason why no magazine gives a piece of software for every letter. Some have tried similar things and quickly dropped the idea because the costs got too high. We'd rather keep the cover price competitive.

However we do pay for articles and programs published. You won't get rich writing for *Atari User* (well, we

## Check-sum routine needed

I AM pleased to say that I have purchased my first copy of *Atari User*, Vol. 1, No. 1 and I am even more pleased to tell you that I will be one more of your many readers, for many issues to come.

If it continues, as I am sure it will, to keep its issue No. 1 standards, it will be, I feel sure, the number one magazine for Atari.

To be honest with you I have gone over it several times to see if I can make any comments. I can find none. Excellent, please keep it up.

There is however one thing I would like to see, that is some kind of code listing type, similar to what we are used to in magazines like *ASIC*. This is a great help to the many, many new Atari users. Is this possible for you to do? — **Les**

**Eastock, Lee Village, Birmingham.**

■ All this praise has the editorial team positively blushing! No more, please, or it will go to their heads.

We're still pondering on the question of a check-sum routine. Like most things in life, there are advantages and disadvantages.

For example, it could be argued that they confuse the people who need them most and that it's good to get some practice at debugging.

On the other hand, a good check-sum routine can save some time since you've entered the routine itself. We'd welcome reader's opinions on this while we're pondering.

haven't, so why should you? but at least you'll have the satisfaction of knowing that you're helping fellow users.

## A way? There are two!

I'VE finally managed to get enough money together to buy a 1000 disc drive. My friends mostly have either drives — they saved up faster than me — and so run DOS 3.

I know there's an option on my DOS 3 that will let me take files off their discs onto one of mine, but we can't work out how to do the opposite.

If I write a program and save it on a disc, how can I give it to my friends?

There must be a way, for we can't work it out. Can you? — **Wayne Ealey, Burgess Hill, Sussex.**

■ There are two ways to transfer files from DOS 3 to DOS 2. The easiest is to load the program from your disc, save it to cassette, switch the cassettes off and then reload from one of your friends' DOS 2

discs.

With DOS 2 loaded, you can load the file from cassette and then save it to disc.

The other way is to find a utility program which enables the transfer without going via cassette. Such programs have appeared in print and indeed we hope to print our own version in a few months time.

Of course, DOS 2.5 may solve all these problems.

## This chip is on our menu

I FOUND Mike Cook's article in the May issue of *Atari User* on the 6502 chip very interesting and informative.

Might I suggest you get him to write a similar article on the 68000 chip which will be used in the new 57 machines? I'm sure many of your readers would find it interesting as well as me. — **Frank Robinson, Milton Keynes, Bucks.**

■ Would you believe Mike has already written such an article? It should appear in next month's issue.

# ATARI USER

Take out a subscription and make sure you keep right up to date with all the exciting things now happening in the ever-expanding world of Atari!

## SAVE £2

with this introductory offer  
Subscribe NOW and pay only £18  
instead of the normal £12

The special introductory  
offer valid until June 30, 1985

**Keying in long  
programs too  
much of  
a chore?**



Then give your fingers a really sending for our monthly disc, containing all the programs from this issue. The June disc contains listings for:

**Frog Jump:** Guide the frog across the road and river to his home in this version of the arcade classic.

**1300KE Ram Power:** Use the extra 64k of memory to good effect, or use the driving routines to produce some pretty displays.

**Submarine:** Scuttle the submarines and practise a little coordinate geometry at the same time.

**Ditch-Sketch:** Draw pretty pictures with only a joystick.

**Random Numbers:** Get random numbers from machine code.

**Fifty Fifteen:** Can you keep the Fifty Fifteen happy in their cells for a week?

**Make the most of your Atari!**  
We'll bring you special offers at special prices - month after month!

### Look what's coming!

- Lots of easy-to-follow features on everything to do with Atari computing. Whether you're a beginner or an expert, you'll always find something to delight and intrigue you.
- In-depth independent evaluations of all the new hardware add-ons now being developed to make your Atari much more powerful and much more versatile.
- Reviews of all the very latest games, educational and business programs now being produced for the Atari.
- PLUS lots of things you will be able to buy in yourself - games, utilities, graphics.

## ORDER FORM

All prices include postage, packing and VAT and are valid to June 30.  
Please enter your requirements by ticking boxes.

<b>Annual subscription</b>	12 Issues	£18.00	<input type="checkbox"/>
	DATE (DD MM YY)	0000	<input type="checkbox"/>
	Quantity (Number 0-9)	000	<input type="checkbox"/>
	Quantity (Number 0-9)	000	<input type="checkbox"/>
* Special introductory offer		Continued with	Issue TOTAL

<b>Back issues</b>	May 1985	£0.00	<input type="checkbox"/>
£1.20 UK			
£1.50 Overseas			
		TOTAL	<input type="checkbox"/>

<b>Monthly Disc</b>	May Issue	20p	<input type="checkbox"/>
£2.00 UK & Overseas	Overseas	25p	<input type="checkbox"/>
		TOTAL	<input type="checkbox"/>

<b>Miracle Modem</b>	£1.95	£0.00	<input type="checkbox"/>
Including software and manuals		TOTAL	<input type="checkbox"/>

<b>Payment please indicate method of</b>	TOTAL	<input type="checkbox"/>
--	-------	--------------------------

☐ Access/Modem/Terminal

No. \_\_\_\_\_

☐ Backlog/Plus

No. \_\_\_\_\_

☐ Cheque/P2 made payable to Dorian Publications Ltd.

Name \_\_\_\_\_

Address \_\_\_\_\_

\_\_\_\_\_

\_\_\_\_\_

Signed \_\_\_\_\_

Send the Atari User, FREEPOST, Europe Home,  
68 Chester Road, Hazel Grove, Stockport SK7 5BN.  
The stamp needed if posted in UK. Please allow 10 days for delivery.  
**YOU CAN ALSO ORDER BY PHONE:**

051-488 0171  
(24 hours)

Don't forget to quote your credit card number and full address.

ATM

\*Atari 400/600/800 (48K)  
 \*BBC Model B "Tandy" 4/4 (32K)  
 \*Commodore-64 "Dragon" 32/64  
 \*Acorn Electron  
 \*ZX Spectrum 48K

## 747 Flight Simulator

from DACC - The Simulation specialists



Atari  
 screen  
 photograph

Unmatched and unbeatable for accuracy and realism - the DACC 747 Flight Simulator is the most successful of its kind on home computers. The only simulator which shows all the essential flight and engine instrumentation of the 747 jet as they really are - real data - and with a projected 3D view of the runway. The control and response of the 747 are faithfully reproduced using genuine aero-dynamics formulas. Start Options include take-off, random landing approach, passenger load fuel load selection, etc. You control the throttle, altimeter, ailerons, flaps, spoilers, landing gear, brakes, reverse thrust, etc. Joysticks and optional on all but Dragon and Tandy versions.

Cassette (9.95 inc. VAT and P&P)

Please state type of computer on order form,  
 and 02042 700 400/401/402/403

Order direct from

**DACC Ltd. (Dept. 4)**  
 22, Waverley Road, Hindley, Nr. Wigan,  
 Lancs. WN2 3BN.

High Quality - Low Cost

ATARI 400, 600,  
 800XL & 800XL

## SOFLOW software

182 Leicester Road, Nottingham,  
 Leicestershire. Tel: 05323 803270



## WHY NOT...

Learn with your Atari?

Your Computer is a superb Teacher - look at our range of **EDUCATIONAL SOFTWARE**

**SOFTSWOT**  
**MATHS 1 - GEOMETRY**  
**ENGLISH**

**£9.50**

nine programs

four programs

With voice soundtrack

© Level revision/teaching aid.

## TARITEACH

**£6.50**

**5000 RAGNAR ? - Great Britain & Ireland**

**2 - United States of America**

**3 - Europe**

**4 - Asia**

Learn the famous names

## HISTORY MAKERS

## FAMILY FUN

**£6.50**

**DOODLEBUG**

Drawing fun for all ages

**4 LETTER WORD**

"Mastermind" type word game

Write or phone for further details.

All prices are inclusive postage and insurance. All New and BBC copyright.  
 Free loan and postage. Trade enquiries invited.

## SUNARO SOFTWARE

### BEST FOR ATARI SOFTWARE

Order any two titles deduct £1 each

NAME	PRICE	NEW CASE	PRICE	NAME	PRICE
AMERICAN	12.95	AMERICAN	12.95	AMERICAN	12.95
AMERICAN	12.95	AMERICAN	12.95	AMERICAN	12.95
AMERICAN	12.95	AMERICAN	12.95	AMERICAN	12.95
AMERICAN	12.95	AMERICAN	12.95	AMERICAN	12.95
AMERICAN	12.95	AMERICAN	12.95	AMERICAN	12.95
AMERICAN	12.95	AMERICAN	12.95	AMERICAN	12.95
AMERICAN	12.95	AMERICAN	12.95	AMERICAN	12.95
AMERICAN	12.95	AMERICAN	12.95	AMERICAN	12.95
AMERICAN	12.95	AMERICAN	12.95	AMERICAN	12.95

See this website regularly on three

at your local price £ 9.95

**SUNARO SOFTWARE (AU)**

PO Box 15, Manchester, Cheshire M13 9PF

## ATARI 400/600/800/800XL

After our phenomenal success home computer on the market in obtaining  
 membership of **MIDLAND GAMES LIBRARY**.

The program "Puzzle" you have just played, on the market.

Our games are now available. All games, all games.

**MIDLAND GAMES LIBRARY**. The company, who over 2 years ago, first

introduced the idea of a software library.

Now, publishing more, 1,000 titles on the market, and first games, including

new titles and updates. Other publishers, including professional, including it

to be given all our members, for example, through adding approximately 10 new

computer libraries.

Over 1,000 new, published, including, more to be seen on market, Sweden, New

Germany, Ireland, Scotland and the

USA, different and finally, various. Members are awarded immediately on both

systems, you a 24 hour notice of service. Regular members and professional

systems, also other non-UK, including, New large a lot, too.

## MIDLAND GAMES LIBRARY

Box 40

40, Broadway, Bishop Cleeve, Cheshire, Chas.

Tel: 0243 67-4880 9.30-4.30

all our programmes are originals with full documentation

## RADFORD HI-FI ATARI MAIN STOCKISTS

Atari 800/1050 Starter Pack **£129.00**

Atari 800/1050 Disk Pack **£149.00**

Atari 1300E from stock **£169.00**

Atari 800XT. Prices for details

Minic Technology VHS2000 System - Multimediam  
 - Adapter £299.00

Atari / Analogue / Page 8 / Atari User

Your range of US and British software catalogues,  
 Printers, interfaces, manuals etc. 0201 6000.

52 Gloucester Road, Bristol, Avon.  
 Tel: Bristol 428447/428508

## SPECIAL DEAL FOR ATARI 400/800/XL/XE OWNERS

No. 1. Give your first 2 games FREE from our extensive range of  
 software. Up to the minute releases available.

No. 2. Buy all the latest software titles at best possible prices (free  
 releases available direct from US) Atari hardware and manuals  
 now available at discount prices. For further details send a.s.c. to:

## CHARNOCK GAMES

27 Warwick Avenue, Broom, Leicestershire

Tel: 0509 412884



# PSYCHEDELIA

*A Light Synthesiser*



32K £7.50

Hammerhead

AVAILABLE FROM H. SMITHS, BOOTS, WOLWORTHS AND MOST COMPUTER RETAILERS OR FROM  
HAMMERHEAD 49 MOUNT PLEASANT, TADLEY, HANTS (TEL. 00356 4476) SAE FOR CATALOGUE & NEWSLETTER  
"THE NATURE OF THE BEAST"